FAIRCHILD
SEMICONDUCTOR®

FPBL15SL60

Smart Power Module (SPM)

General Description

FPBL15SL60 is an advanced smart power module (SPM) that Fairchild has newly developed and designed to provide very compact and low cost, yet high performance ac motor drives mainly targeting low speed low-power inverter-driven application like air conditioners. It combines optimized circuit protection and drive matched to low-loss IGBTs. Highly effective short-circuit current detection/protection is realized through the use of advanced current sensing IGBT chips that allow continuous monitoring of the IGBTs current. System reliability is further enhanced by the integrated under-voltage lock-out protection. The high speed built-in HVIC provides opto-coupler-less IGBT gate driving capability that further reduce the overall size of the inverter system design. In addition the incorporated HVIC facilitates the use of single-supply drive topology enabling the FPBL15SL60 to be driven by only one drive supply voltage without negative bias.

Features

- UL Certified No. E209204
- 600V-15A 3-phase IGBT inverter bridge including control ICs for gate driving and protection
- Single-grounded power supply due to built-in HVIC
- Typical switching frequency of 3kHz
- Inverter power rating of 1kW / 100~253 Vac
- Isolation rating of 2500Vrms/min.
- Very low leakage current due to using ceramic substrate
- Adjustable current protection level by varying series resistor value with sense-IGBTs

Applications

- AC 100V ~ 253V three-phase inverter drive for small power (1kW) ac motor drives
- Home appliances applications requiring low switching frequency operation like air conditioners drive system
- Application ratings:
  - Power : 1kW / 100~253 Vac
  - Switching frequency : Typical 3kHz (PWM Control)
  - 100% load current : 7A (Irms)

External View and Marking Information




Fig. 1.

©2002 Fairchild Semiconductor Corporation

Integrated Power Functions

- 600V-15A IGBT inverter for three-phase DC/AC power conversion (Please refer to Fig. 3)

Integrated Drive, Protection and System Control Functions

- For inverter high-side IGBTs: Gate drive circuit, High voltage isolated high-speed level shifting
  Control circuit under-voltage (UV) protection
  Note) Available bootstrap circuit example is given in Figs. 10, 15 and 16.
- For inverter low-side IGBTs: Gate drive circuit, Short circuit protection (SC)
  Control supply circuit under-voltage (UV) protection
- Fault signaling: Corresponding to a SC fault (Low-side IGBTs) or a UV fault (Low-side supply)
- Input interface: 5V CMOS/LSTTL compatible, Schmitt trigger input

Pin Configuration

Top View




Fig. 2.

Pin Descriptions


Pin Number	Pin Name	Pin Description
1	$V_{CC(L)}$	Low-side Common Bias Voltage for IC and IGBTs Driving
2	$COM_{(L)}$	Low-side Common Supply Ground
3	$IN_{(UL)}$	Signal Input Terminal for Low-side U Phase
4	$IN_{(VL)}$	Signal Input Terminal for Low-side V Phase
5	$IN_{(WL)}$	Signal Input Terminal for Low-side W Phase
6	V_{FO}	Fault Output Terminal
7	C_{FOD}	Capacitor for Fault Output Duration Time Selection
8	C_{SC}	Capacitor (Low-pass Filter) for Short-current Detection Input
9	R_{SC}	Resistor for Short-circuit Current Detection
10	NC	No Connection
11	NC	No Connection
12	NC	No Connection
13	W	Output Terminal for W Phase
14	V	Output Terminal for V Phase
15	U	Output Terminal for U Phase
16	N	Negative DC–Link Input

©2002 Fairchild Semiconductor Corporation

Pin Descriptions (Continued)

Pin Number	Pin Name	Pin Description
17	P	Positive DC–Link Input
18	$IN_{(WH)}$	Signal Input Terminal for High-side W Phase
19	$V_{CC(WH)}$	High-side Bias Voltage for W Phase IC
20	$V_{B(W)}$	High-side Bias Voltage for W Phase IGBT Driving
21	$V_{S(W)}$	High-side Bias Voltage Ground for W Phase IGBT Driving
22	$COM_{(H)}$	High-side Common Supply Ground
23	$IN_{(VH)}$	Signal Input Terminal for High-side V Phase
24	$V_{CC(VH)}$	High-side Bias Voltage for V Phase IC
25	$V_{B(V)}$	High-side Bias Voltage for V Phase IGBT Driving
26	$V_{S(V)}$	High-side Bias Voltage Ground for V Phase IGBT Driving
27	$IN_{(UH)}$	Signal Input Terminal for High-side U Phase
28	$V_{CC(UH)}$	High-side Bias Voltage for U Phase IC
29	$V_{B(U)}$	High-side Bias Voltage for U Phase IGBT Driving
30	$V_{S(U)}$	High-side Bias Voltage Ground for U Phase IGBT Driving

Internal Equivalent Circuit and Input/Output Pins



Note

1. Inverter low-side ((1) - (12) pins) is composed of three sense-IGBTs including freewheeling diodes for each IGBT and one control IC which has gate driving, current sensing and protection functions.
2. Inverter power side ((13) - (17) pins) is composed of two inverter dc-link input terminals and three inverter output terminals.
3. Inverter high-side ((18) - (30) pins) is composed of three normal-IGBTs including freewheeling diodes and three drive ICs for each IGBT.

Fig. 3.

©2002 Fairchild Semiconductor Corporation

Absolute Maximum Ratings

Inverter Part (T_C = 25°C, Unless Otherwise Specified)

Item	Symbol	Condition	Rating	Unit
Supply Voltage	V_{DC}	Applied to DC - Link	450	V
Supply Voltage (Surge)	$V_{PN(Surge)}$	Applied between P- N	500	V
Collector-Emitter Voltage	V_{CES}		600	V
Each IGBT Collector Current	$\pm I_C$	T_C = 25°C (Note Fig. 4)	15	A
Each IGBT Collector Current (Peak)	$\pm I_{CP}$	T_C = 25°C (Note Fig. 4)	30	A
Collector Dissipation	P_C	T_C = 25°C per One Chip	47	W
Operating Junction Temperature	T_J	(Note 1)	-55 ~ 150	°C

Note
1. It would be recommended that the average junction temperature should be limited to $T_J \leq 125°C$ ($@T_C \leq 100°C$) in order to guarantee safe operation.

Control Part (T_C = 25°C, Unless Otherwise Specified)

Item	Symbol	Condition	Rating	Unit
Control Supply Voltage	V_{CC}	Applied between $V_{CC(H)}$ - $COM_{(H)}$, $V_{CC(L)}$ - $COM_{(L)}$	18	V
High-side Control Bias Voltage	V_{BS}	Applied between $V_{B(U)}$ - $V_{S(U)}$, $V_{B(V)}$ - $V_{S(V)}$, $V_{B(W)}$ - $V_{S(W)}$	20	V
Input Signal Voltage	V_{IN}	Applied between $IN_{(UH)}$, $IN_{(VH)}$, $IN_{(WH)}$ - $COM_{(H)}$ $IN_{(UL)}$, $IN_{(VL)}$, $IN_{(WL)}$ - $COM_{(L)}$	-0.3 ~ 6.0	V
Fault Output Supply Voltage	V_{FO}	Applied between V_{FO} - $COM_{(L)}$	-0.3~V_{CC}+0.5	V
Fault Output Current	I_{FO}	Sink Current at V_{FO} Pin	5	mA
Current Sensing Input Voltage	V_{SC}	Applied between C_{SC} - $COM_{(L)}$	-0.3~V_{CC}+0.5	V

Total System

Item	Symbol	Condition	Rating	Unit
Self Protection Supply Voltage Limit (Short Circuit Protection Capability)	$V_{DC(PROT)}$	Applied to DC - Link, V_{CC} = V_{BS} = 13.5 ~ 16.5V T_J = 125°C, Non-repetitive, less than 6µs	400	V
Module Case Operation Temperature	T_C	Note Fig. 4	-20 ~ 100	°C
Storage Temperature	T_{STG}		-55 ~ 150	°C
Isolation Voltage	V_{ISO}	60Hz, Sinusoidal, AC 1 minute, Connection Pins to Heat-sink Plate	2500	V_{rms}

©2002 Fairchild Semiconductor Corporation




Fig. 4. T_c Measurement Point

©2002 Fairchild Semiconductor Corporation

Absolute Maximum Ratings

Thermal Resistance

Item	Symbol	Condition	Min.	Typ.	Max.	Unit
Junction to Case Thermal Resistance	$R_{th(j-c)Q}$	Each IGBT under Inverter Operating Condition (Note 2)	-	-	2.61	°C/W
	$R_{th(j-c)F}$	Each FWDi under Inverter Operating Condition (Note 2)	-	-	3.73	°C/W
Contact Thermal Resistance	$R_{th(c-f)}$	Ceramic Substrate (per 1 Module) Thermal Grease Applied	-	-	0.06	°C/W

Note
2. For the measurement point of case temperature (T_c), please refer to Fig. 4.


Electrical Characteristics

Inverter Part (T_j = 25°C, Unless Otherwise Specified)

Item	Symbol	Condition		Min.	Typ.	Max.	Unit
Collector - Emitter Saturation Voltage	$V_{CE(SAT)}$	$V_{CC} = V_{BS}$ = 15V, V_{IN} = 0V	I_C = 15A, T_j = 25°C	-	-	2.3	V
			I_C = 15A, T_j = 125°C	-	-	2.4	V
FWDi Forward Voltage	V_{FM}	V_{IN} = 5V	I_C = 15A, T_j = 25°C	-	-	2.5	V
			I_C = 15A, T_j = 125°C	-	-	2.3	V
Switching Times	t_{ON}	V_{PN} = 300V, $V_{CC} = V_{BS}$ = 15V, I_C = 15A, T_j = 25°C, V_{IN} = 5V ↔ 0V, Inductive Load (High-Low Side)		-	0.39	-	µs
	$t_{C(ON)}$			-	0.12	-	µs
	t_{OFF}			-	1.0	-	µs
	$t_{C(OFF)}$			-	0.6	-	µs
	t_{rr}	(Note 3)		-	0.1	-	µs
Collector - Emitter Leakage Current	I_{CES}	$V_{CE} = V_{CES}$, T_j = 25°C		-	-	250	µA


Note
3. t_{ON} and t_{OFF} include the propagation delay time of the internal drive IC. $t_{C(ON)}$ and $t_{C(OFF)}$ are the switching time of IGBT itself under the given gate driving condition internally. For the detailed information, please see Fig. 5.

©2002 Fairchild Semiconductor Corporation



(a) Turn-on (b) Turn-off

Fig 5. Switching Time Definition



(a) Turn-on (b) Turn-off

Fig. 6. Experimental Results of Switching Waveforms
Test Condition: Vdc=300V, Vcc=15V, L=500uH (Inductive Load), T_C=25°C

©2002 Fairchild Semiconductor Corporation

Electrical Characteristics

Control Part (T_j = 25°C, Unless Otherwise Specified)

Item	Symbol	Condition		Min.	Typ.	Max.	Unit
Control Supply Voltage	V_{CC}	Applied between $V_{CC(H)}$,$V_{CC(L)}$ - COM		13.5	15	16.5	V
High-Side Bias Voltage	V_{BS}	Applied between $V_{B(U)}$ - $V_{S(U)}$, $V_{B(V)}$ - $V_{S(V)}$, $V_{B(W)}$ - $V_{S(W)}$		13.5	15	16.5	V
Quiescent V_{CC} Supply Current	I_{QCCL}	V_{CC} = 15V $IN_{(UL, VL, WL)}$ = 5V	$V_{CC(L)}$ - $COM_{(L)}$	-	-	26	mA
	I_{QCCH}	V_{CC} = 15V $IN_{(UH, VH, WH)}$ = 5V	$V_{CC(U)}$, $V_{CC(V)}$, $V_{CC(W)}$ - $COM_{(H)}$	-	-	130	uA
Quiescent V_{BS} Supply Current	I_{QBS}	V_{BS} = 15V $IN_{(UH, VH, WH)}$ = 5V	$V_{B(U)}$ - $V_{S(U)}$, $V_{B(V)}$ -$V_{S(V)}$, $V_{B(W)}$ - $V_{S(W)}$	-	-	420	uA
Fault Output Voltage	V_{FOH}	V_{SC} = 0V, V_{FO} Circuit: 4.7kΩ to 5V Pull-up		4.5	-	-	V
	V_{FOL}	V_{SC} = 1V, V_{FO} Circuit: 4.7kΩ to 5V Pull-up		-	-	1.1	V
PWM Input Frequency	f_{PWM}	$T_C \le 100°C$, $T_J \le 125°C$		-	3	-	kHz
Allowable Input Signal Blanking Time Considering Leg Arm-Short	t_{dead}	$-20°C \le T_C \le 100°C$		3	-	-	us
Short Circuit Trip Level	$V_{SC(ref)}$	T_J = 25°, V_{CC} = 15V (Note 4)		0.45	0.51	0.56	V
Sensing Voltage of IGBT Current	V_{SEN}	$-20°C \le T_C \le 100°C$, @ R_{SC} = 82 Ω and I_C = 15A (Note Fig. 7)		0.37	0.45	0.56	V
Supply Circuit Under-Voltage Protection	UV_{CCD}	$T_J \le 125°C$	Detection Level	11.5	12	12.5	V
	UV_{CCR}		Reset Level	12	12.5	13	V
	UV_{BSD}		Detection Level	7.3	9.0	10.8	V
	UV_{BSR}		Reset Level	8.6	10.3	12	V
Fault-Out Pulse Width	t_{FOD}	V_{CC} = 15V, C(sc) = 1V C_{FOD} = 33nF (Note 5)		1.4	1.8	2.0	ms
ON Threshold Voltage	$V_{IN(ON)}$	High-Side	Applied between $IN_{(UH)}$, $IN_{(VH)}$, $IN_{(WH)}$ - $COM_{(H)}$	-	-	0.8	V
OFF Threshold Voltage	$V_{IN(OFF)}$			3.0	-	-	V
ON Threshold Voltage	$V_{IN(ON)}$	Low-Side	Applied between $IN_{(UL)}$, $IN_{(VL)}$, $IN_{(WL)}$ - $COM_{(L)}$	-	-	0.8	V
OFF Threshold Voltage	$V_{IN(OFF)}$			3.0	-	-	V

Note

4. Short-circuit current protection is functioning only at the low-sides. It would be recommended that the value of the external sensing resistor (R_{SC}) should be selected around 56 Ω in order to make the SC trip-level of about 20A.
   Please refer to Fig. 7 which shows the current sensing characteristics according to sensing resistor R_{SC}.
5. The fault-out pulse width t_{FOD} depends on the capacitance value of C_{FOD} according to the following approximate equation : $C_{FOD} = 18.3 \times 10^{-6} \times t_{FOD}$[F]

©2002 Fairchild Semiconductor Corporation




Fig. 7. Relationship between Sensing Resistor and SC Trip Current for Short-Circuit Protection (I_{SC} = 82 × Rating Current(15A) / R_{SC})

©2002 Fairchild Semiconductor Corporation

Mechanical Characteristics and Ratings

Item	Condition		Limits			Units
			Min.	Typ.	Max.	
Mounting Torque	Mounting Screw: M3 (Note 6 and 7)	Recommended 10kg•cm	8	10	12	Kg•cm
		Recommended 0.98N•m	0.78	0.98	1.17	N•m
Ceramic Flatness		(Note Fig. 8)	0	-	+100	um
Weight			-	56	-	g




Fig. 8. Flatness Measurement Position of The Ceramic Substrate

Note

6. Do not make over torque or mounting screws. Much mounting torque may cause ceramic cracks and bolts and Al heat-fin destruction.
7. Avoid one side tightening stress. Fig.9 shows the recommended torque order for mounting screws. Uneven mounting can cause the SPM ceramic substrate to be damaged.





Fig. 9. Mounting Screws Torque Order (1 → 2 → 3 → 4)

©2002 Fairchild Semiconductor Corporation

Recommended Operating Conditions

Item	Symbol	Condition	Value			Unit
			Min.	Typ.	Max.	
Supply Voltage	V_{PN}	Applied between P - N	-	300	400	V
Control Supply Voltage	V_{CC}	Applied between $V_{CC(H)}$ - $COM_{(H)}$, $V_{CC(L)}$ - $COM_{(L)}$	13.5	15	16.5	V
High-Side Bias Voltage	V_{BS}	Applied between $V_{B(U)}$ - $V_{S(U)}$, $V_{B(V)}$ - $V_{S(V)}$, $V_{B(W)}$ - $V_{S(W)}$	13.5	15	16.5	V
Blanking Time for Preventing Arm-short	t_{dead}	For Each Input Signal	3	-	-	us
PWM Input Signal	f_{PWM}	$T_C \leq 100°C$, $T_J \leq 125°C$	-	3	-	kHz
Input ON Threshold Voltage	$V_{IN(ON)}$	Applied between U_{IN},V_{IN}, W_{IN} - COM	0 ~ 0.65			V
Input OFF Threshold Voltage	$V_{IN(OFF)}$	Applied between U_{IN},V_{IN}, W_{IN} - COM	4 ~ 5.5			V

ICs Internal Structure and Input/Output Conditions




Note

1. One LVIC drives three Sense-IGBTs and can do short-circuit current protection also. Three sense emitters are commonly connected to R_{SC} terminal to detect short-circuit current. Low-side part of the inverter consists of three sense-IGBTs
2. One HVIC drives one normal-IGBT. High-side part of the inverter consists of three normal-IGBTs
3. Each IC has under voltage detection and protection function.
4. The logic input is compatible with standard CMOS or LSTTL outputs.
5. R_PC_P coupling at each input/output is recommended in order to prevent the gating input/output signals oscillation and it should be as close as possible to each SPM gating input pin.
6. It would be recommended that the bootstrap diode, D_{BS}, has soft and fast recovery characteristics.

Fig. 10.


©2002 Fairchild Semiconductor Corporation

Time Charts of SPMs Protective Function



P1 : Normal operation - IGBT ON and conducting current
P2 : Under voltage detection
P3 : IGBT gate interrupt
P4 : Fault signal generation
P5 : Under voltage reset
P6 : Normal operation - IGBT ON and conducting current


Fig. 11. Under-Voltage Protection (Low-side)



P1 : Normal operation - IGBT ON and conducting current
P2 : Under voltage detection
P3 : IGBT gate interrupt
P4 : No fault signal
P5 : Under voltage reset
P6 : Normal operation - IGBT ON and conducting current


Fig. 12. Under-Voltage Protection (High-side)

©2002 Fairchild Semiconductor Corporation



P1 : Normal operation - IGBT ON and conducting currents
P2 : Short-circuit current detection
P3 : IGBT gate interrupt / Fault signal generation
P4 : IGBT is slowly turned off
P5 : IGBT OFF signal
P6 : IGBT ON signal - but IGBT cannot be turned on during the fault-output activation
P7 : IGBT OFF state
P8 : Fault-output reset and normal operation start

Fig. 13. Short-circuit Current Protection (Low-side Operation only)



Note
It would be recommended that by-pass capacitors for the gating input signals, $IN_{(XX)}$ should be placed on the SPM pins and on the both sides of CPU and SPM for the fault output signal, V_{FO}, as close as possible.

Fig. 14. Recommended CPU I/O Interface Circuit

©2002 Fairchild Semiconductor Corporation





Fig. 15. Recommended Bootstrap Operation Circuit and Parameters

©2002 Fairchild Semiconductor Corporation




Note

1. $R_P C_{PL}/R_P C_{PH}$ coupling at each SPM input is recommended in order to prevent input signals' oscillation and it should be as close as possible to each SPM input pin.
2. By virtue of integrating an application specific type HVIC inside the SPM, direct coupling to CPU terminals without any opto-coupler or transformer isolation is possible.
3. V_{FO} output is open collector type. This signal line should be pulled up to the positive side of the 5V power supply with approximately 4.7kΩ resistance. Please refer to Fig. 14.
4. C_{SP15} of around 7 times larger than bootstrap capacitor C_{BS} is recommended.
5. V_{FO} output pulse width should be determined by connecting an external capacitor(C_{FOD}) between C_{FOD}(pin7) and $COM_{(L)}$(pin2). (Example : if C_{FOD} = 5.6 nF, then t_{FO} = 300 μs (typ.)) Please refer to the note 5 for calculation method.
6. Each input signal line should be pulled up to the 5V power supply with approximately 4.7kΩ resistance (other RC coupling circuits at each input may be needed depending on the PWM control scheme used and on the wiring impedance of the system's printed circuit board). Approximately a 0.22~2nF by-pass capacitor should be used across each power supply connection terminals.
7. To prevent errors of the protection function, the wiring around R_{SC}, R_F and C_{SC} should be as short as possible.
8. In the short-circuit protection circuit, please select the $R_F C_{SC}$ time constant in the range 3~4 μs. R_F should be at least 30 times larger than R_{SC}. (Recommended Example: R_{SC} = 56 Ω, R_F = 3.9kΩ and C_{SC} = 1nF)
9. Each capacitor should be mounted as close to the pins of the SPM as possible.
10. To prevent surge destruction, the wiring between the smoothing capacitor and the P&N pins should be as short as possible. The use of a high frequency non-inductive capacitor of around 0.1~0.22 uF between the P&N pins is recommended.
11. Relays are used at almost every systems of electrical equipments of home appliances. In these cases, there should be sufficient distance between the CPU and the relays. It is recommended that the distance be 5cm at least

Fig. 16. Application Circuit

©2002 Fairchild Semiconductor Corporation

Detailed Package Outline Drawings



©2002 Fairchild Semiconductor Corporation

TRADEMARKS

The following are registered and unregistered trademarks Fairchild Semiconductor owns or is authorized to use and is not intended to be an exhaustive list of all such trademarks.

ACEx™	FAST®	OPTOLOGIC™	SMART START™	VCX™
Bottomless™	FASTr™	OPTOPLANAR™	STAR*POWER™	
CoolFET™	FRFET™	PACMAN™	Stealth™	
CROSSVOLT™	GlobalOptoisolator™	POP™	SuperSOT™-3	
DenseTrench™	GTO™	Power247™	SuperSOT™-6	
DOME™	HiSeC™	PowerTrench®	SuperSOT™-8	
EcoSPARK™	ISOPLANAR™	QFET™	SyncFET™	
E^2CMOS™	LittleFET™	QS™	TruTranslation™	
EnSigna™	MicroFET™	QT Optoelectronics™	TinyLogic™	
FACT™	MicroPak™	Quiet Series™	UHC™	
FACT Quiet Series™	MICROWIRE™	SLIENT SWITCHER®	UltraFET®	

STAR*POWER is used under license

DISCLAIMER

FAIRCHILD SEMICONDUCTOR RESERVES THE RIGHT TO MAKE CHANGES WITHOUT FURTHER NOTICE TO ANY PRODUCTS HEREIN TO IMPROVE RELIABILITY, FUNCTION OR DESIGN. FAIRCHILD DOES NOT ASSUME ANY LIABILITY ARISING OUT OF THE APPLICATION OR USE OF ANY PRODUCT OR CIRCUIT DESCRIBED HEREIN; NEITHER DOES IT CONVEY ANY LICENSE UNDER ITS PATENT RIGHTS, NOR THE RIGHTS OF OTHERS.

LIFE SUPPORT POLICY

FAIRCHILD'S PRODUCTS ARE NOT AUTHORIZED FOR USE AS CRITICAL COMPONENTS IN LIFE SUPPORT DEVICES OR SYSTEMS WITHOUT THE EXPRESS WRITTEN APPROVAL OF FAIRCHILD SEMICONDUCTOR CORPORATION.

As used herein:

1. Life support devices or systems are devices or systems which, (a) are intended for surgical implant into the body, or (b) support or sustain life, or (c) whose failure to perform when properly used in accordance with instructions for use provided in the labeling, can be reasonably expected to result in significant injury to the user.

2. A critical component is any component of a life support device or system whose failure to perform can be reasonably expected to cause the failure of the life support device or system, or to affect its safety or effectiveness.

PRODUCT STATUS DEFINITIONS

Definition of Terms

Datasheet Identification	Product Status	Definition
Advance Information	Formative or In Design	This datasheet contains the design specifications for product development. Specifications may change in any manner without notice.
Preliminary	First Production	This datasheet contains preliminary data, and supplementary data will be published at a later date. Fairchild Semiconductor reserves the right to make changes at any time without notice in order to improve design.
No Identification Needed	Full Production	This datasheet contains final specifications. Fairchild Semiconductor reserves the right to make changes at any time without notice in order to improve design.
Obsolete	Not In Production	This datasheet contains specifications on a product that has been discontinued by Fairchild semiconductor. The datasheet is printed for reference information only.

©2002 Fairchild Semiconductor Corporation

Стандарт Электрон Связь

Мы молодая и активно развивающаяся компания в области поставок электронных компонентов. Мы поставляем электронные компоненты отечественного и импортного производства напрямую от производителей и с крупнейших складов мира.

Благодаря сотрудничеству с мировыми поставщиками мы осуществляем комплексные и плановые поставки широчайшего спектра электронных компонентов.

Собственная эффективная логистика и склад в обеспечивает надежную поставку продукции в точно указанные сроки по всей России.

Мы осуществляем техническую поддержку нашим клиентам и предпродажную проверку качества продукции. На все поставляемые продукты мы предоставляем гарантию .

Осуществляем поставки продукции под контролем ВП МО РФ на предприятия военно-промышленного комплекса России , а также работаем в рамках 275 ФЗ с открытием отдельных счетов в уполномоченном банке. Система менеджмента качества компании соответствует требованиям ГОСТ ISO 9001.

Минимальные сроки поставки, гибкие цены, неограниченный ассортимент и индивидуальный подход к клиентам являются основой для выстраивания долгосрочного и эффективного сотрудничества с предприятиями радиоэлектронной промышленности, предприятиями ВПК и научно-исследовательскими институтами России.

С нами вы становитесь еще успешнее!

Наши контакты:

Телефон: +7 812 627 14 35

Электронная почта: sales@st-electron.ru

Адрес: 198099, Санкт-Петербург, Промышленная ул, дом № 19, литера Н, помещение 100-Н Офис 331