ULTRA HIGH SPEED SINGLE OPERATIONAL AMPLIFIER

■ GENERAL DESCRIPTION

The **NJM2712** is an ultra high speed dual operational amplifier.

It can swings 260V/μs high slew rate and 1GHz gain band width product(10MHz typ. at 40dB) at ±2.5V.

It is suitable for pickup circuit of CD-R/RW or DVD-R/RW, wideband video system, high resolution scanner or FAX, high speed telecommunications, and any other high speed signal processing system.

■ PACKAGR OUTLINE



NJM2712M

NJU2712RB1

■ FEATURES

- Operating Voltage (±2.0 to ±4.5V)
- Operating Current (3.8mA typ. at V^+/V^-=±2.5V)
- High Slew Rate (260V/μs typ.)
- Gain Bandwidth Product (1GHz typ.)
  Bandwidth (10MHz typ. at 40dB)
- Unity Gain Bandwidth (180MHz typ.)
- Input Offset Voltage (7mV max.)
- Maximum Output Voltage (±1.5V typ. at R_L=1kΩ)
- Open Loop Voltage Gain (75dB typ.)
- Bipolar Technology
- Package Outline DMP8,TVSP8

■ PIN CONFIGURATION

NJM2712M
NJM2712RB1
(Top View)



PIN FUNCTION

1.OUTPUT1
2.-INPUT1
3.+INPUT1
4.V^-
5.+INPUT2
6.-INPUT2
7.OUTPUT2
8.V^+

■ ABSOLUTE MAXIMUM RATINGS (Ta=25°C)

PARAMETER	SYMBOL	RATINGS	UNIT
Supply Voltage	V^+	10	V
Differential Input Voltage	V_{ID}	±2	V
Power Dissipation	P_D	200	mW
Operating Temperature Range	Topr	-40 to +85	°C
Storage Temperature Range	Tstg	-50 to +150	°C

■RECOMMENDED OPERATING CONDITION (Ta=25°C)

PARAMETER	SYMBOL	TEST CONDITION	MIN	TYP	MAX	UNIT
Operating Voltage Range	V^+/V^-		2.0	2.5	4.5	V

■ DC CHARACTERISTICS (V^+/V^-=±2.5V, Ta=25°C)

PARAMETER	SYMBOL	TEST CONDITION	MIN	TYP	MAX	UNIT
Operating Current	I_{CC}	No Signal	-	3.8	6.8	mA
Input Offset Voltage	V_{IO}		-	2.0	7.0	mV
Input Bias Current	I_B		-	2	7	μA
Input Offset Current	I_{IO}		-	350	900	nA
Open Loop Voltage Gain	Av	R_L=2kΩ	65	75	-	dB
Input Common Mode Voltage Range	V_{ICM}		±1.3	±1.5	-	V
Common Mode Rejection	CMR	-1V≤V_{CM}≤+1V	50	60	-	dB
Supply Voltage Rejection	+SVR	2.5V≤V^+≤5V, R_L=2kΩ	50	60	-	dB
	-SVR	-5V≤V^-≤-2.5V, R_L=2kΩ	50	60	-	dB
Maximum Output Voltage	V_{OM}	R_L=1kΩ	±1.2	±1.5	-	V

■ AC CHARACTERISTICS (V^+/V^-=±2.5V, Ta=25°C)

PARAMETER	SYMBOL	TEST CONDITION	MIN	TYP	MAX	UNIT
Bandwidth	BW	Av=40dB,R_f=1.98kΩ ,R_L=∞ C_L=10pF	-	10	-	MHz
Unity Gain Bandwidth	f_T	Av=40dB,Rg=20Ω,R_f=1.98kΩ R_L=∞,C_L=10pF	-	180	-	MHz
Phase Margin	ϕ_M	Av=40dB,Rg=20Ω,R_f=1.98kΩ R_L=∞,C_L=10pF	-	38	-	deg
Equivalent Input Noise Voltage	V_{NI}		-	6.8	-	nV/√Hz

■ TRANSIENT CHARACTERISTICS (V^+/V^-=±2.5V, Ta=25°C)

PARAMETER	SYMBOL	TEST CONDITION	MIN	TYP	MAX	UNIT
Slew Rate	+SR	Av=6dB,R_f=1kΩ,Rg=1kΩ R_L=∞,CL=10pF	-	260	-	V/μs
	-SR		-	260	-	V/μs

■ Note:

non-inverting amplifier

1.The closed gain should be 6dB or higher to prevent the oscillation.
Unity gain follower application may cause the oscillation.
2.When the closed gain is lower than 20dB, use a compensation capacitor (CF: about 5pF), parallel with the feedback resistor RF to avoid oscillation.
3.Recommended feedback resistor is less than 2k-ohom to keep the flatness of the frequency response.
4.Minimize the load capacitor for the better performance.
A large load capacitor CL reduces the frequency response and causes oscillation or ringing.

inverting amplifier

1.When the closed gain is lower than 20dB, use a compensation capacitor (CF; recommended from 1pF to 5pF), parallel with the feedback resistor RF to avoid oscillation.
2.Minimize the feedback resistor to keep the frequency response and the slew rate. (recommended about 1k-ohm)
The proper compensation capacitor CF can counteract oscillation even with a large feedback resistor RF.
3.Total load capacitance should be not more than 100pF.
The oscillation margin may be affected by the total load capacitance.

non-inverting amplifier



inverting amplifier



■ TYPICAL CHARACTERISTICS

Operating Current vs.Operating Voltage



Operating Current vs. Ambient Temperature



Input Offset Voltage
vs. Ambient Temperature



Input Offset Current
vs. Ambient Temperature



Input Bias Current
vs. Ambient Temperature



Maximum Output Voltage Swing
vs. Operating Voltage



Maximum Output Voltage Swing
vs. Ambient Temperature

V^+/V^-=±2.5V



Voltage Gain vs. Ambient Temperature

V^+/V^-=±2.5V,RL=2kΩ



Common Mode Rejection Ratio
vs. Ambient Temperature

V^+/V^-=±2.5V,-1V<Vcm<+1V



V^+ Supply Voltage Rejection Ratio
vs. Ambient Temperature

V^-=-2.5V,+2.5V<V^+<+5V,RL=2kΩ



V^- Supply Voltage Rejection Ratio
vs. Ambient Temperature

V^+=+2.5V,-5V<V^-<-2.5V,RL=2kΩ



Pulse Responce

V^+/V^-=±2.5V,f=5MHz,V_O=2VPP,G_V=6dB,R_T=50Ω,
R_F=1kΩ,C_F=5pF,R_G=1kΩ,R_L=2kΩ,C_L=10pF,Ta=+25℃



Pulse Response (with capacitive load)

V^+/V^-=±2.5V,f=5MHz,V_O=2VPP,G_V=6dB,
R_T=50Ω,R_F=1kΩ,C_F=5pF,R_G=1kΩ,Ta=+25℃



Pulse Response (correlation with RL)

V^+/V^-=±2.5V,f=5MHz,V_O=2V_{PP},G_V=6dB,R_T=50Ω,
R_F=1kΩ,C_F=5pF,R_G=1kΩ,C_L=10pF,Ta=+25℃



Pulse Response (correlation with Ta)

V^+/V^-=±2.5V,f=5MHz,V_O=2VPP,G_V=6dB,R_T=50Ω,
R_F=1kΩ,C_F=5pF,R_G=1kΩ,C_L=10pF,Ta=+25℃



Voltage Gain vs. Frequency

V^+/V^-=±2.5V,V_{IN}=0.02Vpp,G_V=40dB,R_T=50Ω,
R_F=1.98kΩ,R_G=20Ω,C_F=5pF,R_L=2kΩ,C_L=10pF,Ta=+25℃



Voltege Gain vs. Frequency (with Capacitive Load)

V^+/V^-=±2.5V,V_{IN}=0.02Vpp,G_V=40dB,R_T=50Ω,
R_F=1.98kΩ,R_G=20Ω,C_F=5pF,R_L=2kΩ,Ta=+25℃



Voltage Gain vs. Frequency
(correlation with RL)

V^+/V^-=±2.5V,V_{IN}=0.02Vpp,G_V=40dB,R_T=50Ω,
R_F=1.98kΩ,R_G=20Ω,C_F=5pF,C_L=10pF,Ta=+25℃



Voltage Gain vs. Frequency
(correlation with Ta)

V^+/V^-=±2.5V,V_{IN}=0.02Vpp,G_V=40dB,R_T=50Ω, R_F=1.98kΩ,
R_G=20Ω,C_F=5pF,R_L=open,C_L=10pF



Voltage Gain vs. Frequency(with Capacitive Load)

V^+/V^-=±2.5V,V_{IN}=0.02Vpp,G_V=20dB,R_T=50Ω,
R_F=1kΩ,C_F=5pF,R_G=110Ω,R_L=open,Ta=+25℃



Voltage Gain vs. Frequency (with Capacitive Load)

V^+/V^-=±2.5V,V_{IN}=0.02Vpp,G_V=6dB,R_T=50Ω,
R_F=1kΩ,C_F=5pF,R_G=1kΩ,R_L=open,Ta=+25℃



■ MEASUREMENT CIRCUIT



[CAUTION]
The specifications on this databook are only given for information , without any guarantee as regards either mistakes or omissions. The application circuits in this databook are described only to show representative usages of the product and not intended for the guarantee or permission of any right including the industrial rights.

Mouser Electronics

Authorized Distributor

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

NJR:

NJM2712M-TE1 NJM2712M NJM2712RB1-TE1

Стандарт Электрон Связь

Мы молодая и активно развивающаяся компания в области поставок электронных компонентов. Мы поставляем электронные компоненты отечественного и импортного производства напрямую от производителей и с крупнейших складов мира.

Благодаря сотрудничеству с мировыми поставщиками мы осуществляем комплексные и плановые поставки широчайшего спектра электронных компонентов.

Собственная эффективная логистика и склад в обеспечивает надежную поставку продукции в точно указанные сроки по всей России.

Мы осуществляем техническую поддержку нашим клиентам и предпродажную проверку качества продукции. На все поставляемые продукты мы предоставляем гарантию .

Осуществляем поставки продукции под контролем ВП МО РФ на предприятия военно-промышленного комплекса России , а также работаем в рамках 275 ФЗ с открытием отдельных счетов в уполномоченном банке. Система менеджмента качества компании соответствует требованиям ГОСТ ISO 9001.

Минимальные сроки поставки, гибкие цены, неограниченный ассортимент и индивидуальный подход к клиентам являются основой для выстраивания долгосрочного и эффективного сотрудничества с предприятиями радиоэлектронной промышленности, предприятиями ВПК и научно-исследовательскими институтами России.

С нами вы становитесь еще успешнее!

Наши контакты:

Телефон: +7 812 627 14 35

Электронная почта: sales@st-electron.ru

Адрес: 198099, Санкт-Петербург,
Промышленная ул, дом № 19, литера Н,
помещение 100-Н Офис 331