

RFLA9003

Dual Low Noise Amplifier Module 1710MHz to 2180MHz

RFMD's RFLA9003 is a dual Low Noise Amplifier module with external connections to both LNAs. These LNAs feature a shutdown mode to turn off the LNA and provide up to 15dBm drive level without gain expansion and self-biasing in shutdown mode. Noise figure of 1.2dB and input P1dB of -3.5dBm make this component ideal for receiver input lineups. The RFLA9003 is packaged in a small 4.0mm x 4.0mm leadless laminate MCM. This module is internally matched to 50Ω on all RF ports making it easy to use with no external matching components required.



Functional Block Diagram

Ordering Information

RFLA9003SQ	Sample bag with 25 pieces
RFLA9003SR	7" Reel with 100 pieces
RFLA9003TR13	13" Reel with 2500 pieces
RFLA9003PCK-410	1710MHz to 2180MHz PCBA with 5-piece sample bag



Package: MCM, 24-pin, 4.0mm x 4.0mm

Features

- Frequency Range 1710MHz to 2180MHz
- Internally Matched to 50Ω on all RF Ports
- Shutdown Mode with +40dB Isolation
- Gain = >15dB per LNA
- Noise Figure of 1.2dB Typical
- Single +4.0V Supply
- Small 24-Pin, 4.0mm x 4.0mm, Multi-Chip Module (MCM)

Applications

- Cellular Repeaters
- General Purpose LNA

RF Micro Devices Inc. 7628 Thorndike Road, Greensboro, NC 27409-9421 For sales or technical support, contact RFMD at +1.336.678.5570 or customerservice@rfmd.com. DS131114

RF MICRO DEVICES[®] and RFMD[®] are trademarks of RFMD, LLC. BLUETOOTH is a trademark owned by Bluetooth SIG, Inc., U.S.A. and licensed for use by RFMD. All other trade names, trademarks, and registered trademarks are the property of their respective owners. ©2013, RF Micro Devices, Inc.



Absolute Maximum Ratings

Parameter	Rating	Unit
Supply Voltage	+5.5	V _{DC}
Control Voltage	+5.5	V _{DC}
DC Supply Current	130	mA
Power Dissipation	770	mW
Max RF Input Power	15	dBm
Operating Temperature (T _{CASE})	-40 to +85	°C
Storage Temperature Range	-40 to +150	°C
Junction Temperature (T _J)	150	°C
ESD Rating - Human Body Model (HBM)	1000 (Class 1C)	V
Moisture Sensitivity Level	MSL3	





RFMD Green: RoHS status based on EU Directive 2011/65/EU (at time of this document revision), halogen free per IEC 61249-2-21, < 1000pm each of antimony trioxide in polymeric materials and red phosphorus as a flame retardant, and <2% antimony in solder.

Caution! ESD sensitive device.

Exceeding any one or a combination of the Absolute Maximum Rating conditions may cause permanent damage to the device. Extended application of Absolute Maximum Rating conditions to the device may reduce device reliability. Specified typical performance or functional operation of the device under Absolute Maximum Rating conditions is not implied.

Nominal Operating Parameters

Description	Specification					
Parameter	Min	Тур	Max	Unit	Condition	
Individual LNA Performance					Temp = 25°C, V _{CC} = 4V, Standard Application Circuit	
Frequency Range	1710		2180	MHz		
Gain (On Mode)	15	18	21	dB	SD = 0V	
Noise Figure		1.2	1.6	dB		
Input P1dB	-6.5	-3.5		dBm		
Input IP3	6.6	9		dBm		
Gain (Off Mode)		-39		dB	SD = 4V	
Gain Delta	>40			dB	Gain LNA (on mode) – Gain LNA (off mode), 1950MHz	
Input Return Loss		9.7		dB		
Output Return Loss		12.5		dB		
Isolation (LNA1 OUT to LNA2 IN)	35	47.5		dB		
Gain Compression Slope	-1.1	-1	-0.1	dB	Gain compresses monotonically with increased input power once saturated	
Overall Power Supply					Temp = 25°C, V _{CC} = 4V, Standard Application Circuit	
Supply Voltage	3.5	4	5	V		
SD Voltage	0		VCC	V		
Logic High	1.7		VCC	V		
Logic Low	0		0.6	V		
Thermal Resistance		118		°C/W	85°C at 4.5V at 35mA	
Current	14	29	36	mA	On Mode, SD = 0V	
	0.5	3.5	6	mA	Off Mode, SD = 4V	

RF Micro Devices Inc. 7628 Thorndike Road, Greensboro, NC 27409-9421

For sales or technical support, contact RFMD at +1.336.678.5570 or customerservice@rfmd.com.

The information in this publication is believed to be accurate. However, no responsibility is assumed by RF Micro Devices, Inc. ("RFMD") for its use, nor for any infringement of patents or other rights of third parties resulting from its use. No license is granted by implication or otherwise under any patent or patent rights of RFMD. RFMD reserves the right to change component circuitry, recommended application circuitry and specifications at any time without prior notice.

DS131114



Typical Performance: T=25°C, VDD = 4V unless otherwise noted









Current versus Temperature Shutdown Mode





RF Micro Devices Inc. 7628 Thorndike Road, Greensboro, NC 27409-9421

DS131114

For sales or technical support, contact RFMD at +1.336.679.5570 or customerservice@rfmd.com. The information in this publication is believed to be accurate. However, no responsibility is assumed by RF Micro Devices, Inc. ("RFMD") for its use, nor for any infringement of patents or other rights of third parties resulting from its use. No license is granted by implication or otherwise under any patent or patent rights of RFMD. RFMD reserves the right to change component circuitry, recommended application circuitry and specifications at any time without prior notice.













Input Return Loss versus Frequency Active Mode 0 Nom Current -2 35mA Current -4 Return Loss (dB) -6 -8 Input -10 -12 -14 1700 1780 1860 2180 1940 2020 2100 Frequency (MHz)



RF Micro Devices Inc. 7628 Thorndike Road, Greensboro, NC 27409-9421

For sales or technical support, contact RFMD at +1.336.678.5570 or customerservice@rfmd.com.

The information in this publication is believed to be accurate. However, no responsibility is assumed by RF Micro Devices, Inc. ("RFMD") for its use, nor for any infringement of patents or other rights of third parties resulting from its use. No license is granted by implication or otherwise under any patent or patent rights of RFMD. RFMD reserves the right to change component circuitry, recommended application circuitry and specifications at any time without prior notice.

DS131114



Evaluation Board Schematic



DS131114

The information in this publication is believed to be accurate. However, no responsibility is assumed by RF Micro Devices, Inc. ("RFMD") for its use, nor for any infringement of patents or other rights of third parties resulting from its use. No license is granted by implication or otherwise under any patent or patent rights of RFMD. RFMD reserves the right to change component circuitry, recommended application circuitry and specifications at any time without prior notice.



Evaluation Board Bill of Materials (BOM)

Description	Reference Designator	Manufacturer	Manufacturer's P/N
Evaluation Board		DDI	LA9002-410(1)
RFLA9003 Module	U1	RFMD	RFLA9003
CAP, 0.1µF, 10% 16V, X7R, 0402	C1-C4	Murata Electronics	GRM155R71C104KA88D
CONN, SMA, END LNCH, UNIV, HYB MNT, FLT	J1-J4	Heilind Electronics	PER MAT-21-9003
RES, 0Ω, 0402	R5-R6	Kamaya, Inc.	RMC1/16SJPTH
CONN, HDR, ST, PLRZD, 9-PIN	P1	ITW Pancon	MPSS100-5C
DNP	R1-R4*, R7-R9*		

Note: Parts with * following the Reference Designators should not be populated on PCBA.



Evaluation Board Assembly Drawing





Pin Names and Descriptions

Pin	Name	Description	
1	RF_OUT2	RF Output ; Internally 50 Ω matched and DC blocked	
2	GND	Connect to low inductance path to ground	
3	GND	Connect to low inductance path to ground	
4	GND	Connect to low inductance path to ground	
5	GND	Connect to low inductance path to ground	
6	RF_IN1	RF Input; Internally 50Ω matched and DC blocked	
7	GND	Connect to low inductance path to ground	
8	GND	Connect to low inductance path to ground	
9	SD1	Shut down pin for LNA1	
10	VPAR1	Connection for external resistor to raise current when connected from this pad to V_{DD} and to lower current when connected from this pad to ground	
11	VDD1	VDD Supply, 10nF decoupling internal, supply for LNA1	
12	GND	Connect to low inductance path to ground	
13	RF_OUT1	RF Output; Internally 50Ω matched and DC blocked	
14	GND	Connect to low inductance path to ground	
15	GND	Connect to low inductance path to ground	
16	GND	Connect to low inductance path to ground	
17	GND	Connect to low inductance path to ground	
18	RF_IN1	RF Input; Internally 50Ω matched and DC blocked	
19	GND	Connect to low inductance path to ground	
20	SD2	Shut down pin for LNA2	
21	VPAR2	Connection for external resistor to raise current when connected from this pad to V_{DD} and to lower current when connected from this pad to ground	
22	VDD2	VDD Supply, 10nF decoupling internal, supply for LNA2	
23	GND	Connect to low inductance path to ground	
24	GND	Connect to low inductance path to ground	

Truth Table

	SD1	SD2
LNA1 On	0	Х
LNA1 Off	1	Х
LNA2 On	х	0
LNA2 Off	Х	1

RF Micro Devices Inc. 7628 Thorndike Road, Greensboro, NC 27409-9421

DS131114

For sales or technical support, contact RFMD at +1.336.678.5570 or customerservice@fmd.com. The information in this publication is believed to be accurate. However, no responsibility is assumed by RF Micro Devices, Inc. ("RFMD") for its use, nor for any infringement of patents or other rights of third parties resulting from its use. No license is granted by implication or otherwise under any patent or patent sof patents of RFMD. RFMD reserves the right to change component circuitry, recommended application circuitry and specifications at any time without prior notice.



Package Outline Drawing (Dimensions in millimeters)





Stencil Drawing (Dimensions in millimeters)



IO Pattern Label



RF Micro Devices Inc. 7628 Thorndike Road, Greensboro, NC 27409-9421 For sales or technical support, contact RFMD at +1.336.678.5570 or customerservice@rfmd.com. DS131114

The information in this publication is believed to be accurate. However, no responsibility is assumed by RF Micro Devices, Inc. ("RFMD") for its use, nor for any infringement of patents or other rights of third parties resulting from its use. No license is granted by implication or otherwise under any patent or patent rights of RFMD. RFMD reserves the right to change component circuitry, recommended application circuitry and specifications at any time without prior notice.



Branding Diagram





Мы молодая и активно развивающаяся компания в области поставок электронных компонентов. Мы поставляем электронные компоненты отечественного и импортного производства напрямую от производителей и с крупнейших складов мира.

Благодаря сотрудничеству с мировыми поставщиками мы осуществляем комплексные и плановые поставки широчайшего спектра электронных компонентов.

Собственная эффективная логистика и склад в обеспечивает надежную поставку продукции в точно указанные сроки по всей России.

Мы осуществляем техническую поддержку нашим клиентам и предпродажную проверку качества продукции. На все поставляемые продукты мы предоставляем гарантию.

Осуществляем поставки продукции под контролем ВП МО РФ на предприятия военно-промышленного комплекса России, а также работаем в рамках 275 ФЗ с открытием отдельных счетов в уполномоченном банке. Система менеджмента качества компании соответствует требованиям ГОСТ ISO 9001.

Минимальные сроки поставки, гибкие цены, неограниченный ассортимент и индивидуальный подход к клиентам являются основой для выстраивания долгосрочного и эффективного сотрудничества с предприятиями радиоэлектронной промышленности, предприятиями ВПК и научноисследовательскими институтами России.

С нами вы становитесь еще успешнее!

Наши контакты:

Телефон: +7 812 627 14 35

Электронная почта: sales@st-electron.ru

Адрес: 198099, Санкт-Петербург, Промышленная ул, дом № 19, литера Н, помещение 100-Н Офис 331