



Grove - 315MHz Simple RF Link Kit User Manual

Release date: 2015/9/22

Version: 1.0

Wiki: http://www.seeedstudio.com/wiki/Grove - 315MHz_RF_Kit

Bazaar: <http://www.seeedstudio.com/depot/Grove-315MHz-Simple-RF-Link-Kit-p-1061.html>

Document Revision History

Revision	Date	Author	Description
1.0	Sep 22, 2015	Jiankai.li	Create file

Contents

Document Revision History	2
1. Introduction	2
2. Features	3
3. Application Ideas	4
4. Mechanic Dimensions	5
5. Usage	6
5.1 Hardware Installation	6
5.2 Programming	6
6. Resources	8

Disclaimer

For physical injuries and possessions loss caused by those reasons which are not related to product quality, such as operating without following manual guide, natural disasters or force majeure, we take no responsibility for that.

Under the supervision of Seeed Technology Inc., this manual has been compiled and published which covered the latest product description and specification. The content of this manual is subject to change without notice.

Copyright

The design of this product (including software) and its accessories is under tutelage of laws. Any action to violate relevant right of our product will be penalized through law. Please consciously observe relevant local laws in the use of this product.

1. Introduction

This kit is used for one way wireless communication at a frequency of 315MHz and includes a transmitter module and a receiver module. The twig configuration of this kit allows for around 40 meters of transmitting distance indoors, or around 100 meters outside. The 315 MHz frequency is suitable for use without a license in the United States. For use in Europe, please see the 433 MHz version of this product.



2. Features

- GROVE compatible interface.
- Uses ASK (Amplitude Shift Keying) Modulation.
- One way communication.

3. Application Ideas

- Remote control
- Remote automation
- Alarm

4. Mechanic Dimensions

- Receiver: 24mm by 42mm
- Transmitter: 20mm by 24mm

5. Usage

The transmitter and receiver modules both rely on a single wire for communication. Though using the UART supplied by the arduino platform can work, it is recommended, instead, to use the VirtualWire library which uses Amplitude Shift Keying for modulation which provides better communication.

Both the transmitter and receiver modules require three wires: Vcc, Ground, and signal. Pin 2 of both parts of the kit are not connected.

5.1 Hardware Installation

- Connect the Transmitter module to Digital I/O 2 of the [Stem - Base Shield](#) on the arduino being used for transmission.
- Connect the Transmitter module to Digital I/O 2 of the [Stem - Base Shield](#) on the receiving arduino.

5.2 Programming

Sample code for Transmitter:

```
#include <VirtualWire.h>

int RF_TX_PIN = 2;

void setup()
{
    vw_set_tx_pin(RF_TX_PIN); // Setup transmit pin
    vw_setup(2000); // Transmission speed in bits per second.
}

void loop()
{
    const char *msg = "hello";
    vw_send((uint8_t *)msg, strlen(msg)); // Send 'hello' every 400ms.
    delay(400);
}
```

Sample code for Receiver:

```
#include <VirtualWire.h>
```

```
int RF_RX_PIN = 2;

void setup()
{
    Serial.begin(9600);
    Serial.println("setup");
    vw_set_rx_pin(RF_RX_PIN); // Setup receive pin.
    vw_setup(2000); // Transmission speed in bits per second.
    vw_rx_start(); // Start the PLL receiver.
}

void loop()
{
    uint8_t buf[VW_MAX_MESSAGE_LEN];
    uint8_t buflen = VW_MAX_MESSAGE_LEN;
    if(vw_get_message(buf, &buflen)) // non-blocking I/O
    {
        int i;
        // Message with a good checksum received, dump HEX
        Serial.print("Got: ");
        for(i = 0; i < buflen; ++i)
        {
            Serial.print(buf[i], HEX);
            Serial.print(" ");
        }
        Serial.println("");
    }
}
```

6. Resources

- Demo code: [File:433MHz demo.zip](#)
- [VirtualWire 1.20](#)
- [VirtualWire Documentation](#)
- [TI:LM358PSR](#)



**Стандарт
Электрон
Связь**

Мы молодая и активно развивающаяся компания в области поставок электронных компонентов. Мы поставляем электронные компоненты отечественного и импортного производства напрямую от производителей и с крупнейших складов мира.

Благодаря сотрудничеству с мировыми поставщиками мы осуществляем комплексные и плановые поставки широчайшего спектра электронных компонентов.

Собственная эффективная логистика и склад в обеспечивает надежную поставку продукции в точно указанные сроки по всей России.

Мы осуществляем техническую поддержку нашим клиентам и предпродажную проверку качества продукции. На все поставляемые продукты мы предоставляем гарантию .

Осуществляем поставки продукции под контролем ВП МО РФ на предприятия военно-промышленного комплекса России , а также работаем в рамках 275 ФЗ с открытием отдельных счетов в уполномоченном банке. Система менеджмента качества компании соответствует требованиям ГОСТ ISO 9001.

Минимальные сроки поставки, гибкие цены, неограниченный ассортимент и индивидуальный подход к клиентам являются основой для выстраивания долгосрочного и эффективного сотрудничества с предприятиями радиоэлектронной промышленности, предприятиями ВПК и научно-исследовательскими институтами России.

С нами вы становитесь еще успешнее!

Наши контакты:

Телефон: +7 812 627 14 35

Электронная почта: sales@st-electron.ru

Адрес: 198099, Санкт-Петербург,
Промышленная ул, дом № 19, литер Н,
помещение 100-Н Офис 331