General purpose (dual digital transistors)

EMD2 / UMD2N / IMD2A

●Features


1) Both the DTA124E chip and DTC124E chip in a EMT or UMT or SMT package.
2) Mounting possible with EMT6 or UMT6 or SMT6 automatic mounting machines.
3) Transistor elements are independent, eliminating interference.
4) Mounting cost and area can be cut in half.

●Structure

Epitaxial planar type
NPN / PNP silicon transistor (Built-in resistor type)

The following characteristics apply to both the DTr_1 and DTr_2, however, the "–" sign on DTr_2 values for the PNP type have been omitted.

●Equivalent circuit




●Absolute maximum ratings (Ta = 25°C)

Parameter		Symbol	Limits	Unit
Supply voltage		V_{CC}	50	V
Input voltage		V_{IN}	40	V
			−10	
Output current		I_O	30	mA
		$I_{C\ (Max.)}$	100	
Power dissipation	EMD2, UMD2N	Pd	150 (TOTAL)	mW ∗1
	IMD2A		300 (TOTAL)	∗2
Junction temperature		Tj	150	˚C
Storage temperature		Tstg	−55 to +150	˚C

∗1 120mW per element must not be exceeded.
∗2 200mW per element must not be exceeded.


●Dimensions (Unit : mm)

EMD2




ROHM : EMT6
Each lead has same dimensions
Abbreviated symbol : D2

UMD2N



ROHM : UMT6
EIAJ : SC-88
Each lead has same dimensions
Abbreviated symbol : D2

IMD2A



ROHM : SMT6
EIAJ : SC-74
Each lead has same dimensions
Abbreviated symbol : D2

●Electrical characteristics (Ta = 25°C)

Parameter	Symbol	Min.	Typ.	Max.	Unit	Conditions
Input voltage	$V_{I(off)}$	–	–	0.5	V	V_{CC}=5V, I_O=100µA
	$V_{I(on)}$	3	–	–		V_O=0.2V, I_O=5mA
Output voltage	$V_{O(on)}$	–	0.1	0.3	V	I_O=10mA, I_I=0.5mA
Input current	I_I	–	–	0.36	mA	V_I=5V
Output current	$I_{O(off)}$	–	–	0.5	µA	V_{CC}=50V, V_I=0V
DC current gain	G_I	56	–	–	–	V_O=5V, I_O=5mA
Transition frequency	f_T	–	250	–	MHz	V_{CE}=10V, I_E=–5mA, f=100MHz *
Input resistance	R_1	15.4	22	28.6	kΩ	–
Resistance ratio	R_2/R_1	0.8	1	1.2	–	–

* Transition frequency of the device

●Packaging specifications

Type	Package	Taping		
	Code	T2R	TR	T108
	Basic ordering unit (pieces)	8000	3000	3000
EMD2		○	—	—
UMD2N		—	○	—
IMD2A		—	—	○

●Electrical characteristic curves

DTr1 (NPN)




Fig.1 Input voltage vs. output current (ON characteristics)




Fig.2 Output current vs. input voltage (OFF characteristics)




Fig.3 DC current gain vs. output current




Fig.4 Output voltage vs. output current

DTr2 (PNP)




Fig.5 Input voltage vs. output current (ON characteristics)




Fig.6 Output current vs. input voltage (OFF characteristics)




Fig.7 DC current gain vs. output current




Fig.8 Output voltage vs. output current

Notes

- No technical content pages of this document may be reproduced in any form or transmitted by any means without prior permission of ROHM CO.,LTD.
- The contents described herein are subject to change without notice. The specifications for the product described in this document are for reference only. Upon actual use, therefore, please request that specifications to be separately delivered.
- Application circuit diagrams and circuit constants contained herein are shown as examples of standard use and operation. Please pay careful attention to the peripheral conditions when designing circuits and deciding upon circuit constants in the set.
- Any data, including, but not limited to application circuit diagrams information, described herein are intended only as illustrations of such devices and not as the specifications for such devices. ROHM CO.,LTD. disclaims any warranty that any use of such devices shall be free from infringement of any third party's intellectual property rights or other proprietary rights, and further, assumes no liability of whatsoever nature in the event of any such infringement, or arising from or connected with or related to the use of such devices.
- Upon the sale of any such devices, other than for buyer's right to use such devices itself, resell or otherwise dispose of the same, no express or implied right or license to practice or commercially exploit any intellectual property rights or other proprietary rights owned or controlled by
- ROHM CO., LTD. is granted to any such buyer.
- Products listed in this document are no antiradiation design.

The products listed in this document are designed to be used with ordinary electronic equipment or devices (such as audio visual equipment, office-automation equipment, communications devices, electrical appliances and electronic toys).
Should you intend to use these products with equipment or devices which require an extremely high level of reliability and the malfunction of which would directly endanger human life (such as medical instruments, transportation equipment, aerospace machinery, nuclear-reactor controllers, fuel controllers and other safety devices), please be sure to consult with our sales representative in advance.
It is our top priority to supply products with the utmost quality and reliability. However, there is always a chance of failure due to unexpected factors. Therefore, please take into account the derating characteristics and allow for sufficient safety features, such as extra margin, anti-flammability, and fail-safe measures when designing in order to prevent possible accidents that may result in bodily harm or fire caused by component failure. ROHM cannot be held responsible for any damages arising from the use of the products under conditions out of the range of the specifications or due to non-compliance with the NOTES specified in this catalog.

Thank you for your accessing to ROHM product informations.
More detail product informations and catalogs are available, please contact your nearest sales office.

ROHM Customer Support System **THE AMERICAS / EUROPE / ASIA / JAPAN**

www.rohm.com **Contact us** : webmaster@ rohm.co.jp

Copyright © 2008 ROHM CO.,LTD.
ROHM CO., LTD. 21 Saiin Mizosaki-cho, Ukyo-ku, Kyoto 615-8585, Japan
TEL : +81-75-311-2121
FAX : +81-75-315-0172

Стандарт Электрон Связь

Мы молодая и активно развивающаяся компания в области поставок электронных компонентов. Мы поставляем электронные компоненты отечественного и импортного производства напрямую от производителей и с крупнейших складов мира.

Благодаря сотрудничеству с мировыми поставщиками мы осуществляем комплексные и плановые поставки широчайшего спектра электронных компонентов.

Собственная эффективная логистика и склад в обеспечивает надежную поставку продукции в точно указанные сроки по всей России.

Мы осуществляем техническую поддержку нашим клиентам и предпродажную проверку качества продукции. На все поставляемые продукты мы предоставляем гарантию .

Осуществляем поставки продукции под контролем ВП МО РФ на предприятия военно-промышленного комплекса России , а также работаем в рамках 275 ФЗ с открытием отдельных счетов в уполномоченном банке. Система менеджмента качества компании соответствует требованиям ГОСТ ISO 9001.

Минимальные сроки поставки, гибкие цены, неограниченный ассортимент и индивидуальный подход к клиентам являются основой для выстраивания долгосрочного и эффективного сотрудничества с предприятиями радиоэлектронной промышленности, предприятиями ВПК и научно-исследовательскими институтами России.

С нами вы становитесь еще успешнее!

Наши контакты:

Телефон: +7 812 627 14 35

Электронная почта: sales@st-electron.ru

Адрес: 198099, Санкт-Петербург, Промышленная ул, дом № 19, литера Н, помещение 100-Н Офис 331