

4V+2.5V Drive Nch+Pch MOSFET

US6M1

●Structure

Silicon N-channel / P-channel MOSFET


●Features

- 1) Low on-resistance.
- 2) Built-in G-S Protection Diode.
- 3) Small Surface Mount Package (TUMT6).

●Application

Power switching, DC / DC converter.


●Dimensions (Unit : mm)



●Packaging specifications

Type	Package	Taping
	Code	TR
	Basic ordering unit (pieces)	3000
US6M1		○

●Equivalent circuit



●Absolute maximum ratings (Ta=25°C)

Parameter	Symbol	Limits		Unit
		Tr1 : Nchannel	Tr2 : Pchannel	
Drain-source voltage	V_{DS}	30	-20	V
Gate-source voltage	V_{GS}	20	-12	V
Drain current	Continuous	I_D	± 1.4	A
	Pulsed	I_{DP}^{*1}	± 5.6	A
Source current (Body diode)	Continuous	I_S	0.6	A
	Pulsed	I_{SP}^{*1}	5.6	A
Total power dissipation	P_D^{*2}	1		W / TOTAL
		0.7		W / ELEMENT
Channel temperature	T_{ch}	150		°C
Storage temperature	T_{stg}	-55 to +150		°C

*1 $P_w \leq 10 \mu s$, Duty cycle $\leq 1\%$

*2 Mounted on a ceramic board.

●Thermal resistance

Parameter	Symbol	Limits	Unit
Channel to ambient	$R_{th} (ch-a)^*$	125	°C / W / TOTAL
		179	°C / W / ELEMENT

*2 Mounted on a ceramic board.

Transistors

N-ch

●Electrical characteristics (Ta=25°C)

Parameter	Symbol	Min.	Typ.	Max.	Unit	Conditions
Gate-source leakage	I _{GSS}	—	—	10	μA	V _{GS} =20V, V _{DS} =0V
Drain-source breakdown voltage	V _{(BR) DSS}	30	—	—	V	I _D =1mA, V _{GS} =0V
Zero gate voltage drain current	I _{DSS}	—	—	1	μA	V _{DS} =30V, V _{GS} =0V
Gate threshold voltage	V _{GS(th)}	1.0	—	2.5	V	V _{DS} =10V, I _D =1mA
Static drain-source on-state resistance	R _{DS(on)} *	—	170	240	mΩ	I _D =1.4A, V _{GS} =10V
		—	250	350		I _D =1.4A, V _{GS} =4.5V
		—	270	380		I _D =1.4A, V _{GS} =4V
Forward transfer admittance	Y _{fs} *	1.0	—	—	S	I _D =1.4A, V _{DS} =10V
Input capacitance	C _{iss}	—	70	—	pF	V _{DS} =10V
Output capacitance	C _{oss}	—	15	—	pF	V _{GS} =0V
Reverse transfer capacitance	C _{rss}	—	12	—	pF	f=1MHz
Turn-on delay time	t _{d(on)} *	—	6	—	ns	I _D =0.7A, V _{DD} ≐15V
Rise time	t _r *	—	6	—	ns	V _{GS} =10V
Turn-off delay time	t _{d(off)} *	—	13	—	ns	R _L =21Ω
Fall time	t _f *	—	8	—	ns	R _G =10Ω
Total gate charge	Q _g *	—	1.4	2.0	nC	V _{DD} ≐15V R _L =11Ω
Gate-source charge	Q _{gs} *	—	0.6	—	nC	V _{GS} =5V R _G =10Ω
Gate-drain charge	Q _{gd} *	—	0.3	—	nC	I _D =1.4A

*Pulsed

●Body diode characteristics (Source-Drain) (Ta=25°C)

Parameter	Symbol	Min.	Typ.	Max.	Unit	Test Conditions
Forward voltage	V _{SD}	—	—	1.2	V	I _S =0.6A, V _{GS} =0V

Transistors

P-ch

●Electrical characteristics (Ta=25°C)

Parameter	Symbol	Min.	Typ.	Max.	Unit	Conditions
Gate-source leakage	I _{GSS}	—	—	−10	μA	V _{GS} =12V, V _{DS} =0V
Drain-source breakdown voltage	V _{(BR) DSS}	−20	—	—	V	I _D = −1mA, V _{GS} =0V
Zero gate voltage drain current	I _{DSS}	—	—	−1	μA	V _{DS} = −20V, V _{GS} =0V
Gate threshold voltage	V _{GS(th)}	−0.7	—	−2.0	V	V _{DS} = −10V, I _D = −1mA
Static drain-source on-state resistance	R _{DS(on)} *	—	280	390	mΩ	I _D = −1A, V _{GS} = −4.5V
		—	310	430		I _D = −1A, V _{GS} = −4V
		—	570	800		I _D = −0.5A, V _{GS} = −2.5V
Forward transfer admittance	Y _{fs} *	0.7	—	—	S	I _D = −0.5A, V _{DS} = −10V
Input capacitance	C _{iss}	—	150	—	pF	V _{DS} = −10V
Output capacitance	C _{oss}	—	20	—	pF	V _{GS} =0V
Reverse transfer capacitance	C _{rss}	—	20	—	pF	f=1MHz
Turn-on delay time	t _{d(on)} *	—	9	—	ns	I _D = −0.5A, V _{DD} ≐ −15V
Rise time	t _r *	—	8	—	ns	V _{GS} = −4.5V
Turn-off delay time	t _{d(off)} *	—	25	—	ns	R _L =30Ω
Fall time	t _f *	—	10	—	ns	R _G =10Ω
Total gate charge	Q _g *	—	2.1	—	nC	V _{DD} ≐ −15V R _L =15Ω
Gate-source charge	Q _{gs} *	—	0.5	—	nC	V _{GS} = −4.5V R _G =10Ω
Gate-drain charge	Q _{gd} *	—	0.5	—	nC	I _D = −1A

*Pulsed

●Body diode characteristics (Source-Drain) (Ta=25°C)

Parameter	Symbol	Min.	Typ.	Max.	Unit	Test Conditions
Forward voltage	V _{SD}	—	—	−1.2	V	I _S = −0.4A, V _{GS} =0V

Transistors

N-ch

●Electrical characteristic curves




Fig.1 Typical Capacitance vs. Drain-Source Voltage




Fig.2 Switching Characteristics




Fig.3 Dynamic Input Characteristics




Fig.4 Typical Transfer Characteristics




Fig.5 Static Drain-Source On-State Resistance vs. Gate-Source Voltage




Fig.6 Source Current vs. Source-Drain Voltage




Fig.7 Static Drain-Source On-State Resistance vs. Drain Current (I)




Fig.8 Static Drain-Source On-State Resistance vs. Drain Current (II)




Fig.9 Static Drain-Source On-State Resistance vs. Drain Current (III)

Transistors

P-ch

●Electrical characteristic curves




Fig.1 Typical Capacitance vs. Drain-Source Voltage




Fig.2 Switching Characteristics




Fig.3 Dynamic Input Characteristics




Fig.4 Typical Transfer Characteristics




Fig.5 Static Drain-Source On-State Resistance vs. Gate-Source Voltage




Fig.6 Source Current vs. Source-Drain Voltage




Fig.7 Static Drain-Source On-State Resistance vs. Drain Current (I)




Fig.8 Static Drain-Source On-State Resistance vs. Drain Current (II)




Fig.9 Static Drain-Source On-State Resistance vs. Drain Current (III)

Transistors

N-ch

●Measurement circuit




Fig.1-1 Switching Time Measurement Circuit




Fig.1-2 Switching Waveforms




Fig.2-1 Gate Charge Measurement Circuit




Fig.2-2 Gate Charge Waveform

Transistors

P-ch

●Measurement circuit




Fig.3-1 Switching Time Measurement Circuit




Fig.3-2 Switching Waveforms




Fig.4-1 Gate Charge Measurement Circuit




Fig.4-2 Gate Charge Waveform

Notes

- No technical content pages of this document may be reproduced in any form or transmitted by any means without prior permission of ROHM CO.,LTD.
- The contents described herein are subject to change without notice. The specifications for the product described in this document are for reference only. Upon actual use, therefore, please request that specifications to be separately delivered.
- Application circuit diagrams and circuit constants contained herein are shown as examples of standard use and operation. Please pay careful attention to the peripheral conditions when designing circuits and deciding upon circuit constants in the set.
- Any data, including, but not limited to application circuit diagrams information, described herein are intended only as illustrations of such devices and not as the specifications for such devices. ROHM CO.,LTD. disclaims any warranty that any use of such devices shall be free from infringement of any third party's intellectual property rights or other proprietary rights, and further, assumes no liability of whatsoever nature in the event of any such infringement, or arising from or connected with or related to the use of such devices.
- Upon the sale of any such devices, other than for buyer's right to use such devices itself, resell or otherwise dispose of the same, no express or implied right or license to practice or commercially exploit any intellectual property rights or other proprietary rights owned or controlled by
- ROHM CO., LTD. is granted to any such buyer.
- Products listed in this document are no antiradiation design.

The products listed in this document are designed to be used with ordinary electronic equipment or devices (such as audio visual equipment, office-automation equipment, communications devices, electrical appliances and electronic toys).

Should you intend to use these products with equipment or devices which require an extremely high level of reliability and the malfunction of which would directly endanger human life (such as medical instruments, transportation equipment, aerospace machinery, nuclear-reactor controllers, fuel controllers and other safety devices), please be sure to consult with our sales representative in advance.

About Export Control Order in Japan

Products described herein are the objects of controlled goods in Annex 1 (Item 16) of Export Trade Control Order in Japan.

In case of export from Japan, please confirm if it applies to "objective" criteria or an "informed" (by MITI clause) on the basis of "catch all controls for Non-Proliferation of Weapons of Mass Destruction.

Mouser Electronics

Authorized Distributor

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

[ROHM Semiconductor:](#)

[US6M1TR](#)



**Стандарт
Электрон
Связь**

Мы молодая и активно развивающаяся компания в области поставок электронных компонентов. Мы поставляем электронные компоненты отечественного и импортного производства напрямую от производителей и с крупнейших складов мира.

Благодаря сотрудничеству с мировыми поставщиками мы осуществляем комплексные и плановые поставки широчайшего спектра электронных компонентов.

Собственная эффективная логистика и склад в обеспечивает надежную поставку продукции в точно указанные сроки по всей России.

Мы осуществляем техническую поддержку нашим клиентам и предпродажную проверку качества продукции. На все поставляемые продукты мы предоставляем гарантию .

Осуществляем поставки продукции под контролем ВП МО РФ на предприятия военно-промышленного комплекса России , а также работаем в рамках 275 ФЗ с открытием отдельных счетов в уполномоченном банке. Система менеджмента качества компании соответствует требованиям ГОСТ ISO 9001.

Минимальные сроки поставки, гибкие цены, неограниченный ассортимент и индивидуальный подход к клиентам являются основой для выстраивания долгосрочного и эффективного сотрудничества с предприятиями радиоэлектронной промышленности, предприятиями ВПК и научно-исследовательскими институтами России.

С нами вы становитесь еще успешнее!

Наши контакты:

Телефон: +7 812 627 14 35

Электронная почта: sales@st-electron.ru

Адрес: 198099, Санкт-Петербург,
Промышленная ул, дом № 19, литера Н,
помещение 100-Н Офис 331