



Grove – Buzzer User Manual

Release date: 2015/9/22

Version: 1.0

Wiki: http://www.seeedstudio.com/wiki/Grove_-_Button

Bazaar: <http://www.seeedstudio.com/depot/Grove-Buzzer-p-768.html?cPath=38>

Document Revision History

Revision	Date	Author	Description
1.0	Sep 22, 2015	Loovee	Create file

Contents

Document Revision History	2
1. Introduction	2
2. Features	3
3. Usage	4
3.1 Standalone	4
3.2 With Arduino	4
3.3 With TI LaunchPad	5
3.4 With Raspberry Pi	7
4. Resources	10
5. Availability	11
6. Resources	12

Disclaimer

For physical injuries and possessions loss caused by those reasons which are not related to product quality, such as operating without following manual guide, natural disasters or force majeure, we take no responsibility for that.

Under the supervision of Seeed Technology Inc., this manual has been compiled and published which covered the latest product description and specification. The content of this manual is subject to change without notice.

Copyright

The design of this product (including software) and its accessories is under tutelage of laws. Any action to violate relevant right of our product will be penalized through law. Please consciously observe relevant local laws in the use of this product.

1. Introduction

The Grove - Buzzer module has a piezo buzzer as the main component. The piezo can be connected to digital outputs, and will emit a tone when the output is HIGH. Alternatively, it can be connected to an analog pulse-width modulation output to generate various tones and effects.



2. Features

- Easy to use piezoelectric buzzer
- Uses Standard 4-pin Grove Cables to connect to other Grove modules such as Grove Power Modules and Grove - Base Shield

Specifications

- Operating Voltage: 4-8V
- Sound Output: $\geq 85\text{dB}$
- Resonant Frequency: $2300\pm 300\text{Hz}$

3. Usage

3.1 Standalone

Follow these steps to build a sample circuit using this module but without using any microcontroller:


1. Connect the buzzer module to the output side of your circuit (to the right of the power module).
On the input side of the circuit, you may use a range of sensor based input modules (Grove - Light Sensor, Grove - Button or [Grove - Slide Potentiometer](#)).
2. Power up the circuit.
3. The buzzer will start to "buzz" when the input module supplies a trigger:
 - If using with a momentary switch like the one on the Grove - Button module, simply press the button to turn ON the buzzer.
 - If using with a Grove - Slide Potentiometer, move the slider from the GND position to VCC and see how the tone and frequency of the buzzer vary as the supplied voltage increases.
 - If using with a [Grove - Light Sensor](#) connected directly to the input side of the circuit, you should hear the buzzer in bright light and it should stop "buzzing" in the dark. If you want the buzzer to sound only in the dark, add a [Grove - NOT](#) module between the light sensor and the power module.

You can use either the [Grove - USB Power](#) module or the [Grove - DC Jack](#) Power module for the Grove circuit.

3.2 With Arduino

Follow these simple steps to build a Grove circuit using the buzzer:

1. When using the module in conjunction with an Arduino or a Seeeduino, use the Grove - Base Shield and connect the Grove - Buzzer module to the shield using a designated Grove Interface as shown below:



2. Upload the following sample sketch to make the Buzzer make a beeping noise:

```
// Project Four - Noise maker
//


void setup()
{
  pinMode(6, OUTPUT);
}

void loop()
{
  digitalWrite(6, HIGH);
  delay(analogRead(0));
  digitalWrite(6, LOW);
  delay(analogRead(0));
}
```

3.3 With TI LaunchPad

Playing Music (Buzzer)

This example shows how to use the Grove buzzer module to play melodies. It sends a square wave of the appropriate frequency to the buzzer, generating the corresponding tone.



```

/*
  Buzzer

  The example use a buzzer to play melodies. It sends a square wave of the
  appropriate frequency to the buzzer, generating the corresponding tone.

  The circuit:
  * Buzzer attached to pin39 (J14 plug on Grove Base BoosterPack)
  * one side pin (either one) to ground
  * the other side pin to VCC
  * LED anode (long leg) attached to RED_LED
  * LED cathode (short leg) attached to ground

  * Note:

  This example code is in the public domain.

  http://www.seeedstudio.com/wiki/index.php?title=GROVE_-_Starter_Kit_v1.1b#Grove_-_Buzzer

*/

/* Macro Define */
#define BUZZER_PIN          39          /* sig pin of the buzzer */

int length = 15;          /* the number of notes */
char notes[] = "ccggaagffeeddc ";
int beats[] = { 1, 1, 1, 1, 1, 1, 2, 1, 1, 1, 1, 1, 1, 2, 4 };
int tempo = 300;

void setup()
{
  /* set buzzer pin as output */
  pinMode(BUZZER_PIN, OUTPUT);

```

```

}

void loop()
{
    for(int i = 0; i < length; i++) {
        if(notes[i] == ' ') {
            delay(beats[i] * tempo);
        } else {
            playNote(notes[i], beats[i] * tempo);
        }
        delay(tempo / 2);    /* delay between notes */
    }
}

/* play tone */
void playTone(int tone, int duration) {
    for (long i = 0; i < duration * 1000L; i += tone * 2) {
        digitalWrite(BUZZER_PIN, HIGH);
        delayMicroseconds(tone);
        digitalWrite(BUZZER_PIN, LOW);
        delayMicroseconds(tone);
    }
}


void playNote(char note, int duration) {
    char names[] = { 'c', 'd', 'e', 'f', 'g', 'a', 'b', 'C' };
    int tones[] = { 1915, 1700, 1519, 1432, 1275, 1136, 1014, 956 };

    // play the tone corresponding to the note name
    for (int i = 0; i < 8; i++) {
        if (names[i] == note) {
            playTone(tones[i], duration);
        }
    }
}

```

3.4 With Raspberry Pi

The following is a simple example to show how to use the Grove - Buzzer module on Raspberry Pi. The buzzer makes noise and delays one second. Then quiet for a second. It repeats the above action.



```
# GrovePi + Grove Buzzer
import time
import grovepi

# Connect the Grove Buzzer to digital port D8
# SIG, NC, VCC, GND
buzzer = 8

grovepi.pinMode(buzzer, "OUTPUT")

while True:
    try:
        # Buzz for 1 second
        grovepi.digitalWrite(buzzer, 1)
        print 'start'
        time.sleep(1)

        # Stop buzzing for 1 second and repeat
        grovepi.digitalWrite(buzzer, 0)
        print 'stop'
        time.sleep(1)

    except KeyboardInterrupt:
        grovepi.digitalWrite(buzzer, 0)
        break
    except IOError:
        print "Error"
```

Run the program

- Find the path to the file(According to your own path)

```
cd GrovePi/Software/Python/
```

- Run Program

```
sudo python grove_buzzer.py
```

4. Resources

- [Grove - Buzzer Source Files v1.1](#)
- [Grove - Buzzer Source Files v1.0 \(Eagle and pdf\)](#)
- [S9013datasheet](#)
- [Buzzer](#)

5. Availability

The standard Grove - Button module is available as part of the following [Grove Kit Series](#):

- [Grove - Mixer Pack V2](#)
- [Grove - Mixer Pack](#)
- [Grove - Starter Kit V1.1b](#)

Alternatively, it can be bought stand-alone [here](#) at the [Seeed Studio Bazaar](#). To buy the Panel Mount version of the module, go [here](#).

6. Resources

- [Grove-Button \(Eagle Files\)](#) for the version included in [Grove Mixer Pack V2](#)
- [how to upload code](#)



**Стандарт
Электрон
Связь**

Мы молодая и активно развивающаяся компания в области поставок электронных компонентов. Мы поставляем электронные компоненты отечественного и импортного производства напрямую от производителей и с крупнейших складов мира.

Благодаря сотрудничеству с мировыми поставщиками мы осуществляем комплексные и плановые поставки широчайшего спектра электронных компонентов.

Собственная эффективная логистика и склад в обеспечивает надежную поставку продукции в точно указанные сроки по всей России.

Мы осуществляем техническую поддержку нашим клиентам и предпродажную проверку качества продукции. На все поставляемые продукты мы предоставляем гарантию .

Осуществляем поставки продукции под контролем ВП МО РФ на предприятия военно-промышленного комплекса России , а также работаем в рамках 275 ФЗ с открытием отдельных счетов в уполномоченном банке. Система менеджмента качества компании соответствует требованиям ГОСТ ISO 9001.

Минимальные сроки поставки, гибкие цены, неограниченный ассортимент и индивидуальный подход к клиентам являются основой для выстраивания долгосрочного и эффективного сотрудничества с предприятиями радиоэлектронной промышленности, предприятиями ВПК и научно-исследовательскими институтами России.

С нами вы становитесь еще успешнее!

Наши контакты:

Телефон: +7 812 627 14 35

Электронная почта: sales@st-electron.ru

Адрес: 198099, Санкт-Петербург,
Промышленная ул, дом № 19, литера Н,
помещение 100-Н Офис 331