Features

- Single Package Fully-integrated 4-bit Microcontroller with RF Transmitter
- Low Power Consumption in Sleep Mode (< 1 µA Typically)
- Flash Controller for Application Program Available
- Maximum Output Power with Low Supply Current
- 2.0V to 4.0V Operation Voltage for Single Li-cell Power Supply
- –40°C to +125°C Operation Temperature
- SSO24 Package
- About Seven External Components

1. Description

The ATAM862-8 is a single package dual-chip circuit. It combines a UHF ASK/FSK transmitter with a 4-bit microcontroller. It supports highly integrated solutions in car access and tire pressure monitoring applications, as well as manifold applications in the industrial and consumer segment. It is available for the transmitting frequency range of 868 MHz to 928 MHz with data rates up to 32 kbaud Manchester coded.

For further frequency ranges 310 MHz to 330 MHz and 429 MHz to 439 MHz separate datasheets are available.

The device contains a flash microcontroller.

Figure 1-1. Application Diagram





Microcontroller with UHF ASK/FSK Transmitter

ATAM862-8

4590G-4BMCU-06/07





2. Pin Configuration

Figure 2-1. Pinning SSO24



Table 2-1. Pin Description: RF Par

Pin	Symbol	Function	Configuration
1	XTAL	Connection for crystal	XTAL 182 µA
2	VS	Supply voltage	ESD protection circuitry (see Figure 7-5 on page 11)
3	GND	Ground	ESD protection circuitry (see Figure 7-5 on page 11)
4	ENABLE	Enable input	ENABLE 200k

2

ATAM862-8

Table 2-1.	Pin Description: RF Part ((Continued)
------------	----------------------------	-------------

Pin	Symbol	Function	Configuration
21	CLK	Clock output signal for microcontroller, the clock output frequency is set by the crystal to f _{XTAL} /4	
22	PA_ENABLE	Switches on power amplifier, used for ASK modulation	PA_ENABLE 50k Uref = 1.1V
23 24	ANT2 ANT1	Emitter of antenna output stage Open collector antenna output	ANT1 ANT2

Name	Туре	Function	Alternate Function	Pin No.	Reset State
V _{DD}	-	Supply voltage	-	13	NA
V _{SS}	-	Circuit ground	-	12	NA
BP20	I/O	Bi-directional I/O line of Port 2.0	NTE-test mode enable, see also section "Master Reset"	7	Input
BP40	I/O	Bi-directional I/O line of Port 4.0	SC-serial clock or INT3 external interrupt input	14	Input
BP41	I/O	Bi-directional I/O line of Port 4.1	VMI voltage monitor input or T2I external clock input Timer 2	9	Input
BP42	I/O	Bi-directional I/O line of Port 4.2	T2O Timer 2 output	10	Input
BP43	I/O	Bi-directional I/O line of Port 4.3	SD serial data I/O or INT3-external interrupt input	11	Input
BP50	I/O	Bi-directional I/O line of Port 5.0	INT6 external interrupt input	17	Input
BP52	I/O	Bi-directional I/O line of Port 5.2	INT1 external interrupt input	16	Input
BP53	I/O	Bi-directional I/O line of Port 5.3	INT1 external interrupt input	15	Input
BP60	I/O	Bi-directional I/O line of Port 6.0	T3O Timer 3 output	20	Input
BP63	I/O	Bi-directional I/O line of Port 6.3	T3I Timer 3 input	6	Input
OSC1	I	Oscillator input	4-MHz crystal input or 32-kHz crystal input or external clock input or external trimming resistor input	18	Input
OSC2	0	Oscillator output	4-MHz crystal output or 32-kHz crystal output or external clock input	19	Input
NRESET	I/O	Bi-directional reset pin	-	5	I/O





3. UHF ASK/FSK Transmitter Block

4. Features

- Integrated PLL Loop Filter
- ESD Protection also at ANT1/ANT2 (4 kV HBM/200 V MM, Except Pin 2: 4 kV HBM/100 V MM)
- High Output Power (5.5 dBm) with Low Supply Current (8.5 mA)
- Modulation Scheme ASK/FSK
 - FSK Modulation is Achieved by Connecting an Additional Capacitor between the XTAL Load Capacitor and the Open-drain Output of the Modulating Microcontroller
- Easy to Design-in Due to Excellent Isolation of the PLL from the PA and Power Supply
- Single Li-cell for Power Supply
- Supply Voltage 2.0 V to 4.0 V in the Temperature Range of -40° C to 85° C/125° C
- Single-ended Antenna Output with High Efficient Power Amplifier
- CLK Output for Clocking the Microcontroller
- One-chip Solution with Minimum External Circuitry
- 125° C Operation for Tire Pressure Systems

5. Description

The PLL transmitter block has been developed for the demands of RF low-cost transmission systems, at data rates up to 32 kbaud. The transmitting frequency range is 868 MHz to 928 MHz. It can be used in both FSK and ASK systems.

4

Figure 5-1. Block Diagram







6. General Description

The fully-integrated PLL transmitter that allows particularly simple, low-cost RF miniature transmitters to be assembled. The VCO is locked to $64 \times f_{XTAL}$, thus, a 13.5672 MHz crystal is needed for a 868.3 MHz transmitter and a 14.2969 MHz crystal for a 915 MHz transmitter. All other PLL and VCO peripheral elements are integrated.

The XTO is a series resonance oscillator so that only one capacitor together with a crystal connected in series to GND are needed as external elements.

The crystal oscillator together with the PLL needs typically < 1 ms until the PLL is locked and the CLK output is stable. A wait time of \geq 4 ms must be used until the CLK is used for the microcontroller and the PA is switched on.

The power amplifier is an open-collector output delivering a current pulse which is nearly independent from the load impedance. The delivered output power is controlled via the connected load impedance.

This output configuration enables a simple matching to any kind of antenna or to 50 Ω A high power efficiency of $\eta = P_{out}/(I_{S,PA} \times V_S)$ of 24% for the power amplifier at 868.3 MHz results when an optimized load impedance of $Z_{Load} = (166 + j226) \Omega$ is used at 3 V supply voltage.

7. Functional Description

If ENABLE = L and PA_ENABLE = L, the circuit is in standby mode consuming only a very small amount of current, so that a lithium cell used as power supply can work for several years.

With ENABLE = H, the XTO, PLL and the CLK driver are switched on. If PA_ENABLE remains L, only the PLL and the XTO are running and the CLK signal is delivered to the microcontroller. The VCO locks to 64 times the XTO frequency.

With ENABLE = H and PA_ENABLE = H, the PLL, XTO, CLK driver and the power amplifier are on. With PA_ENABLE, the power amplifier can be switched on and off, which is used to perform the ASK modulation.

7.1 ASK Transmission

The PLL transmitter block is activated by ENABLE = H. PA_ENABLE must remain L for t \ge 4 ms, then the CLK signal can be taken to clock the microcontroller and the output power can be modulated by means of pin PA_ENABLE. After transmission, PA_ENABLE is switched to L and the microcontroller switches back to internal clocking. The ATAM862-8 is switched back to standby mode with ENABLE = L.

7.2 FSK Transmission

The PLL transmitter block is activated by ENABLE = H. PA_ENABLE must remain L for $t \ge 4$ ms, then the CLK signal can be taken to clock the microcontroller and the power amplifier is switched on with PA_ENABLE = H. The chip is then ready for FSK modulation. The microcontroller starts to switch on and off the capacitor between the XTAL load capacitor and GND with an open-drain output port, thus changing the reference frequency of the PLL. If the switch is closed, the output frequency is lower than if the switch is open. After transmission PA_ENABLE is switched to L and the microcontroller switches back to internal clocking. The PLL transmitter block is switched back to standby mode with ENABLE = L.

The accuracy of the frequency deviation with XTAL pulling method is about $\pm 25\%$ when the following tolerances are considered.

Figure 7-1. Tolerances of Frequency Modulation



Using C₄ = 9.2 pF ±2%, C₅ = 6.8 pF ±5%, a switch port with C_{Switch} = 3 pF ±10%, stray capacitances on each side of the crystal of C_{Stray1} = C_{Stray2} = 1 pF ±10%, a parallel capacitance of the crystal of C₀ = 3.2 pF ±10% and a crystal with C_M = 13 fF ±10%, an FSK deviation of ±21 kHz typical with worst case tolerances of ±16.3 kHz to ±28.8 kHz results.

7.3 CLK Output

An output CLK signal is provided for a connected microcontroller. The delivered signal is CMOS compatible if the load capacitance is lower than 10 pF.

7.3.1 Clock Pulse Take Over

The clock of the crystal oscillator can be used for clocking the microcontroller. The Microcontroller block has the special feature of starting with an integrated RC-oscillator to switch on the PLL transmitter block with ENABLE = H, and after 4 ms to assume the clock signal of the transmission IC, so the message can be sent with crystal accuracy.

7.3.2 Output Matching and Power Setting

The output power is set by the load impedance of the antenna. The maximum output power is achieved with a load impedance of $Z_{Load,opt} = (166 + j226) \Omega$ at 868.3 MHz. There must be a low resistive path to V_S to deliver the DC current.

The delivered current pulse of the power amplifier is 7.7 mA and the maximum output power is delivered to a resistive load of 475 Ω if the 0.53 pF output capacitance of the power amplifier is compensated by the load impedance.

An optimum load impedance of:

 Z_{Load} = 475 $\Omega \parallel j/(2 \times \pi \times f \times 0.53 \text{ pF})$ = (166 + j226) Ω thus results for the maximum output power of 5.5 dBm.

The load impedance is defined as the impedance seen from the PLL transmitter block's ANT1, ANT2 into the matching network. Do not confuse this large signal load impedance with a small signal input impedance delivered as input characteristic of RF amplifiers and measured from the application into the IC instead of from the IC into the application for a power amplifier.

Less output power is achieved by lowering the real parallel part of 475 Ω where the parallel imaginary part should be kept constant.

Output power measurement can be done with the circuit shown in Figure 7-2 on page 8. Note that the component values must be changed to compensate the individual board parasitics until the PLL transmitter block has the right load impedance $Z_{Load,opt} = (166 + j226) \Omega$ at 868.3 MHz. Also the damping of the cable used to measure the output power must be calibrated.





Figure 7-2. Output Power Measurement



7.4 Application Circuit

For the supply-voltage blocking capacitor C_3 , a value of 68 nF/X7R is recommended (see Figure 7-3 on page 9 and Figure 7-4 on page 10). C_1 and C_2 are used to match the loop antenna to the power amplifier where C_1 typically is 3.9 pF/NP0 and C_2 is 1 pF/NP0; for C_2 two capacitors in series should be used to achieve a better tolerance value and to have the possibility to realize the $Z_{Load,opt}$ by using standard valued capacitors.

 C_1 forms together with the pins of PLL transmitter block and the PCB board wires a series resonance loop that suppresses the 1st harmonic, thus, the position of C_1 on the PCB is important. Normally the best supression is achieved when C_1 is placed as close as possible to the pins ANT1 and ANT2.

The loop antenna should not exceed a width of 1.5 mm, otherwise the Q-factor of the loop antenna is too high.

 $L_1 \approx 50$ nH to 100 nH) can be printed on PCB. C_4 should be selected so the XTO runs on the load resonance frequency of the crystal. Normally, a value of 12 pF results for a 15 pF load-capacitance crystal.

8

Figure 7-3. ASK Application Circuit











MEL

Figure 7-4. FSK Application Circuit





8. Absolute Maximum Ratings: RF Part

Stresses beyond those listed under "Absolute Maximum Ratings" may cause permanent damage to the device. This is a stress rating only and functional operation of the device at these or any other conditions beyond those indicated in the operational sections of this specification is not implied. Exposure to absolute maximum rating conditions for extended periods may affect device reliability.

Parameters	Symbol	Min.	Max.	Unit
Supply voltage	V _S		5	V
Power dissipation	P _{tot}		100	mW
Junction temperature	Tj		150	°C
Storage temperature	T _{stg}	-55	+125	°C
Ambient temperature	T _{amb}	-55	+125	°C
Input voltage	V_{maxPA_ENABLE}	-0.3	$(V_{S} + 0.3)^{(1)}$	V

Note: 1. If V_{S} + 0.3 is higher than 3.7 V, the maximum voltage will be reduced to 3.7 V.

9. Thermal Resistance

Parameters	Symbol	Value	Unit
Junction ambient	R _{thJA}	135	K/W

10. Electrical Characteristics

 V_S = 2.0 V to 4.0 V, T_{amb} = -40°C to +125°C unless otherwise specified.

Typical values are given at $V_s = 3.0$ V and $T_{amb} = 25^{\circ}$ C. All parameters are refered to GND (Pin 3).

Parameters	Test Conditions	Symbol	Min.	Тур.	Max.	Unit
Supply current	Power down, $V_{ENABLE} < 0.25 V$, -40°C to 85°C $V_{PA_ENABLE} < 0.25 V$, -85°C to +125°C $V_{PA_ENABLE} < 0.25 V$, 25°C (100% correlation tested)	I _{S_Off}		<10	350 7	nA μA nA
Supply ourront	Power up, PA off, $V_S = 3 V$ $V_{ENABLE} > 1.7 V$, $V_{PA_ENABLE} < 0.25 V$	ا _s		3.6	4.6	mA
	Power up, V _S = 3.0 V V _{ENABLE} > 1.7 V, V _{PA_ENABLE} > 1.7 V	I _{S_Transmit}		8.5	11	mA
Output power	V_{S} = 3.0 V, T _{amb} = 25° C f = 868.3 MHz, Z _{Load} = (166 + j226) Ω	P _{Ref}	3.5	5.5	8	dBm



	6

10. Electrical Characteristics (Continued)

 $V_{s} = 2.0 \text{ V}$ to 4.0 V, $T_{amb} = -40^{\circ}\text{C}$ to $+125^{\circ}\text{C}$ unless otherwise specified. Typical values are given at $V_{s} = 3.0 \text{ V}$ and $T_{amb} = 25^{\circ}\text{C}$. All parameters are referred to GND (Pin 3).

Parameters	Test Conditions	Symbol	Min.	Тур.	Max.	Unit
Output power variation for the full temperature range	$T_{amb} = -40^{\circ}C \text{ to } +85^{\circ}C$ $V_{S} = 3.0 \text{ V}$ $V_{S} = 2.0 \text{ V}$	$\Delta P_{Ref} \ \Delta P_{Ref}$			-1.5 -4.0	dB dB
Output power variation for the full temperature range	$\begin{split} T_{amb} &= -40^{\circ}\text{C to } +125^{\circ}\text{ C} \\ V_{S} &= 3.0 \text{ V} \\ V_{S} &= 2.0 \text{ V} \\ P_{Out} &= P_{Ref} + \Delta P_{Ref} \end{split}$	$\Delta P_{Ref} \ \Delta P_{Ref}$			-2.0 -4.5	dB dB
Achievable output-power range	Selectable by load impedance	P _{Out_typ}	-3		+5.5	dBm
Spurious emission				-52 -52		dBc dBc
Oscillator frequency XTO (= phase comparator frequency)	$\begin{split} f_{XTO} &= f_0/32 \\ f_{XTAL} &= \text{resonant frequency of the XTAL}, \\ C_M \leq &10 \text{ fF, load capacitance selected} \\ accordingly \\ T_{amb} &= -40^\circ\text{C to } +85^\circ\text{C} \\ T_{amb} &= -40^\circ\text{C to } +125^\circ\text{C} \end{split}$	f _{XTO}	-30 -40	f _{xtal}	+30 +40	ppm ppm
PLL loop bandwidth				250		kHz
Phase noise of phase comparator	Referred to $f_{PC} = f_{XT0,}$ 25 kHz distance to carrier			-116	-110	dBc/Hz
In loop phase noise PLL	25 kHz distance to carrier			-80	-74	dBc/Hz
Phase noise VCO	at 1 MHz at 36 MHz			-89 -120	-86 -117	dBc/Hz dBc/Hz
Frequency range of VCO		f _{VCO}	868		928	MHz
Clock output frequency (CMOS microcontroller compatible)				f ₀ /256		MHz
Voltage swing at Pin CLK	C _{Load} ≤10 pF	V _{0h} V _{0l}	$V_{S} \times 0.8$		$V_{S} \times 0.2$	V V
Series resonance R of the crystal		Rs			110	Ω
Capaictive load at Pin XT0					7	pF
FSK modulation frequency rate	Duty cycle of the modulation signal = 50%		0		32	kHz
ASK modulation frequency rate $Duty cycle of the modulation signal = 50\%$			0		32	kHz
ENABLE input ENABLE input voltage Input Current high		V _{II} V _{Ih} I _{In}	1.7		0.25 20	V V μA
PA_ENABLE input	Low level input voltage High level input voltage Input current high	V _{II} V _{Ih} I _{In}	1.7		0.25 V _S ⁽¹⁾ 5	V V µA

Note: 1. If V_S is higher than 3.6 V, the maximum voltage will be reduced to 3.6 V.

11. Microcontroller Block

12. Features

- 4-Kbyte ROM, 256 x 4-bit RAM
- EEPROM Programmable Options
- Read Protection for the EEPROM Program Memory
- 11 Bi-directional I/Os
- Up to Seven External/Internal Interrupt Sources
- Eight Hardware and Software Interrupt Priorities
- Multifunction Timer/Counter
 - IR Remote Control Carrier Generator
 - Biphase-, Manchester- and Pulse-width Modulator and Demodulator
 - Phase Control Function
- Programmable System Clock with Prescaler and Five Different Clock Sources
- Very Low Sleep Current (< 1 μA)
- 2×512 -bit EEPROM Data Memory
- 256 \times 4-bit RAM Data Memory
- Synchronous Serial Interface (2-wire, 3-wire)
- Watchdog, POR and Brown-out Function
- Voltage Monitoring Inclusive Lo_BAT Detect

13. Description

The microcontroller is designed with EEPROM cells so it can be programmed several times. To offer full compatibility with each ROM version, the I/O configuration is stored into a separate internal EEPROM block during programming. The configuration is downloaded to the I/Os with every power-on reset.

14. Introduction

The microcontroller block is a member of Atmel's family of 4-bit single-chip microcontrollers. Instead of ROM it contains EEPROM, RAM, parallel I/O ports, two 8-bit programmable multi-function timer/counters, voltage supervisor, interval timer with watchdog function and a sophisticated on-chip clock generation with integrated RC-, 32-kHz and 4-MHz crystal oscillators.





14.1 Differences between ATAM862-8 and ATAR862 Microconrtollers

14.1.1 Program Memory

The program memory of the devices is realized as an EEPROM. The memory size for user programs is 4096 bytes. It is programmed as 258×16 bytes blocks of data. the implement LOCK-bit function is user-selectable and protects the device from unauthorized read-out of the program memory.

14.1.2 Configuration Memory

An additional area of 32 bytes of the EEPROM is used to store information about the hardware configuration. All the options that are selectable for the ROM versions are available to the user. This includes not only the different port options but also the possibilities to select different capacitors for OSC1 and OSC2, the option to enable or disable the hardlock for the watchdog, the option to select OSC2 instead of OSC1 as external clock input and the option to enable the external clock monitor as a reset source.

14.1.3 Data Memory

The microcontroller block contains an internal data EEPROM that is organized as two pages of 32×16 -bit. To be compatible with the ROM parts, the page used has to be defined within the application software by writing the 2-wire interface command "09h" to the EEPROM. This command has no effect for the microcontroller block, if it is left inside the HEX-file for the ROM version. Also for compatibility reasons, the access to the EEPROM is handled via the MCL (serial interface) as in the corresponding ROM parts.

14.1.4 Reset Function

During each reset (power-on or brown-out), the I/O configuration is deleted and reloaded with the data from the configuration memory. This leads to a slightly different behavior compared to the ROM versions. Both devices switch their I/Os to input during reset but the ROM part has the mask selected pull-up or pull-down resistors active while the MTP has them removed until the download is finished.

15. MARC4 Architecture General Description

The microcontroller consists of an advanced stack-based, 4-bit CPU core and on-chip peripherals. The CPU is based on the Harvard architecture with physically separated program memory (ROM) and data memory (RAM). Three independent buses, the instruction bus, the memory bus and the I/O bus, are used for parallel communication between ROM, RAM and peripherals. This enhances program execution speed by allowing both instruction prefetching, and a simultaneous communication to the on-chip peripheral circuitry. The extremely powerful integrated interrupt controller with associated eight prioritized interrupt levels supports fast and efficient processing of hardware events. The microcontroller is designed for the high-level programming language qFORTH. The core includes both an expression and a return stack. This architecture enables high-level language programming without any loss of efficiency or code density.





16. Components of Microcontroller Core

The core contains ROM, RAM, ALU, program counter, RAM address registers, instruction decoder and interrupt controller. The following sections describe each functional block in more detail.





16.1 Program Memory

The program memory (EEPROM) is programmable with the customer application program during the fabrication of the microcontroller. The EEPROM is addressed by a 12-bit wide program counter, thus predefining a maximum program bank size of 4-Kbytes. The lowest user program memory address segment is taken up by a 512 bytes Zero page which contains predefined start addresses for interrupt service routines and special subroutines accessible with single byte instructions (SCALL).

The corresponding memory map is shown in Figure 16-1. Look-up tables of constants can also be held in ROM and are accessed via the microcontrollers' built-in table instruction.



Figure 16-1. ROM Map of the Microcontroller Block

16.2 RAM

The microcontroller block contains a 256 x 4-bit wide static random access memory (RAM), which is used for the expression stack. The return stack and data memory are used for variables and arrays. The RAM is addressed by any of the four 8-bit wide RAM address registers SP, RP, X and Y.

16.2.1 Expression Stack

The 4-bit wide expression stack is addressed with the expression stack pointer (SP). All arithmetic, I/O and memory reference operations take their operands, and return their results to the expression stack. The microcontroller performs the operations with the top of stack items (TOS and TOS-1). The TOS register contains the top element of the expression stack and works in the same way as an accumulator. This stack is also used for passing parameters between subroutines and as a scratch pad area for temporary storage of data.

16.2.2 Return Stack

The 12-bit wide return stack is addressed by the return stack pointer (RP). It is used for storing return addresses of subroutines, interrupt routines and for keeping loop index counts. The return stack can also be used as a temporary storage area.

The microcontroller instruction set supports the exchange of data between the top elements of the expression stack and the return stack. The two stacks within the RAM have a user definable location and maximum depth.

Figure 16-2. RAM Map



16.3 Registers

The microcontroller has seven programmable registers and one condition code register (see Figure 16-3).

16.3.1 Program Counter (PC)

The program counter is a 12-bit register which contains the address of the next instruction to be fetched from the EEPROM. Instructions currently being executed are decoded in the instruction decoder to determine the internal micro-operations. For linear code (no calls or branches), the program counter is incremented with every instruction cycle. If a branch-, call-, return-instruction or an interrupt is executed, the program counter is loaded with a new address. The program counter is also used with the table instruction to fetch 8-bit wide EEPROM constants.



Figure 16-3. Programming Mode I





16.3.2 RAM Address Registers

The RAM is addressed with the four 8-bit wide RAM address registers: SP, RP, X and Y. These registers allow access to any of the 256 RAM nibbles.

16.3.3 Expression Stack Pointer (SP)

The stack pointer contains the address of the next-to-top 4-bit item (TOS-1) of the expression stack. The pointer is automatically pre-incremented if a nibble is moved onto the stack or post-decremented if a nibble is removed from the stack. Every post-decrement operation moves the item (TOS-1) to the TOS register before the SP is decremented. After a reset, the stack pointer has to be initialized with >SP S0 to allocate the start address of the expression stack area.

16.3.4 Return Stack Pointer (RP)

The return stack pointer points to the top element of the 12-bit wide return stack. The pointer automatically pre-increments if an element is moved onto the stack, or it post-decrements if an element is removed from the stack. The return stack pointer increments and decrements in steps of 4. This means that every time a 12-bit element is stacked, a 4-bit RAM location is left unwritten. This location is used by the qFORTH compiler to allocate 4-bit variables. After a reset the return stack pointer has to be initialized via >RP FCh.

16.3.5 RAM Address Registers (X and Y)

The X and Y registers are used to address any 4-bit item in the RAM. A fetch operation moves the addressed nibble onto the TOS. A store operation moves the TOS to the addressed RAM location. By using either the pre-increment or post-decrement addressing mode arrays in the RAM can be compared, filled or moved.

16.3.6 Top of Stack (TOS)

The top of stack register is the accumulator of the microcontroller block. All arithmetic/logic, memory reference and I/O operations use this register. The TOS register receives data from the ALU, EEPROM, RAM or I/O bus.

16.3.7 Condition Code Register (CCR)

The 4-bit wide condition code register contains the branch, the carry and the interrupt enable flag. These bits indicate the current state of the CPU. The CCR flags are set or reset by ALU operations. The instructions SET_BCF, TOG_BF, CCR! and DI allow direct manipulation of the condition code register.

16.3.8 Carry/Borrow (C)

The carry/borrow flag indicates that the borrowing or carrying out of arithmetic logic unit (ALU) occurred during the last arithmetic operation. During shift and rotate operations, this bit is used as a fifth bit. Boolean operations have no effect on the C-flag.

16.3.9 Branch (B)

The branch flag controls the conditional program branching. Should the branch flag has been set by a previous instruction, a conditional branch will cause a jump. This flag is affected by arithmetic, logic, shift, and rotate operations.

16.3.10 Interrupt Enable (I)

The interrupt enable flag globally enables or disables the triggering of all interrupt routines with the exception of the non-maskable reset. After a reset or while executing the DI instruction, the interrupt enable flag is reset, thus disabling all interrupts. The core will not accept any further interrupt requests until the interrupt enable flag has been set again by either executing an EI or SLEEP instruction.

16.4 ALU

The 4-bit ALU performs all the arithmetic, logical, shift and rotate operations with the top two elements of the expression stack (TOS and TOS-1) and returns the result to the TOS. The ALU operations affects the carry/borrow and branch flag in the condition code register (CCR).





16.5 I/O Bus

The I/O ports and the registers of the peripheral modules are I/O mapped. All communication between the core and the on-chip peripherals take place via the I/O bus and the associated I/O control. With the microcontroller IN and OUT instructions, the I/O bus allows a direct read or write access to one of the 16 primary I/O addresses. More about the I/O access to the on-chip peripherals is described in the section "Peripheral Modules" on page 32. The I/O bus is internal and is not accessible by the customer on the final microcontroller device, but it is used as the interface for the microcontroller emulation (see section "Emulation" on page 104).

16.6 Instruction Set

The microcontroller instruction set is optimized for the high level programming language qFORTH. Many microcontroller instructions are qFORTH words. This enables the compiler to generate a fast and compact program code. The CPU has an instruction pipeline allowing the controller to prefetch an instruction from EEPROM at the same time as the present instruction is being executed. The microcontroller is a zero-address machine, the instructions contain only the operation to be performed and no source or destination address fields. The operations are implicitly performed on the data placed on the stack. There are one- and two-byte instructions which are executed within 1 to 4 machine cycles. A microcontroller machine cycle is made up of two system clock cycles (SYSCL). Most of the instructions are only one byte long and are executed in a single machine cycle. For more information refer to the "MARC4 Programmer's Guide".





16.7 Interrupt Structure

The microcontroller can handle interrupts with eight different priority levels. They can be generated from the internal and external interrupt sources or by a software interrupt from the CPU itself. Each interrupt level has a hard-wired priority and an associated vector for the service routine in the EEPROM (see Table 16-1 on page 21). The programmer can postpone the processing of interrupts by resetting the interrupt enable flag (I) in the CCR. An interrupt occurrence will still be registered, but the interrupt routine only started after the I-flag is set. All interrupts can be masked, and the priority individually software configured by programming the appropriate control register of the interrupting module (see section "Peripheral Modules" on page 32).

16.7.1 Interrupt Processing

For processing the eight interrupt levels, the microcontroller includes an interrupt controller with two 8-bit wide interrupt pending and interrupt active registers. The interrupt controller samples all interrupt requests during every non-I/O instruction cycle and latches these in the interrupt pending register. If no higher priority interrupt is present in the interrupt active register, it signals the CPU to interrupt the current program execution. If the interrupt enable bit is set, the processor enters an interrupt acknowledge cycle. During this cycle a short call (SCALL) instruction to the service routine is executed and the current PC is saved on the return stack. An interrupt service routine is completed with the RTI instruction. This instruction, resets the corresponding bits in the interrupt pending/active register and fetches the return address from the return stack to the program counter. When the interrupt service routines is inhibited but not the logging of the interrupt requests in the interrupt pending register. The execution of the interrupt is delayed until the interrupt enable flag is set again. Note that interrupts are only lost if an interrupt request occurs while the corresponding bit in the pending register is still set (i.e., the interrupt service routine is not yet finished).

It should be noted that automatic stacking of the RBR is not carried out by the hardware and so if ROM banking is used, the RBR must be stacked on the expression stack by the application program and restored before the RTI. After a master reset (power-on, brown-out or watchdog reset), the interrupt enable flag and the interrupt pending and interrupt active register are all reset.

16.7.2 Interrupt Latency

The interrupt latency is the time from the occurrence of the interrupt to the interrupt service routine being activated. This is extremely short (taking between 3 to 5 machine cycles depending on the state of the core).





Table 16-1. Interrupt Priority

Interrupt	Priority	ROM Address	Interrupt Opcode	Function
INT0	Lowest	040h	C8h (SCALL 040h)	Software interrupt (SWI0)
INT1	I	080h	D0h (SCALL 080h)	External hardware interrupt, any edge at BP52 or BP53
INT2	I	0C0h	D8h (SCALL 0C0h)	Timer 1 interrupt
INT3	I	100h	E8h (SCALL 100h)	SSI interrupt or external hardware interrupt at BP40 or BP43
INT4	I	140h	E8h (SCALL 140h)	Timer 2 interrupt
INT5	I	180h	F0h (SCALL 180h)	Timer 3 interrupt
INT6	I	1C0h	F8h (SCALL 1C0h)	External hardware interrupt, at any edge at BP50 or BP51
INT7	Highest	1E0h	FCh (SCALL 1E0h)	Voltage monitor (VM) interrupt





Table 16-2. Hardware Interrupts

	Interru	pt Mask	
Interrupt	Register	Bit	Interrupt Source
INT1	P5CR	P52M1, P52M2 P53M1, P53M2	Any edge at BP52 any edge at BP53
INT2	T1M	T1IM	Timer 1
INT3	SISC	SIM	SSI buffer full/empty or BP40/BP43 interrupt
INT4	T2CM	T2IM	Timer 2 compare match/overflow
INT5	T3CM1 T3CM2 T3C	T3IM1 T3IM2 T3EIM	Timer 3 compare register 1 match Timer 3 compare register 2 match Timer 3 edge event occurs (T3I)
INT6	P5CR	P50M1, P50M2 P51M1, P51M2	Any edge at BP50, any edge at BP51
INT7	VCM	VIM	External/internal voltage monitoring

16.8 Software Interrupts

The programmer can generate interrupts by using the software interrupt instruction (SWI), which is supported in qFORTH by predefined macros named SWI0...SWI7. The software triggered interrupt operates exactly like any hardware triggered interrupt. The SWI instruction takes the top two elements from the expression stack and writes the corresponding bits via the I/O bus to the interrupt pending register. Therefore, by using the SWI instruction, interrupts can be re-prioritized or lower priority processes scheduled for later execution.

16.9 Hardware Interrupts

In the microcontroller block, there are eleven hardware interrupt sources with seven different levels. Each source can be masked individually by mask bits in the corresponding control registers. An overview of the possible hardware configurations is shown in Table 16-2.

17. Master Reset

The master reset forces the CPU into a well-defined condition. It is unmaskable and is activated independent of the current program state. It can be triggered by either initial supply power-up, a short collapse of the power supply, brown-out detection circuitry, watchdog time-out, or an external input clock supervisor stage (see Figure 17-1). A master reset activation will reset the interrupt enable flag, the interrupt pending register and the interrupt active register. During the power-on reset phase, the I/O bus control signals are set to reset mode, thereby, initializing all on-chip peripherals. All bi-directional ports are set to input mode.

Attention: During any reset phase, the BP20/NTE input is driven towards V_{DD} by an additional internal strong pull-up transistor. This pin must not be pulled down to V_{SS} during reset by any external circuitry representing a resistor of less than 150 k Ω

Releasing the reset results in a short call instruction (opcode C1h) to the ROM address 008h. This activates the initialization routine \$RESET which in turn has to initialize all necessary RAM variables, stack pointers and peripheral configuration registers (see Table 21-1 on page 34).





17.1 Power-on Reset and Brown-out Detection

The microcontroller block has a fully integrated power-on reset and brown-out detection circuitry. For reset generation no external components are needed.

These circuits ensure that the core is held in the reset state until the minimum operating supply voltage has been reached. A reset condition will also be generated should the supply voltage drop momentarily below the minimum operating level except when a power-down mode is activated (the core is in SLEEP mode and the peripheral clock is stopped). In this power-down mode the brown-out detection is disabled.

Two values for the brown-out voltage threshold are programmable via the BOT bit in the SC register.





A power-on reset pulse is generated by a V_{DD} rise across the default BOT voltage level (1.7 V). A brown-out reset pulse is generated when V_{DD} falls below the brown-out voltage threshold. Two values for the brown-out voltage threshold are programmable via the BOT bit in the SC register. When the controller runs in the upper supply voltage range with a high system clock frequency, the high threshold must be used. When it runs with a lower system clock frequency, the low threshold and a wider supply voltage range may be chosen. For further details, see the electrical specification and the SC register description for BOT programming.





BOT = 1, low brown-out voltage threshold 1.7 V (is reset value). BOT = 0, high brown-out voltage threshold 2.0 V.

17.1.1 Watchdog Reset

The watchdog's function can be enabled at the WDC register and triggers a reset with every watchdog counter overflow. To suppress the watchdog reset, the watchdog counter must be regularly reset by reading the watchdog register address (CWD). The CPU reacts in exactly the same manner as a reset stimulus from any of the above sources.

17.1.2 External Clock Supervisor

The external input clock supervisor function can be enabled if the external input clock is selected within the CM and SC registers of the clock module. The CPU reacts in exactly the same manner as a reset stimulus from any of the above sources.

18. Voltage Monitor

The voltage monitor consists of a comparator with internal voltage reference. It is used to supervise the supply voltage or an external voltage at the VMI pin. The comparator for the supply voltage has three internal programmable thresholds one lower threshold (2.2 V), one middle threshold (2.6 V) and one higher threshold (3.0 V). For external voltages at the VMI pin, the comparator threshold is set to $V_{BG} = 1.3$ V. The VMS bit indicates if the supervised voltage is below (VMS = 0) or above (VMS = 1) this threshold. An interrupt can be generated when the VMS bit is set or reset to detect a rising or falling slope. A voltage monitor interrupt (INT7) is enabled when the interrupt mask bit (VIM) is reset in the VMC register.

Figure 18-1. Voltage Monitor



18.0.1 Voltage Monitor Control/Status Register

Primary register address: "F"hex

	Bit 3	Bit 2	Bit 1	Bit 0	
VMC: Write	VM2	VM1	VM0	VIM	Reset value: 1111b
					1
VMST: Read	-	-	Reserved	VMS	Reset value: xx11b

VM2: Voltage monitor Mode bit 2

VM1: Voltage monitor Mode bit 1

VM0: Voltage monitor Mode bit 0

Table 18-1. Voltage Monitor Modes

VM2	VM1	VM0	Function
1	1	1	Disable voltage monitor
1	1	0	External (VIM input), internal reference threshold (1.3 V), interrupt with negative slope
1	0	1	Not allowed
1	0	0	External (VMI input), internal reference threshold (1.3 V), interrupt with positive slope
0	1	1	Internal (supply voltage), high threshold (3.0 V), interrupt with negative slope
0	1	0	Internal (supply voltage), middle threshold (2.6 V), interrupt with negative slope
0	0	1	Internal (supply voltage), low threshold (2.2 V), interrupt with negative slope
0	0	0	Not allowed

VIM

Voltage Interrupt Mask bit

VIM = 0, voltage monitor interrupt is enabled

VIM = 1, voltage monitor interrupt is disabled

VMS

Voltage Monitor Status bit

VMS = 0, the voltage at the comparator input is below $\ensuremath{\mathsf{V}_{\mathsf{Ref}}}$

VMS = 1, the voltage at the comparator input is above V_{Ref}













19. Clock Generation

19.1 Clock Module

The ATAM862-8 contains a clock module with 4 different internal oscillator types: two RC-oscillators, one 4-MHz crystal oscillator and one 32-kHz crystal oscillator. The pins OSC1 and OSC2 are the interface to connect a crystal either to the 4-MHz, or to the 32-kHz crystal oscillator. OSC1 can be used as input for external clocks or to connect an external trimming resistor for the RC-oscillator 2. All necessary circuitry, except the crystal and the trimming resistor, is integrated on-chip. One of these oscillator types or an external input clock can be selected to generate the system clock (SYSCL).

In applications that do not require exact timing, it is possible to use the fully integrated RC-oscillator 1 without any external components. The RC-oscillator 1 center frequency tolerance is better than \pm 50%. The RC-oscillator 2 is a trimmable oscillator whereby the oscillator frequency can be trimmed with an external resistor attached between OSC1 and V_{DD}. In this configuration, the RC-oscillator 2 frequency can be maintained stable with a tolerance of \pm 15% over the full operating temperature and voltage range.

The clock module is programmable via software with the clock management register (CM) and the system configuration register (SC). The required oscillator configuration can be selected with the OS1 bit and the OS0 bit in the SC register. A programmable 4-bit divider stage allows the adjustment of the system clock speed. A special feature of the clock management is that an external oscillator may be used and switched on and off via a port pin for the power-down mode. Before the external clock is switched off, the internal RC-oscillator 1 must be selected with the CCS bit and then the SLEEP mode may be activated. In this state an interrupt can wake up the controller with the RC-oscillator, and the external oscillator can be activated and selected by

software. A synchronization stage avoids too short clock periods if the clock source or the clock speed is changed.

If an external input clock is selected, a supervisor circuit monitors the external input and generates a hardware reset if the external clock source fails or drops below 500 kHz for more than 1 ms.





Table 19-1. Clock Modes

			Clock Source	Clock Source for	
Mode	OS1	OS0	CCS = 1	CCS = 0	SUBCL
1	1	1	RC-oscillator 1 (internal)	External input clock	C _{in} /16
2	0	1	RC-oscillator 1 (internal)	RC-oscillator 2 with external trimming resistor	C _{in} /16
3	1	0	RC-oscillator 1 (internal)	4-MHz oscillator	C _{in} /16
4	0	0	RC-oscillator 1 (internal)	32-kHz oscillator	32 kHz

The clock module generates two output clocks. One is the system clock (SYSCL) and the other the periphery (SUBCL). The SYSCL can supply the core and the peripherals and the SUBCL can supply only the peripherals with clocks. The modes for clock sources are programmable with the OS1 bit and OS0 bit in the SC register and the CCS bit in the CM register.

19.2 Oscillator Circuits and External Clock Input Stage

The microcontroller block series consists of four different internal oscillators: two RC-oscillators, one 4-MHz crystal oscillator, one 32-kHz crystal oscillator and one external clock input stage.

19.2.1 RC-oscillator 1 Fully Integrated

For timing insensitive applications, it is possible to use the fully integrated RC oscillator 1. It operates without any external components and saves additional costs. The RC-oscillator 1 center frequency tolerance is better than $\pm 50\%$ over the full temperature and voltage range. The basic center frequency of the RC-oscillator 1 is $f_0 \approx 3.8$ MHz. The RC oscillator 1 is selected by default after power-on reset.





Figure 19-2. RC-oscillator 1



19.2.2 External Input Clock

The OSC1 or OSC2 (mask option) can be driven by an external clock source provided it meets the specified duty cycle, rise and fall times and input levels. Additionally, the external clock stage contains a supervisory circuit for the input clock. The supervisor function is controlled via the OS1, OS0 bit in the SC register and the CCS bit in the CM register. If the external input clock is missing for more than 1 ms and CCS = 0 is set in the CM register, the supervisory circuit generates a hardware reset.

Figure 19-3. External Input Clock



Table 19-2. Supervisor Function Control Bits

OS1	OS0	CCS	Supervisor Reset Output (Res)
1	1	0	Enable
1	1	1	Disable
х	0	х	Disable

19.2.3 RC-oscillator 2 with External Trimming Resistor

The RC-oscillator 2 is a high resolution trimmable oscillator whereby the oscillator frequency can be trimmed with an external resistor between OSC1 and V_{DD} . In this configuration, the RC-oscillator 2 frequency can be maintained stable with a tolerance of $\pm 10\%$ over the full operating temperature and a voltage range V_{DD} from 2.5 V to 6.0 V.

For example:

An output frequency at the RC-oscillator 2 of 2 MHz can be obtained by connecting a resistor R_{ext} = 360 k Ω (see Figure 19-4 on page 29).

Figure 19-4. RC-oscillator 2



19.2.4 4-MHz Oscillator

The microcontroller block 4-MHz oscillator options need a crystal or ceramic resonator connected to the OSC1 and OSC2 pins to establish oscillation. All the necessary oscillator circuitry is integrated, except the actual crystal, resonator, C3 and C4.

Figure 19-5. 4-MHz Crystal Oscillator







19.2.5 32-kHz Oscillator

Some applications require long-term time keeping or low resolution timing. In this case, an on-chip, low power 32-kHz crystal oscillator can be used to generate both the SUBCL and the SYSCL. In this mode, power consumption is greatly reduced. The 32-kHz crystal oscillator can not be stopped while the power-down mode is in operation.





Figure 19-7. 32-kHz Crystal Oscillator



Note: Both, the 4-MHz and the 32-kHz crystal oscillator, use an integrated 14 stage divider circuit to stabilize oscillation before the oscillator output is used as system clock. This results in an additional delay of about 4 ms for the 4-MHz crystal and about 500 ms for the 32-kHz crystal.

19.3 Clock Management

The clock management register controls the system clock divider and synchronization stage. Writing to this register triggers the synchronization cycle.

19.3.1 Clock Management Register (CM)

Auxiliary register address: "3"hex

Table 2:									
		Bit 3	Bit 2	Bit 1	Bit 0				
CM:	Ν	ISTOP	CCS	CSS1	CSS0	Reset value: 1111b			
NSTOP	Not STOP NSTOP = 0 NSTOP = 1	peripher), stops t I, enable	al clock he periphe s the perip	eral clock w	hile the cor while the c	re is in SLEEP mode core is in SLEEP mode			
CCS	Core Clock Select CCS = 1, the internal RC-oscillator 1 generates SYSCL CCS = 0, the 4-MHz crystal oscillator, the 32-kHz crystal oscillator, an external clock source or the internal RC-oscillator 2 with the external resistor at OSC1 generates SYSCL dependent on the setting of OS0 and OS1 in the system configuration register								
CSS1	Core Speed	d Select	1						
CSS0	Core Speed	d Select	0						

Table 19-3. Core Speed Select

CSS1	CSS0	Divider	Note
0	0	16	-
1	1	8	Reset value
1	0	4	-
0	1	2	-

19.3.2 System Configuration Register (SC)

Primary register address: "3"hex

		Bit 3	Bit 2	Bit 1	Bit 0	
SC: write		BOT		OS1	OS0	Reset value: 1x11b
						-
	_					
DOT	Brow	n-Out Thi	reshold	valtaga th	rachald (1	7.1/1
БОТ	BOT	= 1, low b = 0, high	brown-out	voltage th	reshold (1	2.0 V)
OS1	O scil	lator S ele	ct 1			

OS0 Oscillator Select 0

Mode	OS1	OS0	Input for SUBCL	Selected Oscillators
1	1	1	C _{in/} 16	RC-oscillator 1 and external input clock
2	0	1	C _{in} /16	RC-oscillator 1 and RC-oscillator 2
3	1	0	C _{in} /16	RC-oscillator 1 and 4-MHz crystal oscillator
4	0	0	32 kHz	RC-oscillator 1 and 32-kHz crystal oscillator

Note: If the bit CCS = 0 in the CM register the RC-oscillator 1 always stops.

20. Power-down Modes

The sleep mode is a shut-down condition which is used to reduce the average system power consumption in applications where the microcontroller is not fully utilized. In this mode, the system clock is stopped. The sleep mode is entered via the SLEEP instruction. This instruction sets the interrupt enable bit (I) in the condition code register to enable all interrupts and stops the core. During the sleep mode the peripheral modules remain active and are able to generate interrupts. The microcontroller exits the sleep mode by carrying out any interrupt or a reset.

The sleep mode can only be kept when none of the interrupt pending or active register bits are set. The application of the \$AUTOSLEEP routine ensures the correct function of the sleep mode. For standard applications use the \$AUTOSLEEP routine to enter the power-down mode. Using the SLEEP instruction instead of the \$AUTOSLEEP following an I/O instruction requires to insert 3 non-I/O instruction cycles (for example NOP NOP NOP) between the IN or OUT command and the SLEEP command.

The total power consumption is directly proportional to the active time of the microcontroller. For a rough estimation of the expected average system current consumption, the following formula should be used:

 $I_{total} (V_{DD}, f_{syscl}) = I_{Sleep} + (I_{DD} \times t_{active}/t_{total})$

 I_{DD} depends on V_{DD} and f_{syscl}





The microcontroller block has various power-down modes. During the sleep mode the clock for the microcontroller block core is stopped. With the NSTOP bit in the clock management register (CM), it is programmable if the clock for the on-chip peripherals is active or stopped during the sleep mode. If the clock for the core and the peripherals is stopped, the selected oscillator is switched off. An exception is the 32-kHz oscillator, if it is selected it runs continuously independent of the NSTOP bit. If the oscillator is stopped or the 32-kHz oscillator is selected, power consumption is extremely low.

Mode	CPU Core	Osc-Stop ⁽	Brown-out Function	RC-oscillator 1 RC-oscillator 2 4-MHz Oscillator	32-kHz Oscillator	External Input Clock
Active	RUN	NO	Active	RUN	RUN	YES
Power-down	SLEEP	NO	Active	RUN	RUN	YES
SLEEP	SLEEP	YES	STOP	STOP	RUN	STOP

Table 20-1. Power-down Modes

Note: 1. Osc-Stop = SLEEP and NSTOP and WDL

21. Peripheral Modules

21.1 Addressing Peripherals

Accessing the peripheral modules takes place via the I/O bus (see Figure 21-1 on page 33). The IN or OUT instructions allow direct addressing of up to 16 I/O modules. A dual register addressing scheme has been adopted to enable direct addressing of the primary register. To address the auxiliary register, the access must be switched with an auxiliary switching module. Thus, a single IN (or OUT) to the module address will read (or write into) the module primary register. Accessing the auxiliary register is performed with the same instruction preceded by writing the module address into the auxiliary switching module. Byte wide registers are accessed by multiple IN- (or OUT-) instructions. For more complex peripheral modules, with a larger number of registers, extended addressing is used. In this case, a bank of up to 16 subport registers are indirectly addressed with the subport address. The first OUT instruction writes the subport address to the sub address register, the second IN or OUT instruction reads data from or writes data to the addressed subport.

Figure 21-1. Example of I/O Addressing



Addr.(ASW) = Auxiliary Switch Module address

Addr.(Mx) = Module Mx address

Addr.(SPort) = Subport address

- Prim._Data = Data to be written into Primary Register
- Aux._Data = Data to be written into Auxiliary Register Prim._Data(lo) = Data to be written into Auxiliary Register (low nibble)

(lo) = SPort_Data (low nibble)

SPort_Data(lo) = Data to be written into SubPort (low nibble)

SPort_Data(hi) = Data to be written into SubPort (high nibble)

(hi) = SPort_Data (high nibble)





Table 21-1. Peripheral Addresses

	Port Address		Name	Write/ Read	Reset Value	Begister Function	Module
1	i ont Addition		P1DAT	W/B	1xx1b	Port 1 - data register/input data	M3
2			P2DAT	W/B	1111b	Port 2 - data register/nipat data	M2
_	Auxiliary		P2CB	W	1111b	Port 2 - control register	
3	, tartindi y		SC	W	1x11b	System configuration register	M3
Ũ			CWD	B	xxxxb	Watchdog reset	M3
	Auxiliary		CM	W	1111b	Clock management register	M2
4			P4DAT	W/B	1111b	Port 4 - data register/pin data	M2
	Auxiliary		P4CR	W	1111 1111b	Port 4 - control register (byte)	
5	,		P5DAT	W/R	1111b	Port 5 - data register/pin data	M2
	Auxiliary		P5CR	W	1111 1111b	Port 5 - control register (byte)	
6			P6DAT	W/R	1xx1b	Port 6 - data register/pin data	M2
	Auxiliary		P6CR	W	1111b	Port 6 - control register (byte)	
7			T12SUB	W	_	Data to Timer 1/2 subport	M1
	Γ	Subport ad	dress	_			
	-	0	T2C	W	0000b	Timer 2 control register	M1
	-	1	T2M1	W	1111b	Timer 2 mode register 1	M1
	-	2	T2M2	W	1111b	Timer 2 mode register 2	M1
	-	3	T2CM	W	0000b	Timer 2 compare mode register	M1
	-	4	T2CO1	W	1111b	Timer 2 compare register 1	M1
	-	5	T2CO2	W	1111 1111b	Timer 2 compare register 2 (byte)	M1
	-	6	-	-	-	Reserved	
		7	-	-	-	Reserved	
	-	8	T1C1	W	1111b	Timer 1 control register 1	M1
		9	T1C2	W	x111b	Timer 1 control register 2	M1
		А	WDC	W	1111b	Watchdog control register	M1
		B-F				Reserved	
8			ASW	W	1111b	Auxiliary/switch register	ASW
9			STB	W	xxxx xxxxb	Serial transmit buffer (byte)	M2
			SRB	R	xxxx xxxxb	Serial receive buffer (byte)	
	Auxiliary		SIC1	W	1111b	Serial interface control register 1	
A			SISC	W/R	1x11b	Serial interface status/control register	M2
	Auxiliary		SIC2	W	1111b	Serial interface control register 2	
В	F		T3SUB	W/R	-	Data to/from Timer 3 subport	M1
	-	Subport ad	dress	1			
	-	0	ТЗМ	W	1111b	Timer 3 mode register	M1
		1	T3CS	W	1111b	Timer 3 clock select register	M1
	-	2	T3CM1	W	0000b	Timer 3 compare mode register 1	M1
		3	T3CM2	W	0000b	Timer 3 compare mode register 2	M1
	-	4	T3CO1	W	1111 1111b	Timer 3 compare register 1 (byte)	M1
	-	4	T3CP	R	xxxx xxxxb	Timer 3 capture register (byte)	M1
	F	5	13CO2	W	1111 1111b	l Imer 3 compare register 2 (byte)	M1
	F	6		W	1111b	Heserved	
		/-F		147	-	Heserved	
C	ŀ	130		W	00000	Timer 3 control register	M3
		1351		К	XUUUD	Decembed	M3
D, E		-		14/	-	Neltago monitor control register	Mo
	ŀ			VV	IIID wetth	Voltage monitor control register	IVI3
1		10101	1		77117	vonage monitor status register	IVIO

34 ATAM862-8

22. Bi-directional Ports

With the exception of Port 1 and Port 6, all other ports (2, 4 and 5) are 4 bits wide. Port 1 and Port 6 have a data width of 2 bits (bit 0 and bit 3). All ports may be used for data input or output. All ports are equipped with Schmitt trigger inputs and a variety of mask options for open-drain, open-source, full-complementary outputs, pull-up and pull-down transistors. All Port Data Registers (PxDAT) are I/O mapped to the primary address register of the respective port address and the Port Control Register (PxCR), to the corresponding auxiliary register.

There are five different directional ports available:

- Port 1 2-bit wide bi-directional port with automatic full bus width direction switching.
- Port 2 4-bit wide bitwise-programmable I/O port.
- Port 5 4-bit wide bitwise-programmable bi-directional port with optional strong pull-ups and programmable interrupt logic.
- Port 4 4-bit wide bitwise-programmable bi-directional port also provides the I/O interface to Timer 2, SSI, voltage monitor input and external interrupt input.
- Port 6 2-bit wide bitwise-programmable bi-directional port also provides the I/O interface to Timer 3 and external interrupt input.

22.1 Bi-directional Port 1

In Port 1 the data direction register is not independently software programmable, the direction of the complete port being switched automatically when an I/O instruction occurs (see Figure 22-1 on page 36). The port is switched to output mode via an OUT instruction and to input via an IN instruction. The data written to a port will be stored into the output data latches and appears immediately at the port pin following the OUT instruction. After RESET all output latches are set to "1" and the port is switched to input mode. An IN instruction reads the condition of the associated pins.

Note: Care must be taken when switching the bi-directional port from output to input. The capacitive pin loading at this port in conjunction with the high resistance pull-ups may cause the CPU to read the contents of the output data register rather than the external input state. To avoid this, one of the following programming techniques should be used:

Use two IN-instructions and DROP the first data nibble. The first IN switches the port from output to input and the DROP removes the first invalid nibble. The second IN reads the valid pin state. Use an OUT instruction followed by an IN instruction. Via the OUT instruction, the capacitive load is charged or discharged depending on the optional pull-up/pull-down configuration. Write a "1" for pins with pull-up resistors and a "0" for pins with pull-down resistors.





Figure 22-1. Bi-directional Port 1



22.2 Bi-directional Port 2

As all other bi-directional ports, this port includes a bitwise programmable Control Register (P2CR), which enables the individual programming of each port bit as input or output. It also opens up the possibility of reading the pin condition when in output mode. This is a useful feature for self testing and for serial bus applications.

Port 2, however, has an increased drive capability and an additional low resistance pull-up/pull-down transistor mask option.

Care should be taken connecting external components to BP20/NTE. During any reset phase, the BP20/NTE input is driven towards V_{DD} by an additional internal strong pull-up transistor. This pin must not be pulled down (active or passive) to V_{SS} during reset by any external circuitry representing a resistor of less than 150 k Ω . This prevents the circuit from unintended switching to test mode enable through the application circuitry at pin BP20/NTE. Resistors less than 150 k Ω might lead to an undefined state of the internal test logic thus disabling the application firmware.

To avoid any conflict with the optional internal pull-down transistors, BP20 handles the pull-down options in a different way than all other ports. BP20 is the only port that switches off the pull-down transistors during reset.
37

Figure 22-2. Bi-directional Port 2

ov_{DD} Switched Static pull-up Pull-up (Data out) D Q P2DATy BP2y V _{DD} S Master reset Q Static Pull-down SQ D

Configurable

22.2.1 Port 2 Data Register (P2DAT)

Bit 3 *	Bit 2	Bit 1	Bit 0
P2DAT3	P2DAT2	P2DAT1	P2DAT0

P2CRy

(Direction)

* Bit 3 -> MSB, Bit 0 -> LSB

I/O Bus

I/O Bus

I/O Bus

h

2

22.2.2 Port 2 Control Register (P2CR)

Bit 3	Bit 2	Bit 1	Bit 0
P2CR3	P2CR2	P2CR1	P2CR0

Value: 1111b means all pins in input mode

Table 22-1. Port 2 Control Register

Code	
3210	Function
x x x 1	BP20 in input mode
x x x 0	BP20 in output mode
x x 1 x	BP21 in input mode
x x 0 x	BP21 in output mode
x 1 x x	BP22 in input mode
x 0 x x	BP22 in output mode
1 x x x	BP23 in input mode
0 x x x	BP23 in output mode



Primary register address: "2"hex

Auxiliary register address: "2"hex

Switched pull-down

Reset value: 1111b

Reset value: 1111b



22.3 Bi-directional Port 5

As all other bi-directional ports, this port includes a bitwise programmable Control Register (P5CR), which allows the individual programming of each port bit as input or output. It also opens up the possibility of reading the pin condition when in output mode. This is a useful feature for self testing and for serial bus applications.

The port pins can also be used as external interrupt inputs (see Figure 22-3 and Figure 22-4). The interrupts (INT1 and INT6) can be masked or independently configured to trigger on either edge. The interrupt configuration and port direction is controlled by the Port 5 Control Register (P5CR). An additional low resistance pull-up/pull-down transistor mask option provides an internal bus pull-up for serial bus applications.

The Port 5 Data Register (P5DAT) is I/O mapped to the primary address register of address "5"h and the Port 5 Control Register (P5CR) to the corresponding auxiliary register. The P5CR is a byte-wide register and is configured by writing first the low nibble and then the high nibble (see section "Addressing Peripherals" on page 32).



Figure 22-3. Bi-directional Port 5





38 ATAM862-8

22.3.1 Port 5 Data Register (P5DAT)

Primary register address: "5"hex

	Bit 0	Bit 1	Bit 2	Bit 3
Reset value: 1111	P5DAT0	P5DAT1	P5DAT2	P5DAT3

22.3.2 Port 5 Control Register (P5CR) Byte Write

Auxiliary register address: "5"hex

	Bit 3	Bit 2	Bit 1	Bit 0	
First write cycle	P51M2	P51M1	P50M2	P50M1	Reset value: 1111b
	Bit 7	Bit 6	Bit 5	Bit 4	-
Second write cycle	P53M2	P53M1	P52M2	P52M1	Reset value: 1111b

P5xM2, P5xM1 – Port 5x Interrupt Mode/Direction Code

Table 22-2.Port 5 Control Register

Auxiliary Address: "5"hex, First Write Cycle			Second Write Cycle		
Code 3 2 1 0	Function	Code 3 2 1 0	Function		
x x 1 1	BP50 in input mode - interrupt disabled	x x 1 1	BP52 in input mode - interrupt disabled		
x x 0 1	BP50 in input mode – rising edge interrupt	x x 0 1	BP52 in input mode – rising edge interrupt		
x x 1 0	BP50 in input mode – falling edge interrupt	x x 1 0	BP52 in input mode – falling edge interrupt		
x x 0 0	BP50 in output mode - interrupt disabled	x x 0 0	BP52 in output mode - interrupt disabled		
11xx	BP51 in input mode - interrupt disabled	11xx	BP53 in input mode – interrupt disabled		
0 1 x x	BP51 in input mode – rising edge interrupt	0 1 x x	BP53 in input mode – rising edge interrupt		
10xx	BP51 in input mode – falling edge interrupt	1 0 x x	BP53 in input mode – falling edge interrupt		
0 0 x x	BP51 in output mode - interrupt disabled	0 0 x x	BP53 in output mode – interrupt disabled		





22.4 Bi-directional Port 4

The bi-directional Port 4 is a bitwise configurable I/O port and provides the external pins for the Timer 2, SSI and the voltage monitor input (VMI). As a normal port, it performs in exactly the same way as bi-directional Port 2 (see Figure 22-5). Two additional multiplexes allow data and port direction control to be passed over to other internal modules (Timer 2, VM or SSI). The I/O pins for SC and SD line have an additional mode to generate an SSI interrupt.

All four Port 4 pins can be individually switched by the P4CR-register. Figure 22-5 shows the internal interfaces to bi-directional Port 4.



Figure 22-5. Bi-directional Port 4 and Port 6

22.4.1 Port 4 Data Register (P4DAT)

Primary register address: "4"hex

Bit 3	Bit 2	Bit 1	Bit 0	1
P4DAT3	P4DAT2	P4DAT1	P4DAT0	Reset value: 1111b

22.4.2 Port 4 Control Register (P4CR) Byte Write

Auxiliary register address: "4"hex

	Bit 3	Bit 2	Bit 1	Bit 0	
First write cycle	P41M2	P41M1	P40M2	P40M1	Reset value: 1111b
	Bit 7	Bit 6	Bit 5	Bit 4	- -
Second write cycle	P43M2	P43M1	P42M2	P42M1	Reset value: 1111b

P4xM2, P4xM1 – Port 4x Interrupt mode/direction code

Auxiliary A	Address: "4"hex, First Write Cycle	Second Write Cycle	
Code 3 2 1 0	Function	Code 3 2 1 0	Function
x x 1 1	BP40 in input mode	x x 1 1	BP42 in input mode
x x 1 0	BP40 in output mode	x x 1 0	BP42 in output mode
x x 0 1	BP40 enable alternate function (SC for SSI)	x x 0 x	BP42 enable alternate function (T2O for Timer 2)
x x 0 0	BP40 enable alternate function (falling edge interrupt input for INT3)	11xx	BP43 in input mode
11xx	BP41 in input mode	1 0 x x	BP43 in output mode
1 0 x x	BP41 in output mode	0 1 x x	BP43 enable alternate function (SD for SSI)
0 1 x x	BP41 enable alternate function (VMI for voltage monitor input)	0 0 x x	BP43 enable alternate function (falling edge interrupt input for INT3)
0 0 x x	BP41 enable alternate function (T2I external clock input for Timer 2)	_	-

Table 22-3.	Port 4 Control Register
-------------	-------------------------

22.5 Bi-directional Port 6

The bi-directional Port 6 is a bitwise configurable I/O port and provides the external pins for the Timer 3. As a normal port, it performs in exactly the same way as bi-directional Port 6 (see Figure 22-5 on page 40). Two additional multiplexes allow data and port direction control to be passed over to other internal module (Timer 3). The I/O pin for T3I line has an additional mode to generate a Timer 3 interrupt.

All two Port 6 pins can be individually switched by the P6CR register. Figure 22-5 on page 40 shows the internal interfaces to bi-directional Port 6.

22.5.1 Port 6 Data Register (P6DAT)

Bit 3 P6DAT3

		P6DAT0	Reset value: 1xx1b
Bit 2	Bit 1	Bit 0	
			Primary register address: "6"hex

22.5.2 Port 6 Control Register (P6CR)

Auxiliary register address: "6"hex

Beset value: 1111h	Dit U DE0M0	DIL I	DIL Z	Dit 3
	FOUND	FUUIVIZ	FUSIVIT	FUSIVIZ

P6xM2, P6xM1 - Port 6x Interrupt mode/direction code





Table 22-4. Port 6 Control Register

Auxiliary A	Auxiliary Address: "6"hex		e
Code 3 2 1 0	Function	Code 3 2 1 0	Function
x x 1 1	BP60 in input mode	1 1 x x	BP63 in input mode
x x 1 0	BP60 in output mode	1 0 x x	BP63 in output mode
x x 0 x	BP60 enable alternate port function (T3O for Timer 3)	0 x x x	BP63 enable alternate port function (T3I for Timer 3)

22.6 Universal Timer/Counter/ Communication Module (UTCM)

The Universal Timer/counter/Communication Module (UTCM) consists of three timers (Timer 1, Timer 2, Timer 3) and a Synchronous Serial Interface (SSI).

- Timer 1 is an interval timer that can be used to generate periodical interrupts and as prescaler for Timer 2, Timer 3, the serial interface and the watchdog function.
- Timer 2 is an 8/12-bit timer with an external clock input (T2I) and an output (T2O).
- Timer 3 is an 8-bit timer/counter with its own input (T3I) and output (T3O).
- The SSI operates as two wire serial interface or as shift register for modulation and demodulation. The modulator and demodulator units work together with the timers and shift the data bits into or out of the shift register.

There is a multitude of modes in which the timers and the serial interface can work together.



Figure 22-6. UTCM Block Diagram

22.7 Timer 1

The Timer 1 is an interval timer which can be used to generate periodical interrupts and as prescaler for Timer 2, Timer 3, the serial interface and the watchdog function.

The Timer 1 consists of a programmable 14-stage divider that is driven by either SUBCL or SYSCL. The timer output signal can be used as prescaler clock or as SUBCL and as source for the Timer 1 interrupt. Because of other system requirements, the Timer 1 output T1OUT is synchronized with SYSCL. Therefore, in the power-down mode SLEEP (CPU core -> sleep and OSC-Stop -> yes), the output T1OUT is stopped (T1OUT = 0). Nevertheless, the Timer 1 can be active in SLEEP and generate Timer 1 interrupts. The interrupt is maskable via the T1IM bit and the SUBCL can be bypassed via the T1BP bit of the T1C2 register. The time interval for the timer output can be programmed via the Timer 1 control register T1C1.





This timer starts running automatically after any power-on reset! If the watchdog function is not activated, the timer can be restarted by writing into the T1C1 register with T1RM = 1.

Timer 1 can also be used as a watchdog timer to prevent a system from stalling. The watchdog timer is a 3-bit counter that is supplied by a separate output of Timer 1. It generates a system reset when the 3-bit counter overflows. To avoid this, the 3-bit counter must be reset before it overflows. The application software has to accomplish this by reading the CWD register.

After power-on reset the watchdog must be activated by software in the \$RESET initialization routine. There are two watchdog modes, in one mode the watchdog can be switched on and off by software, in the other mode the watchdog is active and locked. This mode can only be stopped by carrying out a system reset.

The watchdog timer operation mode and the time interval for the watchdog reset can be programmed via the watchdog control register (WDC).









22.7.1 Timer 1 Control Register 1 (T1C1)

T1C0

Address: "7"hex - Subaddress: "8"hex

Bit 3 *	Bit 2	Bit 1	Bit 0			
T1RM	T1C2	T1C1	T1C0	Reset value: 1111b		
* Bit 3 -> N	* Bit 3 -> MSB, Bit 0 -> LSB					
Timer 1 R estart M ode T1RM = 0, write access without Timer 1 restart T1RM T1RM = 1, write access with Timer 1 restart Note: If WDL = 0, Timer 1 restart is impossible						
T1C2	Timer 1 Co	ontrol bit 2				
T1C1	Timer 1 Co	ontrol bit 1				

The three bits T1C[2:0] select the divider for Timer 1. The resulting time interval depends on this divider and the Timer 1 input clock source. The timer input can be supplied by the system clock, the 32-kHz oscillator or via the clock management. If the clock management generates the SUBCL, the selected input clock from the RC oscillator, 4-MHz oscillator or an external clock is divided by 16.

Table 22-5. Timer 1 Control Bits

Timer 1 Control bit 0

T1C2	T1C1	T1C0	Divider	Time Interval with SUBCL	Time Interval with SUBCL = 32 kHz	Time Interval with SYSCL = 2/1 MHz
0	0	0	2	SUBCL/2	61 µs	1 μs/2 μs
0	0	1	4	SUBCL/4	122 µs	2 µs/4 µs
0	1	0	8	SUBCL/8	244 µs	4 μs/8 μs
0	1	1	16	SUBCL/16	488 µs	8 µs/16 µs
1	0	0	32	SUBCL/32	0.977 ms	16 µs/32 µs
1	0	1	256	SUBCL/256	7.812 ms	128 µs/256 µs
1	1	0	2048	SUBCL/2048	62.5 ms	1024 µs/2048 µs
1	1	1	16384	SUBCL/16384	500 ms	8192 µs/16384 µs



22.7.2 Timer 1 Control Register 2 (T1C2)

Bit 3 * Bit 2 Bit 1 Bit 0 T1BP T1CS - - -T1IM Reset value: x111b * Bit 3 -> MSB, Bit 0 -> LSB Timer 1 SUBCL ByPassed T1BP T1BP = 1, TIOUT = T1MUX T1BP = 0, T1OUT = SUBCL Timer 1 input Clock Select T1CS T1CS = 1, CL1 = SUBCL (see Figure 22-7 on page 44) T1CS = 0, CL1 = SYSCL (see Figure 22-7 on page 44) Timer 1 Interrupt Mask T1IM T1IM = 1, disables Timer 1 interrupt T1IM = 0, enables Timer 1 interrupt

22.7.3 Watchdog Control Register (WDC)

Address: "7"hex - Subaddress: "A"hex

Reset value: 1111b

Address: "7"hex - Subaddress: "9"hex

Bit 3 *	Bit 2	Bit 1	Bit 0
WDL	WDR	WDT1	WDT0

* Bit 3 -> MSB, Bit 0 -> LSB

WDL	WatchDog Lock mode WDL = 1, the watchdog can be enabled and disabled by using the WDR-bit WDL = 0, the watchdog is enabled and locked. In this mode the WDR-bit has no effect. After the WDL-bit is cleared, the watchdog is active until a system reset or power-on reset occurs.
WDR	WatchDog Run and stop mode WDR = 1, the watchdog is stopped/disabled WDR = 0, the watchdog is active/enabled
WDT1	WatchDog Time 1
WDT0	WatchDog Time 0

Both these bits control the time interval for the watchdog reset.

Table 22-6. Watchdog Time Control Bits

WDT1	WDT0	Divider	Delay Time to Reset with SUBCL = 32 kHz	Delay Time to Reset with SYSCL = 2/1 MHz
0	0	512	15.625 ms	0.256 ms/0.512 ms
0	1	2048	62.5 ms	1.024 ms/2.048 ms
1	0	16384	0.5 s	8.2 ms/16.4 ms
1	1	131072	4 s	65.5 ms/131 ms

22.8 Timer 2

8-/12-bit Timer for:

- Interrupt, square-wave, pulse and duty cycle generation
- · Baud-rate generation for the internal shift register
- Manchester and Biphase modulation together with the SSI
- Carrier frequency generation and modulation together with the SSI

Timer 2 can be used as an interval timer for interrupt generation, as signal generator or as baud-rate generator and modulator for the serial interface. It consists of a 4-bit and an 8-bit up counter stage which both have compare registers. The 4-bit counter stages of Timer 2 are cascadable as a 12-bit timer or as an 8-bit timer with 4-bit prescaler. The timer can also be configured as an 8-bit timer and a separate 4-bit prescaler.

The Timer 2 input can be supplied via the system clock, the external input clock (T2I), the Timer 1 output clock, the Timer 3 output clock or the shift clock of the serial interface. The external input clock T2I is not synchronized with SYSCL. Therefore, it is possible to use Timer 2 with a higher clock speed than SYSCL. Furthermore, with that input clock the Timer 2 operates in the power-down mode SLEEP (CPU core -> sleep and OSC-Stop -> yes) as well as in the POWER-DOWN (CPU core -> sleep and OSC-Stop -> no). All other clock sources supply no clock signal in SLEEP if NSTOP = 0. The 4-bit counter stages of Timer 2 have an additional clock output (POUT).

Its output has a modulator stage that allows the generation of pulses as well as the generation and modulation of carrier frequencies. The Timer 2 output can modulate with the shift register data output to generate Biphase- or Manchester code.

If the serial interface is used to modulate a bitstream, the 4-bit stage of Timer 2 has a special task. The shift register can only handle bitstream lengths divisible by 8. For other lengths, the 4-bit counter stage can be used to stop the modulator after the right bit-count is shifted out.

If the timer is used for carrier frequency modulation, the 4-bit stage works together with an additional 2-bit duty cycle generator like a 6-bit prescaler to generate carrier frequency and duty cycle. The 8-bit counter is used to enable and disable the modulator output for a programmable count of pulses.

For programming the time interval, the timer has a 4-bit and an 8-bit compare register. For programming the timer function, it has four mode and control registers. The comparator output of stage 2 is controlled by a special compare mode register (T2CM). This register contains mask bits for the actions (counter reset, output toggle, timer interrupt) which can be triggered by a compare match event or the counter overflow. This architecture enables the timer function for various modes.

The Timer 2 has a 4-bit compare register (T2CO1) and an 8-bit compare register (T2CO2). Both these compare registers are cascadable as a 12-bit compare register, or 8-bit compare register and 4-bit compare register.

For 12-bit compare data value:	m = x +1	0 ≤x ≤4095
For 8-bit compare data value:	n = y +1	0 ≤y ≤255
For 4-bit compare data value:	l = z +1	0 ≤z ≤15





Figure 22-9. Timer 2



22.9 Timer 2 Modes

22.9.1 Mode 1: 12-bit Compare Counter

The 4-bit stage and the 8-bit stage work together as a 12-bit compare counter. A compare match signal of the 4-bit and the 8-bit stage generates the signal for the counter reset, toggle flip-flop or interrupt. The compare action is programmable via the compare mode register (T2CM). The 4-bit counter overflow (OVF1) supplies the clock output (POUT) with clocks. The duty cycle generator (DCG) has to be bypassed in this mode.

Figure 22-10. 12-bit Compare Counter



22.9.2 Mode 2: 8-bit Compare Counter with 4-bit Programmable Prescaler

Figure 22-11. 8-bit Compare Counter



The 4-bit stage is used as programmable prescaler for the 8-bit counter stage. In this mode, a duty cycle stage is also available. This stage can be used as an additional 2-bit prescaler or for generating duty cycles of 25%, 33% and 50%. The 4-bit compare output (CM1) supplies the clock output (POUT) with clocks.

22.9.3 Mode 3/4: 8-bit Compare Counter and 4-bit Programmable Prescaler

Figure 22-12. 4-/8-bit Compare Counter



In these modes the 4-bit and the 8-bit counter stages work independently as a 4-bit prescaler and an 8-bit timer with an 2-bit prescaler or as a duty cycle generator. Only in the mode 3 and mode 4, can the 8-bit counter be supplied via the external clock input (T2I) which is selected via the P4CR register. The 4-bit prescaler is started via activating of mode 3 and stopped and reset in mode 4. Changing mode 3 and 4 has no effect for the 8-bit timer stage. The 4-bit stage can be used as prescaler for Timer 3, the SSI or to generate the stop signal for modulator 2 and modulator 3.





22.10 Timer 2 Output Modes

The signal at the timer output is generated via modulator 2. In the toggle mode, the compare match event toggles the output T2O. For high resolution duty cycle modulation 8 bits or 12 bits can be used to toggle the output. In the duty cycle burst modulator modes the DCG output is connected to T2O and switched on and off either by the toggle flip-flop output or the serial data line of the SSI. Modulator 2 also has two modes to output the content of the serial interface as Biphase or Manchester code.

The modulator output stage can be configured by the output control bits in the T2M2 register. The modulator is started with the start of the shift register (SIR = 0) and stopped either by carrying out a shift register stop (SIR = 1) or compare match event of stage 1 (CM1) of Timer 2. For this task, Timer 2 mode 3 must be used and the prescaler has to be supplied with the internal shift clock (SCL).





22.11 Timer 2 Output Signals

22.11.1 Timer 2 Output Mode 1

Toggle Mode A: A Timer 2 compare match toggles the output flip-flop (M2) -> T2O

Figure 22-14. Interrupt Timer/Square Wave Generator – the Output Toggles with Each Edge Compare Match Event





Figure 22-15. Pulse Generator – the Timer Output Toggles with the Timer Start if the T2TS bit Is Set



Toggle Mode C: A Timer 2 compare match toggles the output flip-flop (M2) -> T2O







22.11.2 Timer 2 Output Mode 2

Duty Cycle Burst Generator 1: The DCG output signal (DCGO) is given to the output, and gated by the output flip-flop (M2)

Figure 22-17. Carrier Frequency Burst Modulation with Timer 2 Toggle Flip-flop Output



22.11.3 Timer 2 Output Mode 3

Duty Cycle Burst Generator 2: The DCG output signal (DCGO) is given to the output, and gated by the SSI internal data output (SO)

Figure 22-18. Carrier Frequency Burst Modulation with the SSI Data Output



22.11.4 Timer 2 Output Mode 4

Biphase Modulator: Timer 2 modulates the SSI internal data output (SO) to Biphase code

Figure 22-19. Biphase Modulation



22.11.5 Timer 2 Output Mode 5

Manchester Modulator: Timer 2 modulates the SSI internal data output (SO) to Manchester code





22.11.6 Timer 2 Output Mode 7

In this mode the timer overflow defines the period and the compare register defines the duty cycle. During one period only the first compare match occurrence is used to toggle the timer output flip-flop, until the overflow all further compare match are ignored. This avoids the situation that changing the compare register causes the occurrence of several compare match during one period. The resolution at the pulse-width modulation Timer 2 mode 1 is 12-bit and all other Timer 2 modes are 8-bit.

PWM Mode: Pulse-width modulation output on Timer 2 output pin (T2O)



Figure 22-21. PWM Modulation

22.12 Timer 2 Registers

Timer 2 has 6 control registers to configure the timer mode, the time interval, the input clock and its output function. All registers are indirectly addressed using extended addressing as described in section "Addressing Peripherals". The alternate functions of the Ports BP41 or BP42 must be selected with the Port 4 control register P4CR, if one of the Timer 2 modes require an input at T2I/BP41 or an output at T2O/BP42.



22.12.1 Timer 2 Control Register (T2C)

 Bit 3
 Bit 2
 Bit 1
 Bit 0

 T2CS1
 T2CS0
 T2TS
 T2R
 Reset value: 0000b

T2CS1	Timer 2 Clock Select bit 1

T2CS0 Timer 2 Clock Select bit 0

Table 22-7. Timer 2 Clock Select

T2CS1	T2CS0	Input Clock (CL 2/1) of Counter Stage 2/1
0	0	System clock (SYSCL)
0	1	Output signal of Timer 1 (T1OUT)
1	0	Internal shift clock of SSI (SCL)
1	1	Output signal of Timer 3 (TOG3)

T2TS	Timer 2 Toggle with Start T2TS = 0, the output flip-flop of Timer 2 is not toggled with the timer start T2TS = 1, the output flip-flop of Timer 2 is toggled when the timer is started with T2R
T2R	Timer 2 Run T2R = 0, Timer 2 stop and reset T2R = 1, Timer 2 run

22.12.2 Timer 2 Mode Register 1 (T2M1)

Address: "7"hex - Subaddress: "1"hex

Address: "7"hex - Subaddress: "0"hex

	Bit 0	Bit 1	Bit 2	Bit 3
Reset value: 111	T2MS0	T2MS1	T2D0	T2D1

T2D1	Timer 2 Duty cycle bit 1
T2D0	Timer 2 Duty cycle bit 0

Table 22-8. Timer 2 Duty Cycle Bits

T2D1	T2D0	Function of Duty Cycle Generator (DCG)	Additional Divider Effect
1	1	Bypassed (DCGO0)	/1
1	0	Duty cycle 1/1 (DCGO1)	/2
0	1	Duty cycle 1/2 (DCGO2)	/3
0	0	Duty cycle 1/3 (DCGO3)	/4

T2MS1	Timer	2	Мо	de	Se	elec	ct k	oit	1
		-			_				-

T2MS0 Timer 2 Mode Select bit 0

Mode	T2MS1	T2MS0	Clock Output (POUT)	Timer 2 Modes
1	1	1	4-bit counter overflow (OVF1)	12-bit compare counter; the DCG has to be bypassed in this mode
2	1	0	4-bit compare output (CM1)	8-bit compare counter with 4-bit programmable prescaler and duty cycle generator
3	0	1	4-bit compare output (CM1)	8-bit compare counter clocked by SYSCL or the external clock input T2I, 4-bit prescaler run, the counter 2/1 starts after writing mode 3
4	0	0	4-bit compare output (CM1)	8-bit compare counter clocked by SYSCL or the external clock input T2I, 4-bit prescaler stop and resets

Table 22-9.Timer 2 Mode Select Bits

22.12.3 Duty Cycle Generator

The duty cycle generator generates duty cycles of 25%, 33% or 50%. The frequency at the duty cycle generator output depends on the duty cycle and the Timer 2 prescaler setting. The DCG-stage can also be used as additional programmable prescaler for Timer 2.

Figure 22-22. DCG Output Signals



22.12.4 Timer 2 Mode Register 2 (T2M2)

Address: "7"hex - Subaddress: "2"hex

Bit 3	Bit 2	Bit 1	Bit 0	
T2TOP	T2OS2	T2OS1	T2OS0	Reset value: 1111b

T2TOP	Timer 2 Toggle Output Preset This bit allows the programmer to preset the Timer 2 output T2O. T2TOP = 0, resets the toggle outputs with the write cycle (M2 = 0) T2TOP = 1, sets toggle outputs with the write cycle (M2 = 1) Note: If T2R = 1, no output preset is possible
T2OS2	Timer 2 Output Select bit 2
T2OS1	Timer 2 Output Select bit 1
T2OS0	Timer 2 Output Select bit 0





Output Mode	T2OS2	T2OS1	T2OS0	Clock Output
1	1	1	1	Toggle mode: a Timer 2 compare match toggles the output flip-flop (M2) -> T2O
2	1	1	0	Duty cycle burst generator 1: the DCG output signal (DCG0) is given to the output and gated by the output flip-flop (M2)
3	1	0	1	Duty cycle burst generator 2: the DCG output signal (DCGO) is given to the output and gated by the SSI internal data output (SO)
4	1	0	0	Biphase modulator: Timer 2 modulates the SSI internal data output (SO) to Biphase code
5	0	1	1	Manchester modulator: Timer 2 modulates the SSI internal data output (SO) to Manchester code
6	0	1	0	SSI output: T2O is used directly as SSI internal data output (SO)
7	0	0	1	PWM mode: an 8/12-bit PWM mode
8	0	0	0	Not allowed

 Table 22-10.
 Timer 2 Output Select Bits

22.12.5 Timer 2 Compare and Compare Mode Registers

Timer 2 has two separate compare registers, T2CO1 for the 4-bit stage and T2CO2 for the 8-bit stage of Timer 2. The timer compares the contents of the compare register current counter value and if it matches it generates an output signal. Dependent on the timer mode, this signal is used to generate a timer interrupt, to toggle the output flip-flop as SSI clock or as a clock for the next counter stage.

In the 12-bit timer mode, T2CO1 contains bits 0 to 3 and T2CO2 bits 4 to 11 of the 12-bit compare value. In all other modes, the two compare registers work independently as a 4- and 8-bit compare register.

When assigned to the compare register a compare event will be suppressed.

22.12.6 Timer 2 Compare Mode Register (T2CM)

Address: "7"hex - Subaddress: "3"hex

Bit 3	Bit 2	Bit 1	Bit 0	
T2OTM	T2CTM	T2RM	T2IM	Reset value: 0000b
T2OTM	Timer 2 O ver T2OTM = 0, T2OTM = 1,	rflow T oggle disable over enable overf flip-flop (TC generate ar	Mask bit flow toggle low toggle, a G2). If the T n interrupt ex	a counter overflow (OVF2) toggles output 2OTM bit is set, only a counter overflow can ccept on the Timer 2 output mode 7.
T2CTM	Timer 2 C om T2CTM = 0, T2CTM = 1,	pare Toggle disable com enable comp register tog when the T compare re	Mask bit pare toggle bare toggle, s gles output f 2CTM bit is gister can ge	a match of the counter with the compare lip-flop (TOG2). In Timer 2 output mode 7 and set, only a match of the counter with the enerate an interrupt.
T2RM	Timer 2 R ese T2RM = 0, d T2RM = 1, e	et M ask bit isable counte nable counte resets the c	er reset er reset, a m counter	atch of the counter with the compare register
T2IM	Timer 2 Inter T2IM = 0, dis T2IM = 1, en	rupt M ask b able Timer 2 able Timer 2	it 2 interrupt 2 interrupt	

Table 22-11.	Timer 2 Toggle Mask Bits
--------------	--------------------------

Timer 2 Output Mode	T2OTM	T2CTM	Timer 2 Interrupt Source
1, 2, 3, 4, 5 and 6	0	x	Compare match (CM2)
1, 2, 3, 4, 5 and 6	1	x	Overflow (OVF2)
7	x	1	Compare match (CM2)

22.12.7 Timer 2 COmpare Register 1 (T2CO1)

Address: "7"hex - Subaddress: "4"hex

 Write cycle
 Bit 3
 Bit 2
 Bit 1
 Bit 0
 Reset value: 1111b

In prescaler mode the clock is bypassed if the compare register T2CO1 contains 0.

22.12.8 Timer 2 COmpare Register 2 (T2CO2) Byte Write

					Address: "7"hex - Subaddress: "5"hex
First write cycle	Bit 3	Bit 2	Bit 1	Bit 0	Reset value: 1111b
Second write cycle	Bit 7	Bit 6	Bit 5	Bit 4	Reset value: 1111b
	L				





23. Timer 3

23.1 Features

- Two Compare Registers
- Capture Register
- Edge Sensitive Input with Zero Cross Detection Capability
- Trigger and Single Action Modes
- Output Control Modes
- Automatically Modulation and Demodulation Modes
- FSK Modulation
- Pulse Width Modulation (PWM)
- Manchester Demodulation Together with SSI
- Biphase Demodulation Together with SSI
- Pulse-width Demodulation Together with SSI





Timer 3 consists of an 8-bit up-counter with two compare registers and one capture register. The timer can be used as event counter, timer and signal generator. Its output can be programmed as modulator and demodulator for the serial interface. The two compare registers enable various modes of signal generation, modulation and demodulation. The counter can be driven by internal and external clock sources. For external clock sources, it has a programmable edge-sensitive input which can be used as counter input, capture signal input or trigger input. This timer input is synchronized with SYSCL. Therefore, in the power-down mode SLEEP (CPU core -> sleep and OSC-Stop -> yes), this timer input is stopped too. The counter is readable via its capture register while it is running. In capture mode, the counter value can be captured by a programmable capture event from the Timer 3 input or Timer 2 output.

A special feature of this timer is the trigger- and single-action mode. In trigger mode, the counter starts counting triggered by the external signal at its input. In single-action mode, the counter counts only one time up to the programmed compare match event. These modes are very useful for modulation, demodulation, signal generation, signal measurement and phase controlling. For phase controlling, the timer input is protected against negative voltages and has zero-cross detection capability.

Timer 3 has a modulator output stage and input functions for demodulation. As modulator it works together with Timer 2 or the serial interface. When the shift register is used for modulation the data shifted out of the register is encoded bitwise. In all demodulation modes, the decoded data bits are shifted automatically into the shift register.

23.2 Timer/Counter Modes

Timer 3 has 6 timer modes and 6 modulator/demodulator modes. The mode is set via the Timer 3 Mode Register T3M.

In all these modes, the compare register and the compare-mode register belonging to it define the counter value for a compare match and the action of a compare match. A match of the current counter value with the content of one compare register triggers a counter reset, a Timer 3 interrupt or the toggling of the output flip-flop. The compare mode registers T3M1 and T3M2 contain the mask bits for enabling or disabling these actions.

The counter can also be enabled to execute single actions with one or both compare registers. If this mode is set the corresponding compare match event is generated only once after the counter start.

Most of the timer modes use their compare registers alternately. After the start has been activated, the first comparison is carried out via the compare register 1, the second is carried out via the compare register 2, the third is carried out again via the compare register 1 and so on. This makes it easy to generate signals with constant periods and variable duty cycle or to generate signals with variable pulse and space widths.

If single-action mode is set for one compare register, the comparison is always carried out after the first cycle via the other compare register.

The counter can be started and stopped via the control register T3C. This register also controls the initial level of the output before start. T3C contains the interrupt mask for a T3I input interrupt.

Via the Timer 3 clock-select register, the internal or external clock source can be selected. This register selects also the active edge of the external input. An edge at the external input T3I can generate also an interrupt if the T3EIM-bit is set and the Timer 3 is stopped (T3R = 0) in the T3C-register.





Figure 23-2. Counter 3 Stage



The status of the timer as well as the occurrence of a compare match or an edge detect of the input signal is indicated by the status register T2ST. This allows identification of the interrupt source because all these events share only one timer interrupt.

Timer 3 compares data values.

The Timer 3 has two 8-bit compare registers (T3CO1, T3CO2). The compare data value can be 'm' for each of the Timer 3 compare registers.

The compare data value for the compare registers is: m = x + 1 $0 \le x \le 255$

23.2.1 Timer 3 – Mode 1: Timer/Counter

The selected clock from an internal or external source increments the 8-bit counter. In this mode, the timer can be used as event counter for external clocks at T3I or as timer for generating interrupts and pulses at T3O. The counter value can be read by the software via the capture register.

Figure 23-3. Counter Reset with Each Compare Match





Counter Reset with Compare Register 2 and Toggle with Start Figure 23-4.

Figure 23-5. Single Action of Compare Register 1



23.2.2 Timer 3 – Mode 2: Timer/Counter, External Trigger Restart and External Capture (with T3I Input)

The counter is driven by an internal clock source. After starting with T3R, the first edge from the external input T3I starts the counter. The following edges at T3I load the current counter value into the capture register, reset the counter and restart it. The edge can be selected by the programmable edge decoder of the timer input stage. If single-action mode is activated for one or both compare registers the trigger signal restarts the single action.



Figure 23-6. Externally Triggered Counter Reset and Start Combined with Single-action Mode





23.2.3 Timer 3 – Mode 3: Timer/Counter, Internal Trigger Restart and Internal Capture (with TOG2)

The counter is driven by an internal or external (T3I) clock source. The output toggle signal of Timer 2 resets the counter. The counter value before the reset is saved in the capture register. If single-action mode is activated for one or both compare registers, the trigger signal restarts the single actions. This mode can be used for frequency measurements or as event counter with time gate (see "Combination Mode 10: Frequency Measurement or Event Counter with Time Gate" on page 91).





23.2.4 Timer 3 – Mode 4: Timer/Counter

The timer runs as timer/counter in mode 1, but its output T3O is used as output for the Timer 2 output signal.

23.2.5 Timer 3 – Mode 5: Timer/Counter, External Trigger Restart and External Capture (with T3I Input)

The Timer 3 runs as timer/counter in mode 2, but its output T3O is used as output for the Timer 2 output signal.

23.3 Timer 3 Modulator/Demodulator Modes

23.3.1 Timer 3 – Mode 6:

Carrier Frequency Burst Modulation Controlled by Timer 2 Output Toggle Flip-Flop (M2)

The Timer 3 counter is driven by an internal or external clock source. Its compare- and compare mode registers must be programmed to generate the carrier frequency via the output toggle flip-flop. The output toggle flip-flop of Timer 2 is used to enable or disable the Timer 3 output. Timer 2 can be driven by the toggle output signal of Timer 3 or any other clock source (see "Combination Mode 11: Burst Modulation 1" on page 92).

23.3.2 Timer 3 – Mode 7: Carrier Frequency Burst Modulation Controlled by SSI Internal Output (SO)

The Timer 3 counter is driven by an internal or external clock source. Its compare- and compare mode registers must be programmed to generate the carrier frequency via the output toggle flip-flop. The output (SO) of the SSI is used to enable or disable the Timer 3 output. The SSI should be supplied with the toggle signal of Timer 2 (see "Combination Mode 12: Burst Modulation 2" on page 94).

23.3.3 Timer 3 – Mode 8: FSK Modulation with Shift Register Data (SO)

The two compare registers are used for generating two different time intervals. The SSI internal data output (SO) selects which compare register is used for the output frequency generation. A "0" level at the SSI data output enables the compare register 1. A "1" level enables compare register 2. The compare- and compare-mode registers must be programmed to generate the two frequencies via the output toggle flip-flop. The SSI can be supplied with the toggle signal of Timer 2. The Timer 3 counter is driven by an internal or external clock source. The Timer 2 counter is driven by the Counter 3 (TOG3) (see "Combination Mode 12: Burst Modulation 2" on page 94).



Figure 23-8. FSK Modulation





23.3.4 Timer 3 – Mode 9: Pulse-width Modulation with the Shift Register

The two compare registers are used for generating two different time intervals. The SSI internal data output (SO) selects which compare register is used for the output pulse generation. In this mode both compare- and compare-mode registers must be programmed for generating the two pulse widths. It is also useful to enable the single-action mode for extreme duty cycles. Timer 2 is used as baudrate generator and for the trigger restart of Timer 3. The SSI must be supplied with a toggle signal of Timer 2. The counter is driven by an internal or external clock source (see "Combination Mode 7: Pulse-width Modulation (PWM)" on page 88).



Figure 23-9. Pulse-width Modulation

23.3.5 Timer 3 – Mode 10: Manchester Demodulation/Pulse-width Demodulation

For Manchester demodulation, the edge detection stage must be programmed to detect each edge at the input. These edges are evaluated by the demodulator stage. The timer stage is used to generate the shift clock for the SSI. The compare register 1 match event defines the correct moment for shifting the state from the input T3I as the decoded bit into shift register - after that the demodulator waits for the next edge to synchronize the timer by a reset for the next bit. The compare register 2 can also be used to detect a time-out error and handle it with an interrupt routine (see "Combination Mode 8: Manchester Demodulation/Pulse-width Demodulation" on page 89).

Figure 23-10. Manchester Demodulation



ATAM862-8

23.3.6 Timer 3 – Mode 11: Biphase Demodulation

In the Biphase demodulation mode, the timer operates like in Manchester demodulation mode. The difference is that the bits are decoded via a toggle flip-flop. This flip-flop samples the edge in the middle of the bitframe and the compare register 1 match event shifts the toggle flip-flop output into shift register (see "Combination Mode 9: Biphase Demodulation" on page 90).





23.3.7 Timer 3 – Mode 12: Timer/Counter with External Capture Mode (T3I)

The counter is driven by an internal clock source and an edge at the external input T3I loads the counter value into the capture register. The edge can be selected with the programmable edge detector of the timer input stage. This mode can be used for signal and pulse measurements.

Figure 23-12. External Capture Mode







23.4 Timer 3 Modulator for Carrier Frequency Burst Modulation

If the output stage operates as pulse-width modulator for the shift register, the output can be stopped with stage 1 of Timer 2. For this task, the timer mode 3 must be used and the prescaler must be supplied by the internal shift clock of the shift register.

The modulator can be started with the start of the shift register (SIR = 0) and stopped either by a shift register stop (SIR = 1) or compare match event of stage 1 of Timer 2. For this task, the Timer 2 must be used in mode 3 and the prescaler stage must be supplied by the internal shift clock of the shift register.

Figure 23-13. Modulator 3



23.5 Timer 3 Demodulator for Biphase, Manchester and Pulse-width-modulated Signals

The demodulator stage of Timer 3 can be used to decode Biphase, Manchester and pulse-width-coded signals.

Figure 23-14. Timer 3 Demodulator 3



23.6 Timer 3 Registers

23.6.1 Timer 3 Mode Register (T3M)

T3M2

Address: "B"hex - Subaddress: "0"hex

Reset value: 1111b

Bit 3	Bit 2	Bit 1	Bit 0
ТЗМЗ	T3M2	T3M1	T3M0
TO 140	T : 0.11		
131/13	I Imer 3 Mod	e seiect bit 3	5

T3M1	Timer 3 Mode select bit 1
ТЗМ0	Timer 3 Mode select bit 0

Table 23-1. Timer 3 Mode Select Bits

Timer 3 Mode select bit 2

Mode	T3M3	T3M2	T3M1	T3M0	Timer 3 Modes
1	1	1	1	1	Timer/counter with a read access
2	1	1	1	0	Timer/counter, external capture and external trigger restart mode (T3I)
3	1	1	0	1	Timer/counter, internal capture and internal trigger restart mode (TOG2)
4	1	1	0	0	Timer/counter mode 1 without output (T2O -> T3O)
5	1	0	1	1	Timer/counter mode 2 without output (T2O -> T3O)
6	1	0	1	0	Burst modulation with Timer 2 (M2)
7	1	0	0	1	Burst modulation with shift register (SO)
8	1	0	0	0	FSK modulation with shift register (SO)
9	0	1	1	1	Pulse-width modulation with shift register (SO) and Timer 2 (TOG2), internal trigger restart (SCO) -> counter reset
10	0	1	1	0	Manchester demodulation/pulse-width demodulation ⁽¹⁾ (T2O -> T3O)
11	0	1	0	1	Biphase demodulation (T2O -> T3O)
12	0	1	0	0	Timer/counter with external capture mode (T3I)
13	0	0	1	1	Not allowed
14	0	0	1	0	Not allowed
15	0	0	0	1	Not allowed
16	0	0	0	0	Not allowed

Note: 1. In this mode, the SSI can be used only as demodulator (8-bit NRZ rising edge). All other SSI modes are not allowed.





23.6.2 Timer 3 Control Register 1 (T3C) Write

Primary register address: "C"hex - Write

		Bit 3	Bit 2	Bit 1	Bit 0			
Write		T3EIM	T3TOP	T3TS	T3R	Reset value: 0000b		
T3EIM	T imer T3EIN T3EIN	3 E dge Inter I = 0, disabl I = 1, enable	errupt M ask les the internes the internes	rupt when ar upt when ar	n edge even i edge even	t for Timer 3 occurs (T3I) t for Timer 3 occurs (T3I)		
ТЗТОР	Timer 3 T oggle O utput P reset T3TOP = 0, sets toggle output (M3) to "0" T3TOP = 1, sets toggle output (M3) to "1" Note: If T3R = 1, no output preset is possible							
T3TS	Timer	3 Toggle wi	ith S tart . T3 T3	3TS = 0, Tim 3TS = 1, Tim	ner 3 output ner 3 output	is not toggled during the start is toggled if started with T3R		
T3R	Timer	3 R un		BR = 0, Time BR = 1, Time	er 3 stop and er 3 run	d reset		

23.6.3 Timer 3 Status Register 1 (T3ST) Read

Primary register address: "C"hex - Read

	Bit 3	Bit 2	Bit 1	Bit 0	
Read		T3ED	T3C2	T3C1	Reset value: x000b

T3ED	Timer 3 E dge D etect This bit will be set by the edge-detect logic of Timer 3 input (T3I)
T3C2	Timer 3 C ompare 2 This bit will be set when a match occurs between Counter 3 and T3CO2
T3C1	Timer 3 C ompare 1 This bit will be set when a match occurs between Counter 3 and T3CO1
Note:	The status bits T3C1, T3C2 and T3ED will be reset after a READ access to T3ST.

23.6.4 Timer 3 Clock Select Register (T3CS)

Address: "B"hex - Subaddress: "1"hex

	Bit 3	Bit 2	Bit 1	Bit 0	
T3CS	T3E1	T3E0	T3CS1	T3CS0	Reset value: 1111b

T3E1Timer 3 Edge select bit 1

T3E0 Timer 3 Edge select bit 0

Table 23-2. Timer 3 Edge Select Bits

T3E1	T3E0	Timer 3 Input Edge Select (T3I)
1	1	
1	0	Positive edge at T3I pin
0	1	Negative edge at T3I pin
0	0	Each edge at T3I pin

T3CS1 Timer 3 Clock Source select bit 1

T3CS0 Timer 3 Clock Source select bit 0

T3CS1	TCS0	Counter 3 Input Signal (CL3)
1	1	System clock (SYSCL)
1	0	Output signal of Timer 2 (POUT)
0	1	Output signal of Timer 1 (T1OUT)
0	0	External input signal from T3I edge detect

23.6.5 Timer 3 Compare- and Compare-mode Register

Timer 3 has two separate compare registers T3CO1 and T3CO2 for the 8-bit stage of Timer 3. The timer compares the content of the compare register with the current counter value. If both match, it generates a signal. This signal can be used for the counter reset, to generate a timer interrupt, for toggling the output flip-flop, as SSI clock or as clock for the next counter stage. For each compare register, a compare-mode register exists. These registers contain mask bits to enable or disable the generation of an interrupt, a counter reset, or an output toggling with the occurrence of a compare match of the corresponding compare register. The mask bits for activating the single-action mode can also be located in the compare mode registers. When assigned to the compare register a compare event will be suppressed.





23.6.6 Timer 3 Compare-Mode Register 1 (T3CM1)

Address: "B"hex - Subaddress: "2"hex

	Bit 3	Bit 2	Bit 1	Bit 0				
T3CM1	T3SM1	T3TM1	T3RM1	T3IM1	Reset value: 0000b			
T3SM1	T imer 3 S ingle T3SM1 = 0, di T3SM1 = 1, e	e action M a sables sing nables sing register (T3	sk bit 1 le-action co le-compare CO1) is use	ompare mo mode. Afte	de er this bit is set, the compare next compare match.			
T3TM1	Timer 3 compare Toggle action Mask bit 1 T3TM1 = 0, disables compare toggle T3TM1 = 1, enables compare toggle. A match of Counter 3 with the compare register (T3CO1) toggles the output flip-flop (TOG3).							
T3RM1	Timer 3 R eset M ask bit 1 T3RM1 = 0, disables counter reset T3RM1 = 1, enables counter reset. A match of Counter 3 with the compare register (T3CO1) resets the Counter 3.							
T3IM1	Timer 3 Interrupt M ask bit 1 T3RM1 = 0, disables Timer 3 interrupt for T3CO1 register. T3RM1 = 1, enables Timer 3 interrupt for T3CO1 register.							

T3CM1 contains the mask bits for the match event of the Counter 3 compare register 1.

23.6.7 Timer 3 Compare Mode Register 2 (T3CM2)

Address: "B"hex - Subaddress: "3"hex

		Bit 3	Bit 2	Bit 1	Bit 0				
T3CM2		T3SM2	T3TM2	T3RM2	T3IM2	Reset value: 0000b			
T3SM2	Timer 3 S ingle action M ask bit 2 T3SM2 = 0, disables single-action compare mode T3SM2 = 1, enables single-compare mode. After this bit is set, the compare register (T3CO2) is used until the next compare match.								
T3TM2	Timer 3 compare Toggle action Mask bit 2 T3TM2 = 0, disables compare toggle T3TM2 = 1, enables compare toggle. A match of Counter 3 with the compare register (T3CO2) toggles the output flip-flop (TOG3).								
T3RM2	Timer 3 R eset M ask bit 2 T3RM2 = 0, disables counter reset T3RM2 = 1, enables counter reset. A match of Counter 3 with the compare register (T3CO2) resets the Counter 3.								
T3IM2	Timer 3 Interrupt M ask bit 2 T3RM2 = 0, disables Timer 3 interrupt for T3CO2 register. T3RM2 = 1, enables Timer 3 interrupt for T3CO2 register.								
T3CM2 con	T3CM2 contains the mask bits for the match event of Counter 3 compare register 2								

ATAM862-8

The compare registers and corresponding counter reset masks can be used to program the counter time intervals and the toggle masks can be used to program output signal. The single-action mask can also be used in this mode. It starts operating after the timer started with T3R.

23.6.8 Timer 3 COmpare Register 1 (T3CO1) Byte Write

				Add	dress: "B"hex - Subaddress: "4"hex
		High	Nibble		
Second write cycle	Bit 7	Bit 6	Bit 5	Bit 4	Reset value: 1111b
		Low I	Vibble		
First write cycle	Bit 3	Bit 2	Bit15	Bit 0	Reset value: 1111b
			1	1	

23.6.9 Timer 3 COmpare Register 2 (T3CO2) Byte Write

Address: "B"hex - Subaddress: "5"hex

Address: "B"hex - Subaddress: "4"hex



23.7 Timer 3 Capture Register

The counter content can be read via the capture register. There are two ways to use the capture register. In modes 1 and 4, it is possible to read the current counter value directly out of the capture register. In the capture modes 2, 3, 5 and 12, a capture event like an edge at the Timer 3 input or a signal from Timer 2 stores the current counter value into the capture register. This counter value can be read from the capture register.

23.7.1 Timer 3 CaPture Register (T3CP) Byte Read

		High	Nibble		
First read cycle	Bit 7	Bit 6	Bit 5	Bit 4	Reset value: xxxxb
		Low I	Nibble		
Second read cycle	Bit 3	Bit 2	Bit15	Bit 0	Reset value: xxxxb





23.8 Synchronous Serial Interface (SSI)

23.8.1 SSI Features

- With Timer 1
 - 2- and 3-wire NRZ
 - 2-wire mode multi-chip link mode (MCL), additional internal 2-wire link for multi-chip packaging solutions
- With Timer 2
 - Biphase modulation
 - Manchester modulation
 - Pulse-width demodulation
 - Burst modulation
- With Timer 3
 - Pulse-width modulation (PWM)
 - FSK modulation
 - Biphase demodulation
 - Manchester demodulation
 - Pulse-width demodulation
 - Pulse position demodulation

23.8.2 SSI Peripheral Configuration

The synchronous serial interface (SSI) can be used either for serial communication with external devices such as EEPROMs, shift registers, display drivers, other microcontrollers, or as a means for generating and capturing on-chip serial streams of data. External data communication takes place via the Port 4 (BP4), a multi-functional port which can be software configured by writing the appropriate control word into the P4CR register. The SSI can be configured in any of the following ways:

- 1. 2-wire external interface for bi-directional data communication with one data terminal and one shift clock. The SSI uses the Port BP43 as a bi-directional serial data line (SD) and BP40 as shift clock line (SC).
- 2. 3-wire external interface for simultaneous input and output of serial data, with a serial input data terminal (SI), a serial output data terminal (SO) and a shift clock (SC). The SSI uses BP40 as shift clock (SC), while the serial data input (SI) is applied to BP43 (configured in P4CR as input). Serial output data (SO) in this case is passed through to BP42 (configured in P4CR to T2O) via the Timer 2 output stage (T2M2 configured in mode 6).
- 3. Timer/SSI combined modes the SSI used together with Timer 2 or Timer 3 is capable of performing a variety of data modulation and demodulation functions (see Timer Section). The modulating data is converted by the SSI into a continuous serial stream of data which is in turn modulated in one of the timer functional blocks. Serial demodulated data can be serially captured in the SSI and read by the controller. In the Timer 3 modes 10 and 11 (demodulation modes) the SSI can only be used as demodulator.
4. Multi-chip link (MCL) – the SSI can also be used as an interchip data interface for use in single package multi-chip modules or hybrids. For such applications, the SSI is provided with two dedicated pads (MCL_SD and MCL_SC) which act as a two-wire chip-to-chip link. The MCL can be activated by the MCL control bit. Should these MCL pads be used by the SSI, the standard SD and SC pins are not required and the corresponding Port 4 ports are available as conventional data ports.



Figure 23-15. Block Diagram of the Synchronous Serial Interface

23.8.3 General SSI Operation

The SSI is comprised essentially of an 8-bit shift register with two associated 8-bit buffers – the receive buffer (SRB) for capturing the incoming serial data and a transmit buffer (STB) for intermediate storage of data to be serially output. Both buffers are directly accessable by software. Transferring the parallel buffer data into and out of the shift register is controlled automatically by the SSI control, so that both single byte transfers or continuous bit streams can be supported.

The SSI can generate the shift clock (SC) either from one of several on-chip clock sources or accept an external clock. The external shift clock is output on, or applied to the Port BP40. Selection of an external clock source is performed by the Serial Clock Direction control bit (SCD). In the combinational modes, the required clock is selected by the corresponding timer mode.

The SSI can operate in three data transfer modes – synchronous 8-bit shift mode, MCL compatible 9-bit shift modes or 8-bit pseudo MCL protocol (without acknowledge-bit).

External SSI clocking is not supported in these modes. The SSI should thus generate and has full control over the shift clock so that it can always be regarded as an MCL Bus Master device.

All directional control of the external data port used by the SSI is handled automatically and is dependent on the transmission direction set by the Serial Data Direction (SDD) control bit. This control bit defines whether the SSI is currently operating in Transmit (TX) mode or Receive (RX) mode.

Serial data is organized in 8-bit telegrams which are shifted with the most significant bit first. In the 9-bit MCL mode, an additional acknowledge bit is appended to the end of the telegram for handshaking purposes (see "MCL Bus Protocol" on page 77).





At the beginning of every telegram, the SSI control loads the transmit buffer into the shift register and proceeds immediately to shift data serially out. At the same time, incoming data is shifted into the shift register input. This incoming data is automatically loaded into the receive buffer when the complete telegram has been received. Thus, data can be simultaneously received and transmitted if required.

Before data can be transferred, the SSI must first be activated. This is performed by means of the SSI reset control (SIR) bit. All further operation then depends on the data directional mode (TX/RX) and the present status of the SSI buffer registers shown by the Serial Interface Ready Status Flag (SRDY). This SRDY flag indicates the (empty/full) status of either the transmit buffer (in TX mode), or the receive buffer (in RX mode). The control logic ensures that data shifting is temporarily halted at any time, if the appropriate receive/transmit buffer is not ready (SRDY = 0). The SRDY status will then automatically be set back to '1' and data shifting resumed as soon as the application software loads the new data into the transmit register (in TX mode) or frees the shift register by reading it into the receive buffer (in RX mode).

A further activity status (ACT) bit indicates the present status of the serial communication. The ACT bit remains high for the duration of the serial telegram or if MCL stop or start conditions are currently being generated. Both the current SRDY and ACT status can be read in the SSI status register. To deactivate the SSI, the SIR bit must be set high.

23.8.4 8-bit Synchronous Mode



Figure 23-16. 8-bit Synchronous Mode

In the 8-bit synchronous mode, the SSI can operate as either a 2- or 3-wire interface (see "SSI Peripheral Configuration" on page 72). The serial data (SD) is received or transmitted in NRZ format, synchronized to either the rising or falling edge of the shift clock (SC). The choice of clock edge is defined by the Serial Mode Control bits (SM0,SM1). It should be noted that the transmission edge refers to the SC clock edge with which the SD changes. To avoid clock skew problems, the incoming serial input data is shifted in with the opposite edge.

When used together with one of the timer modulator or demodulator stages, the SSI must be set in the 8-bit synchronous mode 1.

In RX mode, as soon as the SSI is activated (SIR = 0), 8 shift clocks are generated and the incoming serial data is shifted into the shift register. This first telegram is automatically transferred into the receive buffer and the SRDY set to 0 indicating that the receive buffer contains valid data. At the same time an interrupt (if enabled) is generated. The SSI then continues shifting in the following 8-bit telegram. If, during this time the first telegram has been read by the controller, the second telegram will also be transferred in the same way into the receive buffer

and the SSI will continue clocking in the next telegram. Should, however, the first telegram not have been read (SRDY = 1), then the SSI will stop, temporarily holding the second telegram in the shift register until a certain point of time when the controller is able to service the receive buffer. In this way no data is lost or overwritten.

Deactivating the SSI (SIR = 1) in mid-telegram will immediately stop the shift clock and latch the present contents of the shift register into the receive buffer. This can be used for clocking in a data telegram of less than 8 bits in length. Care should be taken to read out the final complete 8-bit data telegram of a multiple word message before deactivating the SSI (SIR = 1) and terminating the reception. After termination, the shift register contents will overwrite the receive buffer.



Figure 23-17. Example of 8-bit Synchronous Transmit Operation









23.8.5 9-bit Shift Mode (MCL compatible)

In the 9-bit shift mode, the SSI is able to handle the MCL protocol (described below). It always operates as an MCL master device, i.e., SC is always generated and output by the SSI. Both the MCL start and stop conditions are automatically generated whenever the SSI is activated or deactivated by the SIR bit. In accordance with the MCL protocol, the output data is always changed in the clock low phase and shifted in on the high phase.

Before activating the SSI (SIR = 0) and commencing an MCL dialog, the appropriate data direction for the first word must be set using the SDD control bit. The state of this bit controls the direction of the data port (BP43 or MCL_SD). Once started, the 8 data bits are, depending on the selected direction, either clocked into or out of the shift register. During the 9th clock period, the port direction is automatically switched over so that the corresponding acknowledge bit can be shifted out or read in. In transmit mode, the acknowledge bit received from the device is captured in the SSI Status Register (TACK) where it can be read by the controller. In receive mode, the state of the acknowledge bit to be returned to the device is predetermined by the SSI Status Register (RACK).

Changing the directional mode (TX/RX) should not be performed during the transfer of an MCL telegram. One should wait until the end of the telegram which can be detected using the SSI interrupt (IFN =1) or by interrogating the ACT status.

Once started, a 9-bit telegram will always run to completion and will not be prematurely terminated by the SIR bit. So, if the SIR bit is set to '1' in telegram, the SSI will complete the current transfer and terminate the dialog with an MCL stop condition.



Figure 23-19. Example of MCL Transmit Dialog





23.8.6 8-bit Pseudo MCL Mode

In this mode, the SSI exhibits all the typical MCL operational features except for the acknowledge-bit which is never expected or transmitted.

23.8.7 MCL Bus Protocol

The MCL protocol constitutes a simple 2-wire bi-directional communication highway via which devices can communicate control and data information. Although the MCL protocol can support multi-master bus configurations, the SSI in MCL mode is intended for use purely as a master controller on a single master bus system. So all reference to multiple bus control and bus contention will be omitted at this point.

All data is packaged into 8-bit telegrams plus a trailing handshaking or acknowledge-bit. Normally the communication channel is opened with a so-called start condition, which initializes all devices connected to the bus. This is then followed by a data telegram, transmitted by the master controller device. This telegram usually contains an 8-bit address code to activate a single slave device connected onto the I²C bus. Each slave receives this address and compares it with its own unique address. The addressed slave device, if ready to receive data, will respond by pulling the SD line low during the 9th clock pulse. This represents a so-called MCL acknowledge. The controller detecting this affirmative acknowledge then opens a connection to the required slave. Data can then be passed back and forth by the master controller, each 8-bit telegram being acknowledged by the respective recipient. The communication is finally closed by the master device and the slave device put back into standby by applying a stop condition onto the bus.





Figure 23-21. MCL Bus Protocol 1





Figure 23-22. MCL Bus Protocol 2



23.8.8 SSI Interrupt

The SSI interrupt INT3 can be generated either by an SSI buffer register status (i.e., transmit buffer empty or receive buffer full), the end of SSI data telegram or on the falling edge of the SC/SD pins on Port 4 (see "Port 4 Control Register (P4CR) Byte Write" on page 40). SSI interrupt selection is performed by the Interrupt FunctioN control bit (IFN). The SSI interrupt is usually used to synchronize the software control of the SSI and inform the controller of the present SSI status. The Port 4 interrupts can be used together with the SSI or, if the SSI itself is not required, as additional external interrupt sources. In either case this interrupt is capable of waking the controller out of sleep mode.

To enable and select the SSI relevant interrupts use the SSI interrupt mask (SIM) and the Interrupt Function (IFN) while the Port 4 interrupts are enabled by setting appropriate control bits in P4CR register.

23.8.9 Modulation and Demodulation

If the shift register is used together with Timer 2 or Timer 3 for modulation or demodulation purposes, the 8-bit synchronous mode must be used. In this case, the unused Port 4 pins can be used as conventional bi-directional ports.

The modulation and demodulation stages, if enabled, operate as soon as the SSI is activated (SIR = 0) and cease when deactivated (SIR = 1).

Due to the byte-orientated data control, the SSI (when running normally) generates serial bit streams which are submultiples of 8 bits. An SSI output masking (OMSK) function permits; however, the generation of bit streams of any length. The OMSK signal is derived indirectly from the 4-bit prescaler of the Timer 2 and masks out a programmable number of unrequired trailing data bits during the shifting out of the final data word in the bit stream. The number of non-masked data bits is defined by the value preprogrammed in the prescaler compare register. To use output masking, the modulator stop mode bit (MSM) must be set to "0" before programming the final data word into the SSI transmit buffer. This in turn, enables shift clocks to the prescaler when this final word is shifted out. On reaching the compare value, the prescaler triggers the OMSK signal and all following data bits are blanked.



Figure 23-23. SSI Output Masking Function





23.9 Serial Interface Registers

23.9.1 Serial Interface Control Register 1 (SIC1)

Bit 3	Bit 2	Bit 1	Bit 0			
SIR	SCD	SCS1	SCS0	Reset value: 1111b		
SIR	S erial I SIR = 1 SIR = 0	nterface R e , SSI inacti), SSI active	eset ve e			
SCD	Serial Clock Direction SCD = 1, SC line used as output SCD = 0, SC line used as input					
Note:	This bit has t	to be set to	"1" during	the MCL mode and the Timer 3 mode 10 or 11		
SCS1 SCS0	Serial C Serial C	Clock source Clock source	e S elect bit e S elect bit	1 0		
Note:	With SCD =	0 the bits S	CS1 and S	CS0 are insignificant		
			. .			

Auxiliary register address: "9"hex

Table 23-4. Serial Clock Source Select Bits

SCS1	SCS0	Internal Clock for SSI
1	1	SYSCL/2
1	0	T1OUT/2
0	1	POUT/2
0	0	TOG2/2

• In transmit mode (SDD = 1) shifting starts only if the transmit buffer has been loaded (SRDY = 1).

• Setting SIR-bit loads the contents of the shift register into the receive buffer (synchronous 8-bit mode only).

• In MCL modes, writing a 0 to SIR generates a start condition and writing a 1 generates a stop condition.

23.9.2 Serial Interface Control Register 2 (SIC2)

Auxiliary register address: "A"hex

	Bit 0	Bit 1	Bit 2	Bit 3
Reset value: 1111	SDD	SM0	SM1	MSM

Modular Stop Mode

	MSM = 1, modulator stop mode disabled (output masking off)
MSM	MSM = 0, modulator stop mode enabled (output masking on) - used in modulation modes for generating bit streams which are not sub-multiples of 8 bits.
SM1	Serial Mode control bit 1
SM0	Serial Mode control bit 0

Table 23-5.	Serial Mode Control Bits

Mode	SM1	SM0	SSI Mode
1	1	1	8-bit NRZ-Data changes with the rising edge of SC
2	1	0	8-bit NRZ-Data changes with the falling edge of SC
3	0	1	9-bit two-wire MCL compatible
4	0	0	8-bit two-wire pseudo MCL compatible (no acknowledge)

Serial Data Direction

	SDD = 1, transmit mode – SD line used as output (transmit data). SRDY is set
SDD	by a transmit buffer write access.
	SDD = 0, receive mode – SD line used as input (receive data). SRDY is set
	by a receive buffer read access

Note: SDD controls port directional control and defines the reset function for the SRDY-flag





23.9.3 Serial Interface Status and Control Register (SISC)

Primary register address: "A"hex

	Bit 3	Bit 2	Bit 1	Bit 0	
Write	MCL	RACK	SIM	IFN	Reset value: 1111b
Read		TACK	ACT	SRDY	Reset value: xxxxb
					-
MCL	Multi-Chip L MCL = 1,mu tra MCL = 0, co	ink activation Ilti-chip link di nsactions to nnects SC ar	sabled. Th / from the i nd SD addit	is bit has t n ternal EEI ionally to th	o be set to "0" during PROM ne internal multi-chip link pads
RACK	R eceive AC RACK = 0, 1 RACK = 1, 1	K nowledge st ransmit ackno ransmit no ac	atus/contro owledge in knowledge	bl bit for MC next receive in last rece	CL mode e telegram sive telegram
TACK	Transmit AC TACK = 0, a TACK = 1, r	Knowledge s cknowledge r o acknowledg	tatus/contro eceived in je received	ol bit for MC last transmi in last tran	CL mode it telegram smit telegram
SIM	S erial Interr SIM = 1, dis SIM = 0, en	upt M ask able interrupt able serial inte	s errupt. An i	nterrupt is g	generated.
IFN	Interrupt Fu IFN = 1, the IFN = 0, the be	N ction serial interru serial interru comes empty,	ot is genera ot is genera 'full in trans	ated at the e ated when t smit/receive	end of telegram he SRDY goes low (i.e., buffer • mode)
SRDY	S erial interfa SRDY = 1, SRDY = 0,	ace buffer R ea in receive m in transmit r in receive m in transmit r	a DY status node: receiv node: trans node: receiv node: trans	flag /e buffer en mit buffer fu /e buffer ful smit buffer e	npty JII I empty
ACT	Transmissio ACT = 1, tra ar ACT = 0, tra	n ACT ive stat insmission is e currently in insmission is	us flag active, i.e., progress. inactive	serial data	transfer. Stop or start conditions

23.9.4 Serial Transmit Buffer (STB) – Byte Write

Primary register address: "9"hex

First write cycle	Bit 3	Bit 2	Bit 1	Bit 0	Reset value: xxxxb
Second write cycle	Bit 7	Bit 6	Bit 5	Bit 4	Reset value: xxxxb

The STB is the transmit buffer of the SSI. The SSI transfers the transmit buffer into the shift register and starts shifting with the most significant bit.

Primary register address: "9"hex

23.9.5 Serial Receive Buffer (SRB) – Byte Read

First read cycle	Bit 7	Bit 6	Bit 5	Bit 4	Reset value: xxxxb
Second read cycle	Bit 3	Bit 2	Bit 1	Bit 0	Reset value: xxxxb

The SRB is the receive buffer of the SSI. The shift register clocks serial data in (most significant bit first) and loads content into the receive buffer when complete telegram has been received.

24. Combination Modes

The UTCM consists of two timers (Timer 2 and Timer 3) and a serial interface. There is a multitude of modes in which the timers and serial interface can work together.

The 8-bit wide serial interface operates as shift register for modulation and demodulation. The modulator and demodulator units work together with the timers and shift the data bits into or out of the shift register.

24.1 Combination Mode Timer 2 and SSI

Figure 24-1. Combination Timer 2 and SSI







24.1.1 Combination Mode 1: Burst Modulation

SSI mode 1:	8-bit NRZ and internal data SO output to the Timer 2 modulator stage			
Timer 2 mode 1, 2, 3 or 4:	8-bit compare counter with 4-bit programmable prescaler and DCG			
Timer 2 output mode 3:	Duty cycle burst generator			
Figure 24-2. Carrier Freque	ncy Burst Modulation with the SSI Internal Data Output			



24.1.2 Combination Mode 2: Biphase Modulation 1

SSI mode 1:	8-bit shift register internal data output (SO) to the Timer 2 modulator stage
Timer 2 mode 1, 2, 3 or 4:	8-bit compare counter with 4-bit programmable prescaler
Timer 2 output mode 4:	The modulator 2 of Timer 2 modulates the SSI internal data output to Biphase code

Figure 24-3. Biphase Modulation 1



ATAM862-8

24.1.3 Combination Mode 3: Manchester Modulation 1

SSI mode 1:	8-bit shift register internal data output (SO) to the Timer 2 modulator stage
Timer 2 mode 1, 2, 3 or 4:	8-bit compare counter with 4-bit programmable prescaler
Timer 2 output mode 5:	The modulator 2 of Timer 2 modulates the SSI internal data output to Manchester code

Figure 24-4. Manchester Modulation 1



24.1.4 Combination Mode 4: Manchester Modulation 2

SSI mode 1:	8-bit shift register internal data output (SO) to the Timer 2 modulator stage
Timer 2 mode 3:	8-bit compare counter and 4-bit prescaler
Timer 2 output mode 5:	The modulator 2 of Timer 2 modulates the SSI data output to Manchester code

The 4-bit stage can be used as prescaler for the SSI to generate the stop signal for modulator 2. The SSI has a special mode to supply the prescaler with the shift clock. The control output signal (OMSK) of the SSI is used as stop signal for the modulator. Figure 24-5 shows an example for a 12-bit Manchester telegram.



Figure 24-5. Manchester Modulation 2





24.1.5 Combination Mode 5: Biphase Modulation 2

SSI mode 1:	8-bit shift register internal data output (SO) to the Timer 2 modulator stage
Timer 2 mode 3:	8-bit compare counter and 4-bit prescaler
Timer 2 output mode 4:	The modulator 2 of Timer 2 modulates the SSI data output to Biphase code

The 4-bit stage can be used as prescaler for the SSI to generate the stop signal for modulator 2. The SSI has a special mode to supply the prescaler via the shift clock. The control output signal (OMSK) of the SSI is used as stop signal for the modulator. Figure 24-6 shows an example for a 13-bit Biphase telegram.





24.2 Combination Mode Timer 3 and SSI









24.2.1 Combination Mode 6: FSK Modulation

SSI mode 1: 8-bit shift register internal data output (SO) to the Timer 3

Timer 3 mode 8: FSK modulation with shift register data (SO)

The two compare registers are used to generate two varied time intervals. The SSI data output selects which compare register is used for the output frequency generation. A "0" level at the SSI data output enables the compare register 1 and a "1" level enables the compare register 2. The compare and compare mode registers must be programmed to generate the two frequencies via the output toggle flip-lop. The SSI can be supplied with the toggle signal of Timer 2 or any other clock source. The Timer 3 counter is driven by an internal or external clock source.



Figure 24-8. FSK Modulation

24.2.2 Combination Mode 7: Pulse-width Modulation (PWM)

SSI mode 1: 8-bit shift register internal data output (SO) to the Timer 3

Timer 3 mode 9: Pulse-width modulation with the shift register data (SO)

The two compare registers are used to generate two varied time intervals. The SSI data output selects which compare register is used for the output pulse generation. In this mode, both compare and compare mode registers must be programmed to generate the two pulse width. It is also useful to enable the single-action mode for extreme duty cycles. Timer 2 is used as baudrate generator and for the triggered restart of Timer 3. The SSI must be supplied with the toggle signal of Timer 2. The counter is driven by an internal or external clock source.

Figure 24-9. Pulse-width Modulation



ATAM862-8

24.2.3 Combination Mode 8: Manchester Demodulation/Pulse-width Demodulation

SSI mode 1: 8-bit shift register internal data input (SI) and the internal shift clock (SCI) from the Timer 3

Timer 3 mode 10: Manchester demodulation/pulse-width demodulation with Timer 3

For Manchester demodulation, the edge detection stage must be programmed to detect each edge at the input. These edges are evaluated by the demodulator stage. The timer stage is used to generate the shift clock for the SSI. A compare register 1 match event defines the correct moment for shifting the state from the input T3I as the decoded bit into shift register. After that, the demodulator waits for the next edge to synchronize the timer by a reset for the next bit. The compare register 2 can be used to detect a time error and handle it with an interrupt routine.

Before activating the demodulator mode the timer and the demodulator stage must be synchronized with the bitstream. The Manchester code timing consists of parts with the half bitlength and the complete bitlength. A synchronization routine must start the demodulator after an interval with the complete bitlength.

The counter can be driven by any internal clock source. The output T3O can be used by Timer 2 in this mode. The Manchester decoder can also be used for pulse-width demodulation. The input must programmed to detect the positive edge. The demodulator and timer must be synchronized with the leading edge of the pulse. After that a counter match with the compare register 1 shifts the state at the input T3I into the shift register. The next positive edge at the input restarts the timer.



Figure 24-10. Manchester Demodulation





24.2.4 Combination Mode 9: Biphase Demodulation

SSI mode 1:

8-bit shift register internal data input (SI) and the internal shift clock (SCI) from the Timer 3

Timer 3 mode 11: Biphase demodulation with Timer 3

In the Biphase demodulation mode the timer works like in the Manchester demodulation mode. The difference is that the bits are decoded with the toggle flip-flop. This flip-flop samples the edge in the middle of the bitframe and the compare register 1 match event shifts the toggle flip-flop output into shift register. Before activating the demodulation the timer and the demodulation stage must be synchronized with the bitstream. The Biphase code timing consists of parts with the half bitlength and the complete bitlength. The synchronization routine must start the demodulator after an interval with the complete bitlength.

The counter can be driven by any internal clock source and the output T3O can be used by Timer 2 in this mode.



Figure 24-11. Biphase Demodulation

24.3 Combination Mode Timer 2 and Timer 3



Figure 24-12. Combination Timer 3 and Timer 2

24.3.1 Combination Mode 10: Frequency Measurement or Event Counter with Time Gate

Timer 2 mode 1/2:	12-bit compare counter/8-bit compare counter and 4-bit prescaler
Timer 2 output mode 1/6:	Timer 2 compare match toggles (TOG2) to the Timer 3
Timer 3 mode 3:	Timer/Counter; internal trigger restart and internal capture (with Timer 2 TOG2-signal)

The counter is driven by an external (T3I) clock source. The output signal (TOG2) of Timer 2 resets the counter. The counter value before reset is saved in the capture register. If single-action mode is activated for one or both compare registers, the trigger signal restarts also the single actions. This mode can be used for frequency measurements or as event counter with time gate.





Figure 24-13. Frequency Measurement



Figure 24-14. Event Counter with Time Gate



24.3.2 Combination Mode 11: Burst Modulation 1

Timer 2 mode 1/2:	12-bit compare counter/8-bit compare counter and 4-bit prescaler
Timer 2 output mode 1/6:	Timer 2 compare match toggles the output flip-flop (M2) to the Timer 3
Timer 3 mode 6:	Carrier frequency burst modulation controlled by Timer 2 output (M2)

The Timer 3 counter is driven by an internal or external clock source. Its compare and compare mode registers must be programmed to generate the carrier frequency with the output toggle flip-flop. The output toggle flip-flop (M2) of Timer 2 is used to enable and disable the Timer 3 output. The Timer 2 can be driven by the toggle output signal of Timer 3 (TOG3) or any other clock source.

Figure 24-15. Burst Modulation 1



24.4 Combination Mode Timer 2, Timer 3 and SSI

Figure 24-16. Combination Timer 2, Timer 3 and SSI







24.4.1 Combination Mode 12: Burst Modulation 2

SSI mode 1:	8-bit shift register internal data output (SO) to the Timer 3
Timer 2 output mode 2:	8-bit compare counter and 4-bit prescaler
Timer 2 output mode 1/6:	Timer 2 compare match toggles (TOG2) to the SSI
Timer 3 mode 7:	Carrier frequency burst modulation controlled by the internal output (SO) of SSI

The Timer 3 counter is driven by an internal or external clock source. Its compare- and compare mode registers must be programmed to generate the carrier frequency with the output toggle flip-flop (M3). The internal data output (SO) of the SSI is used to enable and disable the Timer 3 output. The SSI can be supplied with the toggle signal of Timer 2.

Figure 24-17. Burst Modulation 2

	ากกกกกก			ותתתתתח					ההההההה	ההההההה	הההההההה	INNNNNN
Counter 3	2,34,5,01,0,12 11 H H	3,45,0,10,1,2	3450101 1 H H I I	50 <u>1</u> 01				50101 HHH	50101 11 H H 11			50,1,0,1
СМ31												
СМ32				[[[
тодз												
мз 🔟												
Counter 2/2 📥	0	1	²	3	1			3	0	1	²	3
тод2												
SO												
тзо												

24.4.2 Combination Mode 13: FSK Modulation

SSI mode 1:	8-bit shift register internal data output (SO) to the Timer 3
Timer 2 output mode 3:	8-bit compare counter and 4-bit prescaler
Timer 2 output mode 1/6:	Timer 2 4-bit compare match signal (POUT) to the SSI
Timer 3 mode 8:	FSK modulation with shift register data output (SO)
Timer 2 output mode 1/6: Timer 3 mode 8:	Timer 2 4-bit compare match signal (POUT) to the SSI FSK modulation with shift register data output (SO)

The two compare registers are used to generate two different time intervals. The SSI data output selects which compare register is used for the output frequency generation. A "0" level at the SSI data output enables the compare register 1 and a "1" level enables the compare register 2. The compare- and compare mode registers must be programmed to generate the two frequencies via the output toggle flip-flop. The SSI can be supplied with the toggle signal of Timer 2 or any other clock source. The Timer 3 counter is driven by an internal or external clock source.

Figure 24-18. FSK Modulation



24.5 Data EEPROM

The internal data EEPROM offers 2 pages of 512 bits each. Both pages are organized as 32×16 -bit words. The programming voltage as well as the write cycle timing is generated on chip. To be compatible with the ROM parts, two restrictions have to be taken into account:

- To use the same EEPROM page as with the ROM parts the application software has to write the MCL-command "09h" to the EEPROM. This command has no effect for the microcontroller if it is left inside the HEX-file for the ROM version.
- Data handling for read and write is performed using the serial interface MCL.

The page select is performed by either writing "01h" (page 1) or "09h" (page 0) to the EEPROM.



Figure 24-19. Data EEPROM





24.6 Serial Interface

The EEPROM uses an two-wire serial (TWI) interface to the microcontroller for read and write accesses to the data. It is considered to be a slave in all these applications. That means, the controller has to be the master that initiates the data transfer and provides the clock for transmit and receive operations.

The serial interface is controlled by the microcontroller which generates the serial clock and controls the access via the SCL line and SDA line. SCL is used to clock the data into and out of the device. SDA is a bi-directional line that is used to transfer data into and out of the device. The following protocol is used for the data transfers.

24.6.1 Serial Protocol

- Data states on the SDA line changing only while SCL is low.
- Changes on the SDA line while SCL is high are interpreted as START or STOP condition.
- A START condition is defined as high to low transition on the SDA line while the SCL line is high.
- A STOP condition is defined as low to high transition on the SDA line while the SCL line is high.
- Each data transfer must be initialized with a START condition and terminated with a STOP condition. The START condition wakes the device from standby mode and the STOP condition returns the device to standby mode.
- A receiving device generates an acknowledge (A) after the reception of each byte. This requires an additional clock pulse, generated by the master. If the reception was successful the receiving master or slave device pulls down the SDA line during that clock cycle. If an acknowledge is not detected (N) by the interface in transmit mode, it will terminate further data transmissions and go into receive mode. A master device must finish its read operation by a non-acknowledge and then send a stop condition to bring the device into a known state.

Figure 24-20. MCL Protocol



- Before the START condition and after the STOP condition the device is in standby mode and the SDA line is switched as input with pull-up resistor.
- The control byte that follows the START condition determines the following operation. It consists of the 5-bit row address, 2 mode control bits and the READ/NWRITE bit that is used to control the direction of the following transfer. A "0" defines a write access and a "1" a read access.

24.6.2 Control Byte Format

	EEPROM Address						e Control Bits	Read/ NWrite		
Start	A4	A3	A2	A1	A0	C1	C0	R/	NW	Ackn
									·	
Start	Control	byte	Ackn	Data b	yte	Ackn	Data by	te	Ackn	Stop

24.7 EEPROM

The EEPROM has a size of 2×512 bits and is organized as 32×16 -bit matrix each. To read and write data to and from the EEPROM the serial interface must be used. The interface supports one and two byte write accesses and one to n-byte read accesses to the EEPROM.

24.7.1 EEPROM – Operating Modes

The operating modes of the EEPROM are defined via the control byte. The control byte contains the row address, the mode control bits and the read/not-write bit that is used to control the direction of the following transfer. A "0" defines a write access and a "1" a read access. The five address bits select one of the 32 rows of the EEPROM memory to be accessed. For all accesses the complete 16-bit word of the selected row is loaded into a buffer. The buffer must be read or overwritten via the serial interface. The two mode control bits C1 and C2 define in which order the accesses to the buffer are performed: High byte – low byte or low byte – high byte. The EEPROM also supports autoincrement and autodecrement read operations. After sending the start address with the corresponding mode, consecutive memory cells can be read row by row without transmission of the row addresses.

Two special control bytes enable the complete initialization of EEPROM with "0" or with "1".

24.7.2 Write Operations

The EEPROM permits 8-bit and 16-bit write operations. A write access starts with the START condition followed by a write control byte and one or two data bytes from the master. It is completed via the STOP condition from the master after the acknowledge cycle.

The programming cycle consists of an erase cycle (write "zeros") and the write cycle (write "ones"). Both cycles together take about 10 ms.

24.7.3 Acknowledge Polling

If the EEPROM is busy with an internal write cycle, all inputs are disabled and the EEPROM will not acknowledge until the write cycle is finished. This can be used to detect the end of the write cycle. The master must perform acknowledge polling by sending a start condition followed by the control byte. If the device is still busy with the write cycle, it will not return an acknowledge and the master has to generate a stop condition or perform further acknowledge polling sequences. If the cycle is complete, it returns an acknowledge and the master can proceed with the next read or write cycle.





24.7.4 Write One Data Byte

Start	Control byte	А	Data byte 1	А	Stop
-------	--------------	---	-------------	---	------

24.7.5 Write Two Data Bytes

Start Control byte A Data byte 1 A Data byte 2 A Stop

24.7.6 Write Control Byte Only

Start	Control byte	А	Stop
-------	--------------	---	------

24.7.7 Write Control Bytes

	M	SB						LSB
Write low byte first	A4	A3	A2	A1	A0	C1	C0	R/NW
	Row address					0	1	0
Byte order	LB(R) HB(R)							
	M	SB						LSB
Write high byte first	A4	A3	A2	A1	A0	C1	C0	R/NW
	Row address					1	0	0
Byte order	HB(R) LB(R)							

A -> acknowledge; HB: high byte; LB: low byte; R: row address

24.7.8 Read Operations

The EEPROM allows byte-, word- and current address read operations. The read operations are initiated in the same way as write operations. Every read access is initiated by sending the START condition followed by the control byte which contains the address and the read mode. When the device has received a read command, it returns an acknowledge, loads the addressed word into the read/write buffer and sends the selected data byte to the master. The master has to acknowledge the received byte if it wants to proceed the read operation. If two bytes are read out from the buffer the device increments respectively decrements the word address automatically and loads the buffer with the next word. The read mode bits determines if the low or high byte is read first from the buffer and if the word address is incremented or decremented for the next read access. If the memory address limit is reached, the data word address will roll over and the sequential read will continue. The master can terminate the read operation after every byte by not responding with an acknowledge (N) and by issuing a stop condition.

24.7.9 Read One Data Byte

Start Control byte A Data byte 1 N Stop

24.7.10 Read Two Data Bytes

Start Control byte A Data byte 1 A Data byte 2 N Stop

24.7.11 Read n Data Bytes

Start	Control byte	А	Data byte 1	А	Data byte 2	Α		Data byte n	Ν	Stop
-------	--------------	---	-------------	---	-------------	---	--	-------------	---	------

24.7.12 Read Control Bytes

			М	SB							LSB
Read low byte address incre	first, ment		A4	A3	A2	A1	A0	C	1	C0	R/NW
				Rov	w addre	ess		0		1	1
		-									
Byte order	LB(R)	HB(F	R) L	B(R+1)	HB(I	R+1)			LB(R+n)	HB(R+n)
			М	SB							LSB
Read high byt address decre	e first, ement		A4	A3	A2	A1	A0	C	1	C0	R/NW
				Rov	w addre	ess		1		0	1
Byte order	HB(R)	LB(R	R) F	IB(R-1)	LB(R-1)			HB((R-n)	LB(R-n)

A -> acknowledge, N -> no acknowledge; HB: high byte; LB: low byte, R: row address

24.8 Initialization the Serial Interface to the EEPROM

To prevent unexpected behavior of he EEPROM and its interface it is good practice to use an initialization sequence after any reset of the circuit. This is performed by writing:

Start "FFh" A Stop

to the serial interface. If the EEPROM acknowledges this sequence it is in a defined state. Maybe it is necessary to perform this sequence twice.





25. Absolute Maximum Ratings: Microcontroller Part

Stresses beyond those listed under "Absolute Maximum Ratings" may cause permanent damage to the device. This is a stress rating only and functional operation of the device at these or any other conditions beyond those indicated in the operational sections of this specification is not implied. Exposure to absolute maximum rating conditions for extended periods may affect device reliability.

All inputs and outputs are protected against high electrostatic voltages or electric fields. However, precautions to minimize the build-up of electrostatic charges during handling are recommended. Reliability of operation is enhanced if unused inputs are connected to an appropriate logic voltage level (e.g., V_{DD}).

Voltages are given relative to V_{SS}

Parameters	Symbol	Value	Unit
Supply voltage	V _{DD}	-0.3 to + 6.5	V
Input voltage (on any pin)	V _{IN}	V_{SS} -0.3 $\leq V_{IN} \leq V_{DD}$ +0.3	V
Output short circuit duration	t _{short}	Indefinite	S
Operating temperature range	T _{amb}	-40 to +125	°C
Storage temperature range	T _{stg}	-40 to +150	°C
Soldering temperature (t ≤10 s)	T _{sld}	260	°C

26. Thermal Resistance

Parameter	Symbol	Value	Unit
Thermal resistance	R _{thJA}	135	K/W

27. DC Operating Characteristics

 $V_{SS} = 0 \text{ V}, \text{ T}_{amb} = -40^{\circ} \text{ C} \text{ to } +125^{\circ} \text{ C} \text{ unless otherwise specified.}$

Parameters	Test Conditions	Symbol	Min.	Тур.	Max.	Unit
Power Supply						
Operating voltage at V_{DD}		V _{DD}	V _{POR}		4.0	V
Active current CPU active	f _{SYSCL} = 1 MHz V _{DD} = 1.8 V V _{DD} = 3.0 V	I _{DD}		0.3 0.4	0.4	mA mA
Power down current (CPU sleep, RC oscillator active, 4-MHz quartz oscillator active)	$f_{SYSCL} = 1 \text{ MHz}$ $V_{DD} = 1.8 \text{ V}$ $V_{DD} = 3.0 \text{ V}$	I _{PD}		40 70	150	μA μA
Sleep current (CPU sleep, 32-kHz quartz oscillator active 4-MHz quartz oscillator inactive)	$V_{DD} = 1.8 V$ $V_{DD} = 3.0 V$ $V_{DD} = 3.0 V \text{ at } 85^{\circ} \text{ C}$	I _{Sleep}		0.4 0.6	4.3 1.5	μΑ μΑ μΑ
Sleep current (CPU sleep, 32-kHz quartz oscillator inactive 4-MHz quartz oscillator inactive)	$V_{DD} = 3.0 V$ $V_{DD} = 3.0 V \text{ at } 85^{\circ} \text{ C}$	I _{Sleep}		0.3	3.5 1.0	μΑ μΑ
Pin capacitance	Any pin to V _{SS}	CL		7	10	pF

27. DC Operating Characteristics (Continued)

 $V_{SS} = 0 \text{ V}, \text{ T}_{amb} = -40^{\circ} \text{ C}$ to $+125^{\circ} \text{ C}$ unless otherwise specified.

Parameters	Test Conditions	Symbol	Min.	Тур.	Max.	Unit
Power-on Reset Threshold Voltage	•					•
POR threshold voltage	BOT = 1	V _{POR}	1.54	1.7	1.88	V
POR threshold voltage	BOT = 0	V _{POR}	1.83	2.0	2.20	V
POR hysteresis		V _{POR}		50		mV
Voltage Monitor Threshold Voltage	•					
VM high threshold voltage	$V_{DD} > VM, VMS = 1$	V _{MThh}		3.0	3.35	V
VM high threshold voltage	$V_{DD} < VM, VMS = 0$	V _{MThh}	2.77	3.0		V
VM middle threshold voltage	$V_{DD} > VM, VMS = 1$	V _{MThm}		2.6	2.9	V
VM middle threshold voltage	$V_{DD} < VM, VMS = 0$	V _{MThm}	2.4	2.6		V
VM low threshold voltage	$V_{DD} > VM, VMS = 1$	V _{MThl}		2.2	2.44	V
VM low threshold voltage	$V_{DD} < VM, VMS = 0$	V _{MThl}	2.0	2.2		V
External Input Voltage						
VMI	V _{DD} = 3 V, VMS = 1	V _{VMI}		1.3	1.44	V
VMI	$V_{DD} = 3 V, VMS = 0$	V _{VMI}	1.18	1.3		V
All Bi-directional Ports						
Input voltage LOW	$V_{DD} = 2.0$ to 4.0 V	V _{IL}	V _{SS}		$0.2 imes V_{DD}$	V
Input voltage HIGH	V _{DD} = 2.0 to 4.0 V	V _{IH}	$0.8 imes V_{DD}$		V _{DD}	V
Input LOW current (switched pull-up)	$V_{DD} = 2.0 V,$ $V_{DD} = 3.0 V, V_{IL} = V_{SS}$	IL	-3 -10	-8 -20	-14 -40	μΑ μΑ
Input HIGH current (switched pull-down)	$V_{DD} = 2.0 \text{ V},$ $V_{DD} = 3.0 \text{ V}, \text{ V}_{IH} = \text{V}_{DD}$	I _{IH}	3 10	6 20	14 40	μΑ μΑ
Input LOW current (static pull-up)	$V_{DD} = 2.0 V$ $V_{DD} = 3.0 V$, $V_{IL} = V_{SS}$	IL	-30 -80	-50 -160	-98 -320	μΑ μΑ
Input LOW current (static pull-down)	$V_{DD} = 2.0 V$ $V_{DD} = 3.0 V$, $V_{IH} = V_{DD}$	l _{IH}	20 80	50 160	100 320	μΑ μΑ
Input leakage current	V _{IL} = V _{SS}	I _{IL}			100	nA
Input leakage current	$V_{IH} = V_{DD}$	I _{IH}			100	nA
Output LOW current		I _{OL}	0.9 3	1.8 5	3.6 8	mA mA
Output HIGH current	$V_{OH} = 0.8 \times V_{DD}$ $V_{DD} = 2.0 V$ $V_{DD} = 3.0 V$	I _{он}	-0.8 -3	-1.7 -5	-3.4 -8	mA mA

Note: The pin BP20/NTE has a static pull-up resistor during the reset-phase of the microcontroller





28. AC Characteristics

Supply voltage Vas -	18 to 40 V	$V_{aa} = 0 V T$	- 25° C unless	otherwise specified
Supply vollage v _{DD} -	1.0 10 4.0 V,	$v_{SS} = 0 v$, r_{an}	nb = 25 0 unless	outerwise specified.

Parameters	Test Conditions	Symbol	Min.	Тур.	Max.	Unit
Operation Cycle Time		L				
System alogy avala	$V_{DD} = 1.8 \text{ to } 4.0 \text{ V}$ $T_{amb} = -40 \text{ to } +125^{\circ} \text{ C}$	t _{SYSCL}	500		2000	ns
System clock cycle	$V_{DD} = 2.4 \text{ to } 4.0 \text{ V}$ $T_{amb} = -40 \text{ to } +125^{\circ} \text{ C}$	t _{SYSCL}	250		2000	ns
Timer 2 input Timing Pin T2I		i			L L	
Timer 2 input clock		f _{T2I}			5	MHz
Timer 2 input LOW time	Rise/fall time < 10 ns	t _{T2IL}	100			ns
Timer 2 input HIGH time	Rise/fall time < 10 ns	t _{T2IH}	100			ns
Timer 3 Input Timing Pin T3I		H			- II II	
Timer 3 input clock		f _{T3I}			SYSCL/2	MHz
Timer 3 input LOW time	Rise/fall time < 10 ns	t _{T3IL}	2 t _{SYSCL}			ns
Timer 3 input HIGH time	Rise/fall time < 10 ns	t _{T3IH}	2 t _{SYSCL}			ns
Interrupt Request Input Timing		i				
Interrupt request LOW time	Rise/fall time < 10 ns	t _{IRL}	100			ns
Interrupt request HIGH time	Rise/fall time < 10 ns	t _{IRH}	100			ns
External System Clock	1					
EXSCL at OSC1, ECM = EN	Rise/fall time < 10 ns	f _{EXSCL}	0.5		4	MHz
EXSCL at OSC1, ECM = DI	Rise/fall time < 10 ns	f _{EXSCL}	0.02		4	MHz
Input HIGH time	Rise/fall time < 10 ns	t _{IH}	0.1			μs
Reset Timing		L			-	
Power-on reset time	$V_{DD} > V_{POR}$	t _{POR}		1.5	5	ms
RC Oscillator 1	1	U				
Frequency		f _{RcOut1}		3.8		MHz
Stability	$V_{DD} = 2.0 \text{ to } 4.0 \text{ V}$ $T_{amb} = -40 \text{ to } +125^{\circ} \text{ C}$	Δf/f			±50	%
RC Oscillator 2 – External Resistor		i				
Frequency	R _{ext} = 180 kΩ	f _{RcOut2}		4		MHz
Stability	$V_{DD} = 2.0 \text{ to } 4.0 \text{ V}$ $T_{amb} = -40 \text{ to } +125^{\circ} \text{ C}$	Δf/f			±15	%
Stabilization time		t _S			10	μs
4-MHz Crystal Oscillator (Operating	Range V _{DD} = 2.2 V to 4.0 V)	U				
Frequency		f _X		4		MHz
Start-up time		t _{SQ}		5		ms
Stability		$\Delta f/f$	-10		10	ppm
Integrated input/output capacitances (configurable)	C _{IN} /C _{OUT} programmable	C _{IN} C _{OUT}	0, 2 0, 2	, 5, 7, 10 , 5, 7, 10	or 12 or 12	pF pF

28. AC Characteristics (Continued)

Supply voltage V_{DD} = 1.8 to 4.0 V, V_{SS} = 0 V, T_{amb} = 25° C unless otherwise specified.

Parameters	Test Conditions	Symbol	Min.	Тур.	Max.	Unit
32-kHz Crystal Oscillator (Operating	g Range V _{DD} = 2.0 V to 4.0 V)					
Frequency		f _X		32.768		kHz
Start-up time		t _{SQ}		0.5		s
Stability		$\Delta f/f$	-10		10	ppm
Integrated input/output capacitances (configurable)	C _{IN} /C _{OUT} programmable	C _{IN} C _{OUT}	0, 2 0, 2	, 5, 7, 10 o , 5, 7, 10 o	r 12 r 12	pF pF
External 32-kHz Crystal Parameters						
Crystal frequency		f _X		32.768		kHz
Serial resistance		RS		30	50	kΩ
Static capacitance		C 0		1.5		pF
Dynamic capacitance		C1		3		fF
External 4-MHz Crystal Parameters						
Crystal frequency		f _X		4.0		MHz
Serial resistance		RS		40	150	W
Static capacitance		C 0		1.4	3	pF
Dynamic capacitance		C1		3		fF
EEPROM						
Operating current during erase/write cycle		I _{WR}		600	1300	μA
Endurance	Erase-/write cycles $T_{amb} = 125^{\circ}C$	E _D E _D	500000 10000	1000000 20000		Cycles Cycles
Data erase/write cycle time	For 16-bit access	t _{DEW}		9	13	ms
Data retention time	$T_{amb} = 125^{\circ} C$	t _{DR} t _{DR}	100 1			Years Years
Power-up to read operation		t _{PUR}			0.2	ms
Power-up to write operation		t _{PUW}			0.2	ms
Program EEPROM	Erase-/write cycles, $T_{amb} = 0$ to 40° C	n _{EW}	100	1000		Cycles
Serial Interface	·					
SCL clock frequency		f _{SC_MCL}		100	500	kHz

29. Crystal Characteristics











30. Emulation

The basic function of emulation is to test and evaluate the customer's program and hardware in real time. This therefore enables the analysis of any timing, hardware or software problem. For emulation purposes, all MARC4 controllers include a special emulation mode. In this mode, the internal CPU core is inactive and the I/O buses are available via Port 0 and Port 1 to allow an external access to the on-chip peripherals. The MARC4 emulator uses this mode to control the peripherals of any MARC4 controller (target chip) and emulates the lost ports for the application.

The MARC4 emulator can stop and restart a program at specified points during execution, making it possible for the applications engineer to view the memory contents and those of various registers during program execution. The designer also gains the ability to analyze the executed instruction sequences and all the I/O activities.





31. Ordering Information

Extended Type Number ⁽¹⁾	Program Memory	Data-EEPROM	Package	Delivery
ATAM862x-TNQYzf	4 kB Flash	2×512 bit	SSO24	Taped and reeled
ATAM862x-TNSYzf	4 kB Flash	2×512 bit	SSO24	Tubes

Note: 1. x = Hardware revision

z

f

= Operating temperature range

J (-40° C to +125° C) + lead free

= RF frequency range

= 8 (868 MHz/915 MHz)

32. Package Information





Drawing-No.: 6.543-5056.02-4 Issue: 1; 07.06.01 Package: SSO24 Dimensions in mm

technical drawings according to DIN specifications





33. Revision History

Please note that the following page numbers referred to in this section refer to the specific revision mentioned, not to this document.

Revision No.	History
4590G-4BMCU-04/07	 Put datasheet in new template Features on page 1: Maximum output power value and the low current value are changed
4590F-4BMCU-12/05	 Put datasheet in new template Page 30: Section "32-kHz Oscillator" changed Page 105: Ordering Information changed
4590E-4BMCU-09/04	 Abs. Max. Ratings table (page 11): row "Input voltage" changed Abs. Max. Ratings table (page 11): table note 1 changed El. Char. table (page 12): row "PA_ENABLE input" changed El. Char. table (page 12): table note 1 changed

34. Table of Contents

1	Descr	iption	1
2	Pin Co	onfiguration	2
3	UHF A	SK/FSK Transmitter Block	
4	Featu	res	
5	Descr	iption	4
6	Gener	al Description	6
7	Funct	ional Description	6
	7.1	ASK Transmission	6
	7.2	FSK Transmission	6
	7.3	CLK Output	7
	7.4	Application Circuit	8
8	Absol	ute Maximum Ratings: RF Part	11
9	Therm	nal Resistance	
10	Electr	ical Characteristics	
11	Micro	controller Block	
12	Featu	res	
13	Descr	iption	
1Л	Introd		12
14	14.1	Differences between ATANOCO 9 and ATADOCO Microconstellers	
	14.1	Differences between ATAM862-6 and ATAM662 Microconnollers	14
15	MARC	A Architecture General Description	
16	Сотр	onents of Microcontroller Core	15
17	Progra	am Memory	
	17.1	RAM	16
	17.2	Registers	17
	17.3	ALU	19
	17.4	I/O Bus	19
	17.5	Instruction Set	19
	47.0	Interrupt Structure	20
	17.6		20





18 Master Reset 23 18.1 Power-on Reset and Brown-out Detection 23 19 Voltage Monitor 24 20 Clock Generation 26 20.1 Clock Module 26 20.2 Oscillator Circuits and External Clock Input Stage 27 20.3 Clock Management 30 21 Power-down Modes 31 22 Peripheral Modules 32 23.1 Bi-directional Ports 35 23.2 Bi-directional Port 1 35 23.3 Bi-directional Port 2 36 23.4 Bi-directional Port 5 38 23.4 Bi-directional Port 6 41 23.5 Bi-directional Port 6 41 23.6 Universal Timer/Counter/ Communication Module (UTCM) 42 23.7 Timer 1 43 23.8 Timer 2 47 23.9 Timer 2 Modes 50 23.11 Timer 2 Output Modes 50 23.11 Timer 2 Modes 58 24.1 Features 58 <th></th> <th>17.8</th> <th>Hardware Interrupts</th> <th>22</th>		17.8	Hardware Interrupts	22	
18.1 Power-on Reset and Brown-out Detection 23 19 Voltage Monitor 24 20 Clock Generation 26 20.1 Clock Module 26 20.2 Oscillator Circuits and External Clock Input Stage 27 20.3 Clock Management 30 21 Power-down Modes 31 22 Peripheral Modules 32 23.1 Bi-directional Ports 35 23.2 Bi-directional Port 1 35 23.3 Bi-directional Port 2 36 23.4 Bi-directional Port 5 38 23.4 Bi-directional Port 6 41 23.6 Bi-directional Port 6 41 23.6 Bi-directional Port 6 41 23.7 Timer 1 43 23.8 Timer 2 47 23.9 Timer 2 Output Modes 50 23.11 Timer 2 Output Modes 50 23.12 Timer 2 Nudes 58 24.1 Features 58 24.2 Timer 7 Soutput Signals 50	18	Master Reset			
19 Voltage Monitor 24 20 Clock Generation 26 20.1 Clock Module 26 20.2 Oscillator Circuits and External Clock Input Stage 27 20.3 Clock Management 30 21 Power-down Modes 31 22 Peripheral Modules 32 23.1 Bi-directional Ports 35 23.2 Bi-directional Ports 35 23.3 Bi-directional Port 1 35 23.4 Bi-directional Port 5 38 23.4 Bi-directional Port 6 41 23.6 Universal Timer/Counter/ Communication Module (UTCM) 42 23.7 Timer 1 43 23.8 Timer 2 47 23.9 Timer 2 Output Modes 50 23.11 Timer 2 Output Modes 50 23.12 Timer 3 Registers 53 24 Timer 3 Modulator for Carrier Frequency Burst Modulation 66 24.4 Timer 3 Capture Register 67 24.4 Timer 3 Capture Register 67 24.4 <		18.1	Power-on Reset and Brown-out Detection	23	
20 Clock Generation 26 20.1 Clock Module 26 20.2 Oscillator Circuits and External Clock Input Stage 27 20.3 Clock Management 30 21 Power-down Modes 31 22 Peripheral Modules 32 23.1 Bi-directional Ports 35 23.1 Bi-directional Port 1 35 23.2 Bi-directional Port 5 38 23.3 Bi-directional Port 4 40 23.5 Bi-directional Port 5 38 23.4 Bi-directional Port 6 41 23.6 Universal Timer/Counter/ Communication Module (UTCM) 42 23.7 Timer 1 43 23.8 Timer 2 47 23.9 Timer 2 Output Modes 50 23.11 Timer 2 Output Modes 50 23.12 Timer 3 Registers 53 24 Timer 7 58 24.1 Features 58 24.2 Timer 3 Modulator for Carrier Frequency Burst Modulation 66 24.3 Timer 3 Demodulator f	19	Voltage Monitor			
20.1 Clock Module 26 20.2 Oscillator Circuits and External Clock Input Stage 27 20.3 Clock Management 30 21 Power-down Modes 31 22 Peripheral Modules 32 23.1 Bi-directional Ports 35 23.1 Bi-directional Ports 35 23.2 Bi-directional Port 1 35 23.3 Bi-directional Port 2 36 23.3 Bi-directional Port 5 38 23.4 Bi-directional Port 5 38 23.4 Bi-directional Port 6 41 23.5 Bi-directional Port 6 41 23.6 Universal Timer/Counter/ Communication Module (UTCM) 42 23.7 Timer 1 43 23.8 Timer 2 47 23.9 Timer 2 47 23.9 Timer 1 50 23.11 Timer 2 50 23.12 Timer 2 50 23.12 Timer 3 50 23.12 Timer 3 50 23.12 Ti	20	Clock Generation			
20.2 Oscillator Circuits and External Clock Input Stage 27 20.3 Clock Management 30 21 Power-down Modes 31 22 Peripheral Modules 32 23.1 Bi-directional Ports 35 23.2 Bi-directional Ports 35 23.3 Bi-directional Port 1 35 23.3 Bi-directional Port 5 38 23.4 Bi-directional Port 5 38 23.3 Bi-directional Port 4 40 23.5 Bi-directional Port 5 38 23.4 Bi-directional Port 6 41 23.6 Universal Timer/Counter/ Communication Module (UTCM) 42 23.7 Timer 1 43 23.8 Timer 2 47 23.9 Timer 2 47 23.9 Timer 2 Output Modes 50 23.11 Timer 2 Output Modes 50 23.12 Timer 3 Registers 53 24 Timer 4 58 24.1 Features 58 24.2 Timer/Counter Modes 59	20	20.1	Clock Module	26	
20.3 Clock Management 30 21 Power-down Modes 31 22 Peripheral Modules 32 22.1 Addressing Peripherals 32 23 Bi-directional Ports 35 23.1 Bi-directional Port 1 35 23.2 Bi-directional Port 2 36 23.3 Bi-directional Port 1 35 23.4 Bi-directional Port 2 36 23.5 Bi-directional Port 4 40 23.5 Bi-directional Port 5 38 23.4 Bi-directional Port 6 41 23.5 Bi-directional Port 6 41 23.6 Universal Timer/Counter/ Communication Module (UTCM) 42 23.7 Timer 1 43 23.8 Timer 2 47 23.9 Timer 2 47 23.9 Timer 2 47 23.10 Timer 2 48 23.10 Timer 2 48 23.11 Timer 2 47 23.12 Timer 3 50 23.12 Timer 4 <td< th=""><th></th><th>20.2</th><th>Oscillator Circuits and External Clock Input Stage</th><th>27</th></td<>		20.2	Oscillator Circuits and External Clock Input Stage	27	
21 Power-down Modes 31 22 Peripheral Modules 32 22.1 Addressing Peripherals 32 23 Bi-directional Ports 35 23.1 Bi-directional Port 1 35 23.2 Bi-directional Port 1 35 23.3 Bi-directional Port 2 36 23.3 Bi-directional Port 5 38 23.4 Bi-directional Port 6 41 23.5 Bi-directional Port 6 41 23.6 Universal Timer/Counter/ Communication Module (UTCM) 42 23.7 Timer 1 43 23.8 Timer 2 47 23.9 Timer 2 Modes 48 23.10 Timer 2 Output Modes 50 23.11 Timer 2 Output Signals 50 23.12 Timer 3 58 24.1 Features 58 24.2 Timer/Counter Modes 59 24.3 Timer 3 Modulator/Demodulator Modes 59 24.4 Timer 3 Modulator for Carrier Frequency Burst Modulation 66 24.5 Timer 3 Demodulat		20.3	Clock Management	30	
22 Peripheral Modules 32 22.1 Addressing Peripherals 32 23 Bi-directional Ports 35 23.1 Bi-directional Port 1 35 23.2 Bi-directional Port 2 36 23.3 Bi-directional Port 5 38 23.4 Bi-directional Port 5 38 23.4 Bi-directional Port 6 40 23.5 Bi-directional Port 6 41 23.6 Universal Timer/Counter/ Communication Module (UTCM) 42 23.7 Timer 1 43 23.8 Timer 2 47 23.9 Timer 2 47 23.9 Timer 2 47 23.9 Timer 2 48 23.10 Timer 2 48 23.10 Timer 2 50 23.11 Timer 2 53 24 Timer 3 58 24.1 Features 58 24.2 Timer 3 59 24.3 Timer 3 59 24.3 Timer 3 58 24.4	21	Power	r-down Modes	31	
22.1 Addressing Peripherals 32 23 Bi-directional Ports 35 23.1 Bi-directional Port 1 35 23.2 Bi-directional Port 2 36 23.3 Bi-directional Port 5 38 23.4 Bi-directional Port 5 38 23.5 Bi-directional Port 6 40 23.5 Bi-directional Port 6 41 23.6 Universal Timer/Counter/ Communication Module (UTCM) 42 23.7 Timer 1 43 23.8 Timer 2 47 23.9 Timer 2 Modes 50 23.11 Timer 2 Output Modes 50 23.12 Timer 2 Nodes 50 23.12 Timer 2 Registers 53 24 Timer 3 58 24.1 Features 58 24.2 Timer 3 Modulator/Demodulator Modes 63 24.4 Timer 3 Modulator for Carrier Frequency Burst Modulation 66 24.5 Timer 3 Demodulator for Biphase, Manchester and Pulse-width-modulated Signals 66 24.6 Timer 3 Registers 67 <	22	Perinheral Modules 3			
23 Bi-directional Ports 35 23.1 Bi-directional Port 1 35 23.2 Bi-directional Port 2 36 23.3 Bi-directional Port 5 38 23.4 Bi-directional Port 5 38 23.5 Bi-directional Port 6 40 23.5 Bi-directional Port 6 41 23.6 Universal Timer/Counter/ Communication Module (UTCM) 42 23.7 Timer 1 43 23.8 Timer 2 47 23.9 Timer 2 47 23.9 Timer 2 Modes 50 23.11 Timer 2 Output Modes 50 23.12 Timer 2 Notes 53 24 Timer 3 58 24.1 Features 58 24.2 Timer 3 Modulator/Demodulator Modes 59 24.3 Timer 3 Modulator for Carrier Frequency Burst Modulation 66 24.4 Timer 3 Demodulator for Biphase, Manchester and Pulse-width-modulated Signals 66 24.6 Timer 3 Registers 67 24.7 Timer 3 Capture Register 71	22	22 1	Addressing Peripherals	32	
23 Bi-directional Ports 35 23.1 Bi-directional Port 1 35 23.2 Bi-directional Port 2 36 23.3 Bi-directional Port 5 38 23.4 Bi-directional Port 5 38 23.5 Bi-directional Port 6 40 23.5 Bi-directional Port 6 41 23.6 Universal Timer/Counter/ Communication Module (UTCM) 42 23.7 Timer 1 43 23.8 Timer 2 47 23.9 Timer 2 47 23.9 Timer 2 Modes 48 23.10 Timer 2 Output Modes 50 23.11 Timer 2 Output Signals 50 23.12 Timer 2 Registers 53 24 Timer 3 58 24.1 Features 58 24.2 Timer/Counter Modes 59 24.3 Timer 3 Modulator/Demodulator Modes 63 24.4 Timer 3 Modulator for Carrier Frequency Burst Modulation 66 24.5 Timer 3 Demodulator for Biphase, Manchester and Pulse-width-modulated Signals 66	1 2	Di dir	national Porta	25	
23.1 Bi-directional Port 1 35 23.2 Bi-directional Port 2 36 23.3 Bi-directional Port 5 38 23.4 Bi-directional Port 4 40 23.5 Bi-directional Port 6 41 23.6 Universal Timer/Counter/ Communication Module (UTCM) 42 23.7 Timer 1 43 23.8 Timer 2 47 23.9 Timer 2 Modes 48 23.10 Timer 2 Output Modes 50 23.11 Timer 2 Output Signals 50 23.12 Timer 2 Registers 53 24 Timer 3 58 24.1 Features 58 24.2 Timer 3 Modulator/Demodulator Modes 59 24.3 Timer 3 Modulator/Demodulator Modes 59 24.4 Timer 3 Demodulator for Carrier Frequency Burst Modulation 66 24.5 Timer 3 Demodulator for Biphase, Manchester and Pulse-width-modulated Signals 66 24.6 Timer 3 Registers 67 24.7 Timer 3 Capture Register 71 24.8 Synchronous Serial Interface (23			35	
23.2 Differentional Port 2 38 23.3 Bi-directional Port 5 38 23.4 Bi-directional Port 4 40 23.5 Bi-directional Port 6 41 23.6 Universal Timer/Counter/ Communication Module (UTCM) 42 23.7 Timer 1 43 23.8 Timer 2 47 23.9 Timer 2 47 23.9 Timer 2 Output Modes 50 23.10 Timer 2 Output Modes 50 23.11 Timer 2 Output Signals 50 23.12 Timer 2 Registers 53 24 Timer 3 58 24.1 Features 58 24.2 Timer 3 Modulator/Demodulator Modes 59 24.3 Timer 3 Modulator/Demodulator Modes 63 24.4 Timer 3 Modulator for Carrier Frequency Burst Modulation 66 24.5 Timer 3 Demodulator for Biphase, Manchester and Pulse-width-modulated Signals 66 24.6 Timer 3 Registers 67 24.7 Timer 3 Capture Register 71 24.8 Synchronous Serial Interface (SSI)		23.1 23.2	Bi-directional Port 1	26	
23.4 Bi-directional Port 4 40 23.5 Bi-directional Port 6 41 23.6 Universal Timer/Counter/ Communication Module (UTCM) 42 23.7 Timer 1 43 23.8 Timer 2 47 23.9 Timer 2 Modes 48 23.10 Timer 2 Output Modes 50 23.11 Timer 2 Output Signals 50 23.12 Timer 2 Registers 53 24 Timer 3 58 24.1 Features 58 24.2 Timer 3 Modulator/Demodulator Modes 59 24.3 Timer 3 Modulator/Demodulator Modes 63 24.4 Timer 3 Modulator for Carrier Frequency Burst Modulation 66 24.5 Timer 3 Demodulator for Biphase, Manchester and Pulse-width-modulated Signals 66 24.6 Timer 3 Registers 67 24.7 Timer 3 Capture Register 71 24.8 Synchronous Serial Interface (SSI) 72		23.2	Bi-directional Port 5	38	
23.5 Bi-directional Port 6 41 23.6 Universal Timer/Counter/ Communication Module (UTCM) 42 23.7 Timer 1 43 23.8 Timer 2 47 23.9 Timer 2 Modes 48 23.10 Timer 2 Output Modes 50 23.11 Timer 2 Output Signals 50 23.12 Timer 2 Registers 53 24 Timer 3 58 24.1 Features 58 24.2 Timer 3 Modulator/Demodulator Modes 59 24.3 Timer 3 Modulator for Carrier Frequency Burst Modulation 66 24.4 Timer 3 Demodulator for Biphase, Manchester and Pulse-width-modulated Signals 66 24.6 Timer 3 Registers 67 24.7 Timer 3 Capture Register 71 24.8 Synchronous Serial Interface (SSI) 72		23.4	Bi-directional Port 4	40	
23.6 Universal Timer/Counter/ Communication Module (UTCM) 42 23.7 Timer 1 43 23.8 Timer 2 47 23.9 Timer 2 Modes 48 23.10 Timer 2 Output Modes 50 23.11 Timer 2 Output Signals 50 23.12 Timer 2 Registers 53 24 Timer 3 58 24.1 Features 58 24.2 Timer/Counter Modes 59 24.3 Timer 3 Modulator/Demodulator Modes 63 24.4 Timer 3 Modulator for Carrier Frequency Burst Modulation 66 24.5 Timer 3 Demodulator for Biphase, Manchester and Pulse-width-modulated Signals 66 24.6 Timer 3 Registers 67 24.7 Timer 3 Capture Register 71 24.8 Synchronous Serial Interface (SSI) 72		23.5	Bi-directional Port 6	41	
23.7 Timer 1 43 23.8 Timer 2 47 23.9 Timer 2 Modes 48 23.10 Timer 2 Output Modes 50 23.11 Timer 2 Output Signals 50 23.12 Timer 2 Registers 53 24 Timer 3 58 24.1 Features 58 24.2 Timer/Counter Modes 59 24.3 Timer 3 Modulator/Demodulator Modes 63 24.4 Timer 3 Modulator for Carrier Frequency Burst Modulation 66 24.5 Timer 3 Demodulator for Biphase, Manchester and Pulse-width-modulated Signals 66 24.6 Timer 3 Registers 67 24.7 Timer 3 Capture Register 71 24.8 Synchronous Serial Interface (SSI) 72		23.6	Universal Timer/Counter/ Communication Module (UTCM)	42	
23.8 Timer 2 47 23.9 Timer 2 Modes 48 23.10 Timer 2 Output Modes 50 23.11 Timer 2 Output Signals 50 23.12 Timer 2 Registers 53 24 Timer 3 58 24.1 Features 58 24.2 Timer/Counter Modes 59 24.3 Timer 3 Modulator/Demodulator Modes 63 24.4 Timer 3 Modulator for Carrier Frequency Burst Modulation 66 24.5 Timer 3 Demodulator for Biphase, Manchester and Pulse-width-modulated Signals 66 24.6 Timer 3 Registers 67 24.7 Timer 3 Capture Register 71 24.8 Synchronous Serial Interface (SSI) 72		23.7	Timer 1	43	
23.9 Timer 2 Modes 48 23.10 Timer 2 Output Modes 50 23.11 Timer 2 Output Signals 50 23.12 Timer 2 Registers 53 24 Timer 3 58 24.1 Features 58 24.2 Timer/Counter Modes 59 24.3 Timer 3 Modulator/Demodulator Modes 63 24.4 Timer 3 Modulator for Carrier Frequency Burst Modulation 66 24.5 Timer 3 Demodulator for Biphase, Manchester and Pulse-width-modulated Signals 66 24.6 Timer 3 Registers 67 24.7 Timer 3 Capture Register 71 24.8 Synchronous Serial Interface (SSI) 72		23.8	Timer 2	47	
23.10 Timer 2 Output Modes 50 23.11 Timer 2 Output Signals 50 23.12 Timer 2 Registers 53 24 Timer 3 58 24.1 Features 58 24.2 Timer/Counter Modes 59 24.3 Timer 3 Modulator/Demodulator Modes 63 24.4 Timer 3 Modulator for Carrier Frequency Burst Modulation 66 24.5 Timer 3 Demodulator for Biphase, Manchester and Pulse-width-modulated Signals 66 24.6 Timer 3 Registers 67 24.7 Timer 3 Capture Register 71 24.8 Synchronous Serial Interface (SSI) 72		23.9	Timer 2 Modes	48	
23.11 Timer 2 Output Signals5023.12 Timer 2 Registers5324 Timer 35824.1 Features5824.2 Timer/Counter Modes5924.3 Timer 3 Modulator/Demodulator Modes6324.4 Timer 3 Modulator for Carrier Frequency Burst Modulation6624.5 Timer 3 Demodulator for Biphase, Manchester and Pulse-width-modulated Signals6624.6 Timer 3 Registers6724.7 Timer 3 Capture Register7124.8 Synchronous Serial Interface (SSI)72		23.10	Timer 2 Output Modes	50	
23.12 Timer 2 Registers5324 Timer 35824.1 Features5824.2 Timer/Counter Modes5924.3 Timer 3 Modulator/Demodulator Modes6324.4 Timer 3 Modulator for Carrier Frequency Burst Modulation6624.5 Timer 3 Demodulator for Biphase, Manchester and Pulse-width-modulated Signals6624.6 Timer 3 Registers6724.7 Timer 3 Capture Register7124.8 Synchronous Serial Interface (SSI)72		23.11	Timer 2 Output Signals	50	
24Timer 35824.1Features5824.2Timer/Counter Modes5924.3Timer 3 Modulator/Demodulator Modes6324.4Timer 3 Modulator for Carrier Frequency Burst Modulation6624.5Timer 3 Demodulator for Biphase, Manchester and Pulse-width-modulated Signals6624.6Timer 3 Registers6724.7Timer 3 Capture Register7124.8Synchronous Serial Interface (SSI)72		23.12	2 Timer 2 Registers	53	
24.1Features5824.2Timer/Counter Modes5924.3Timer 3 Modulator/Demodulator Modes6324.4Timer 3 Modulator for Carrier Frequency Burst Modulation6624.5Timer 3 Demodulator for Biphase, Manchester and Pulse-width-modulated Signals6624.6Timer 3 Registers6724.7Timer 3 Capture Register7124.8Synchronous Serial Interface (SSI)72	24	4 Timer 3		58	
24.2Timer/Counter Modes5924.3Timer 3 Modulator/Demodulator Modes6324.4Timer 3 Modulator for Carrier Frequency Burst Modulation6624.5Timer 3 Demodulator for Biphase, Manchester and Pulse-width-modulated Signals6624.6Timer 3 Registers6724.7Timer 3 Capture Register7124.8Synchronous Serial Interface (SSI)72		24.1	Features	58	
24.3Timer 3 Modulator/Demodulator Modes6324.4Timer 3 Modulator for Carrier Frequency Burst Modulation6624.5Timer 3 Demodulator for Biphase, Manchester and Pulse-width-modulated Signals6624.6Timer 3 Registers6724.7Timer 3 Capture Register7124.8Synchronous Serial Interface (SSI)72		24.2	Timer/Counter Modes	59	
 24.4 Timer 3 Modulator for Carrier Frequency Burst Modulation		24.3	Timer 3 Modulator/Demodulator Modes	63	
 24.5 Timer 3 Demodulator for Biphase, Manchester and Pulse-width-modulated Signals		24.4	Timer 3 Modulator for Carrier Frequency Burst Modulation	66	
24.6Timer 3 Registers		24.5	Timer 3 Demodulator for Biphase, Manchester and Pulse-width-modulated Signals	66	
24.7 Timer 3 Capture Register		24.6	Timer 3 Registers	67	
24.8 Synchronous Serial Interface (SSI)72		24.7	Timer 3 Capture Register	71	
		24.8	Synchronous Serial Interface (SSI)	72	
ATAM862-8

	24.9	Serial Interface Registers	80
25	Comb	ination Modes	83
	25.1	Combination Mode Timer 2 and SSI	
	25.2	Combination Mode Timer 3 and SSI	87
	25.3	Combination Mode Timer 2 and Timer 3	91
	25.4	Combination Mode Timer 2, Timer 3 and SSI	93
	25.5	Data EEPROM	95
	25.6	Serial Interface	96
	25.7	EEPROM	97
	25.8	Initialization the Serial Interface to the EEPROM	99
26	Absolute Maximum Ratings: Microcontroller Part		
27	Thern	nal Resistance	100
27 28	Thern DC Op	nal Resistance perating Characteristics	100 100
27 28 29	Therm DC O _l AC Cl	nal Resistance perating Characteristics haracteristics	100 100 102
27 28 29 30	Thern DC Op AC Ch Crysta	nal Resistance perating Characteristics haracteristics al Characteristics	100 100 102 103
27 28 29 30 31	Thern DC Op AC Ch Crysta Emula	nal Resistance perating Characteristics haracteristics al Characteristics	100 100 102 103 104
27 28 29 30 31 32	Therm DC Op AC Ch Crysta Emula Order	nal Resistance perating Characteristics haracteristics al Characteristics ation ing Information	100 100 102 103 104 105
27 28 29 30 31 32 33	Therm DC Op AC Ch Crysta Emula Order Packa	nal Resistance perating Characteristics haracteristics al Characteristics ation ing Information nge Information	100 100 102 103 104 105 105
27 28 29 30 31 32 33 33	Therm DC Op AC Ch Crysta Emula Order Packa Revis	nal Resistance perating Characteristics haracteristics al Characteristics ation ing Information nge Information ion History	100 100 102 103 104 105 106





Headquarters

Atmel Corporation 2325 Orchard Parkway San Jose, CA 95131 USA Tel: 1(408) 441-0311 Fax: 1(408) 487-2600

International

Atmel Asia Room 1219 Chinachem Golden Plaza 77 Mody Road Tsimshatsui East Kowloon Hong Kong Tel: (852) 2721-9778 Fax: (852) 2722-1369 Atmel Europe Le Krebs 8, Rue Jean-Pierre Timbaud BP 309 78054 Saint-Quentin-en-Yvelines Cedex France Tel: (33) 1-30-60-70-00 Fax: (33) 1-30-60-71-11

Atmel Japan

9F, Tonetsu Shinkawa Bldg. 1-24-8 Shinkawa Chuo-ku, Tokyo 104-0033 Japan Tel: (81) 3-3523-3551 Fax: (81) 3-3523-7581

Product Contact

Web Site www.atmel.com *Technical Support* marc4@atmel.com Sales Contact www.atmel.com/contacts

Literature Requests www.atmel.com/literature

Disclaimer: The information in this document is provided in connection with Atmel products. No license, express or implied, by estoppel or otherwise, to any intellectual property right is granted by this document or in connection with the sale of Atmel products. EXCEPT AS SET FORTH IN ATMEL'S TERMS AND CONDI-TIONS OF SALE LOCATED ON ATMEL'S WEB SITE, ATMEL ASSUMES NO LIABILITY WHATSOEVER AND DISCLAIMS ANY EXPRESS, IMPLIED OR STATUTORY WARRANTY RELATING TO ITS PRODUCTS INCLUDING, BUT NOT LIMITED TO, THE IMPLIED WARRANTY OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE, OR NON-INFRINGEMENT. IN NO EVENT SHALL ATMEL BE LIABLE FOR ANY DIRECT, INDIRECT, CONSEQUENTIAL, PUNTIVE, SPECIAL OR INCIDEN-TAL DAMAGES (INCLUDING, WITHOUT LIMITATION, DAMAGES FOR LOSS OF PROFITS, BUSINESS INTERRUPTION, OR LOSS OF INFORMATION) ARISING OUT OF THE USE OR INABILITY TO USE THIS DOCUMENT, EVEN IF ATMEL HAS BEEN ADVISED OF THE POSSIBILITY OF SUCH DAMAGES. Atmel makes no representations or warranties with respect to the accuracy or completeness of the contents of this document and reserves the right to make changes to specifications and product descriptions at any time without notice. Atmel does not make any commitment to update the information contained herein. Unless specifically provided otherwise, Atmel products are not suitable for, and shall not be used in, automotive applications. Atmel's products are not intended, or warranted for use as components in applications intended to support or sustain life.

© 2007 Atmel Corporation. All rights reserved. Atmel[®], logo and combinations thereof, and others are registered trademarks or trademarks of Atmel Corporation or its subsidiaries. Other terms and product names may be trademarks of others.



Мы молодая и активно развивающаяся компания в области поставок электронных компонентов. Мы поставляем электронные компоненты отечественного и импортного производства напрямую от производителей и с крупнейших складов мира.

Благодаря сотрудничеству с мировыми поставщиками мы осуществляем комплексные и плановые поставки широчайшего спектра электронных компонентов.

Собственная эффективная логистика и склад в обеспечивает надежную поставку продукции в точно указанные сроки по всей России.

Мы осуществляем техническую поддержку нашим клиентам и предпродажную проверку качества продукции. На все поставляемые продукты мы предоставляем гарантию.

Осуществляем поставки продукции под контролем ВП МО РФ на предприятия военно-промышленного комплекса России, а также работаем в рамках 275 ФЗ с открытием отдельных счетов в уполномоченном банке. Система менеджмента качества компании соответствует требованиям ГОСТ ISO 9001.

Минимальные сроки поставки, гибкие цены, неограниченный ассортимент и индивидуальный подход к клиентам являются основой для выстраивания долгосрочного и эффективного сотрудничества с предприятиями радиоэлектронной промышленности, предприятиями ВПК и научноисследовательскими институтами России.

С нами вы становитесь еще успешнее!

Наши контакты:

Телефон: +7 812 627 14 35

Электронная почта: sales@st-electron.ru

Адрес: 198099, Санкт-Петербург, Промышленная ул, дом № 19, литера Н, помещение 100-Н Офис 331