


# CUSTOMER DRAWING



REVISED PER  
ECO-12-013789

REV:  
**C**


DATE:  
July 26, 2012



**STRAIGHT ADAPTOR**  
**-00**



**45° ADAPTOR**  
**-45**



**90° ADAPTOR**  
**-90**

© 2012 Tyco Electronics Corporation. All rights reserved.

|                                                                                                             |                 |                                                                                                                                                                                                                                                                           |  |                                                                                                 |                |                  |
|-------------------------------------------------------------------------------------------------------------|-----------------|---------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|--|-------------------------------------------------------------------------------------------------|----------------|------------------|
|                          |                 | Raychem Wire and Harnessing Products<br>300 Constitution Drive<br>Menlo Park, CA 94025<br>USA                                                                                                                                                                             |  | TITLE:<br><br><b>HEXASHIELD ADAPTOR FOR<br/>CODE 40 CONNECTORS<br/>(BANDSTRAP CLAMPING NUT)</b> |                |                  |
| UNLESS OTHERWISE SPECIFIED<br>DIMENSIONS ARE IN<br>MILLIMETERS.<br>INCH DIMENSIONS ARE SHOWN IN<br>BRACKETS |                 | This drawing and the information set forth hereon is the property of Tyco Electronics and is to be held in trust and confidence. Publication, duplication, disclosure or use for any other purpose not expressly authorized in writing by Tyco Electronics is prohibited. |  | DOCUMENT NO.<br><br><b>HEX40-AY-YY-YY-AYY-3-YY</b>                                              |                |                  |
| DRAWN:<br>CRJ                                                                                               | DATE:<br>MAR 00 | Tyco Electronics reserves the right to amend this drawing at any time. Users should evaluate the suitability of the product for their application.                                                                                                                        |  | FILE-UK:<br>Hex40-3scd-us                                                                       | SCALE:<br>NONE | SHEET:<br>1 OF 4 |

If this document is printed it becomes uncontrolled. Check with the web for the latest revision.



|                         |                              |                  |                        |
|-------------------------|------------------------------|------------------|------------------------|
| <b>CUSTOMER DRAWING</b> | REVISED PER<br>ECO-12-013789 | REV:<br><b>C</b> | DATE:<br>July 26, 2012 |
|-------------------------|------------------------------|------------------|------------------------|

## **PART NUMBERING**


|                                             |              |           |          |            |            |            |           |            |
|---------------------------------------------|--------------|-----------|----------|------------|------------|------------|-----------|------------|
|                                             | <b>HEX40</b> | <b>-A</b> | <b>B</b> | <b>-00</b> | <b>-21</b> | <b>-A9</b> | <b>-3</b> | <b>-DS</b> |
| - CONNECTOR CODE NUMBER                     |              |           |          |            |            |            |           |            |
| HEX40 = MIL-C-38999 SERIES III AND IV       |              |           |          |            |            |            |           |            |
| - MATERIAL CODE:                            |              |           |          |            |            |            |           |            |
| A = ALUMINIUM ALLOY                         |              |           |          |            |            |            |           |            |
| - PLATING CODE:                             |              |           |          |            |            |            |           |            |
| B = CADMIUM OLIVE DRAB TO QQ-P416           |              |           |          |            |            |            |           |            |
| C = ELECTROLESS NICKEL TO MIL-C-26074       |              |           |          |            |            |            |           |            |
| - BODY STYLE                                |              |           |          |            |            |            |           |            |
| 00 = STRAIGHT                               |              |           |          |            |            |            |           |            |
| 45 = 45°                                    |              |           |          |            |            |            |           |            |
| 90 = 90°                                    |              |           |          |            |            |            |           |            |
| - ORDER NUMBER                              |              |           |          |            |            |            |           |            |
| - FERRULE QUANTITY CODE                     |              |           |          |            |            |            |           |            |
| - 3 = BANDSTRAP CLAMPING NUT                |              |           |          |            |            |            |           |            |
| - DS = DRILLED STAR - OPTIONAL - SEE NOTE 2 |              |           |          |            |            |            |           |            |

## **APPLICATION**

- These adaptors are designed to be mounted on the following connectors:

MIL-C-38999 Series III and IV

- They are qualified to the Raychem specification RB-114, when installed on metallic Mil-Specification circular connectors only.
- They are designed primarily for open wire bundle installation having an overall braid, but are also designed to accept Raychem heat shrink moulded parts where strain relief is required – see illustration.



- Use in conjunction with the ferrules HET-A-\*\*\*, which are purchased separately. Refer to HET-A-\*\*\* S.C.D. for relevant selection details.

© 2012 Tyco Electronics Corporation. All rights reserved.

© 2012 Tyco Electronics Corporation. All rights reserved.

|                                                                                                             |                 |                                                                                                                                                                                                                                                                                       |  |                                                                                                 |                |                  |
|-------------------------------------------------------------------------------------------------------------|-----------------|---------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|--|-------------------------------------------------------------------------------------------------|----------------|------------------|
|                          |                 | Raychem Wire and Harnessing Products<br>300 Constitution Drive<br>Menlo Park, CA 94025<br>USA                                                                                                                                                                                         |  | TITLE:<br><br><b>HEXASHIELD ADAPTOR FOR<br/>CODE 40 CONNECTORS<br/>(BANDSTRAP CLAMPING NUT)</b> |                |                  |
| UNLESS OTHERWISE SPECIFIED<br>DIMENSIONS ARE IN<br>MILLIMETERS.<br>INCH DIMENSIONS ARE SHOWN IN<br>BRACKETS |                 | This drawing and the information set forth hereon is the<br>property of Tyco Electronics and is to be held in trust and<br>confidence. Publication, duplication, disclosure or use for<br>any other purpose not expressly authorized in writing by<br>Tyco Electronics is prohibited. |  | DOCUMENT NO.<br><br><b>HEX40-AY-YY-YY-AYY-3-YY</b>                                              |                |                  |
| DRAWN:<br>CRJ                                                                                               | DATE:<br>MAR 00 | Tyco Electronics reserves the right to amend this drawing at<br>any time. Users should evaluate the suitability of the<br>product for their application.                                                                                                                              |  | FILE-UK:<br>Hex40-3scd-us                                                                       | SCALE:<br>NONE | SHEET:<br>3 OF 4 |

If this document is printed it becomes uncontrolled. Check with the web for the latest revision.

# CUSTOMER DRAWING

REVISED PER  
ECO-12-013789

REV:  
**C**

DATE:  
July 26, 2012

## INSTALLATION


- See Installation Procedure RPIP-696-04.

## PACKAGING

- All components are supplied in a plastic bag.

## NOTES!

- Item 4 - Star - is **not** supplied with Hexashield Order Number 09.
- The DS option, illustrated below, is for a Drilled Star that is available on sizes 15 to 25 only. This option is to allow unshielded wires to pass through the assembly.




| STAR SIZE | 15             | 17             | 19             | 21              | 23              | 25              |
|-----------|----------------|----------------|----------------|-----------------|-----------------|-----------------|
| Ø T MAX   | 3.5<br>[0.14"] | 6.5<br>[0.26"] | 9.5<br>[0.37"] | 12.5<br>[0.48"] | 15.5<br>[0.61"] | 18.5<br>[0.73"] |

- Where the ferrule quantities required are standard, the item 4 - Star - is also standard.  
If the optional quantity is selected then 2 items 4 will be supplied - one "split" and the other one standard.  
See below for illustration.

EXAMPLE: FERRULE QUANTITY CODE -A13

-A13 = -A10 SPLIT STAR + -A3 STANDARD STAR



\* On Order Number 19 only, the Optional Ferrule quantity of 8 uses a "standard" star also.

- Assembly is to be permanently marked with Code Identity Number and Part Number.  
(e.g. 06090 HEX40-AB-00-21-A9-3)

© 2012 Tyco Electronics Corporation. All rights reserved.

|                                                                                                             |                 |                                                                                                                                                                                                                                                                                       |  |                                                                                                 |                |                  |
|-------------------------------------------------------------------------------------------------------------|-----------------|---------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|--|-------------------------------------------------------------------------------------------------|----------------|------------------|
|                          |                 | Raychem Wire and Harnessing Products<br>300 Constitution Drive<br>Menlo Park, CA 94025<br>USA                                                                                                                                                                                         |  | TITLE:<br><br><b>HEXASHIELD ADAPTOR FOR<br/>CODE 40 CONNECTORS<br/>(BANDSTRAP CLAMPING NUT)</b> |                |                  |
| UNLESS OTHERWISE SPECIFIED<br>DIMENSIONS ARE IN<br>MILLIMETERS.<br>INCH DIMENSIONS ARE SHOWN IN<br>BRACKETS |                 | This drawing and the information set forth hereon is the<br>property of Tyco Electronics and is to be held in trust and<br>confidence. Publication, duplication, disclosure or use for<br>any other purpose not expressly authorized in writing by<br>Tyco Electronics is prohibited. |  | DOCUMENT NO.<br><br><b>HEX40-AY-YY-YY-AYY-3-YY</b>                                              |                |                  |
| DRAWN:<br>CRJ                                                                                               | DATE:<br>MAR 00 | Tyco Electronics reserves the right to amend this drawing at<br>any time. Users should evaluate the suitability of the<br>product for their application.                                                                                                                              |  | FILE-UK:<br>Hex40-3scd-us                                                                       | SCALE:<br>NONE | SHEET:<br>4 OF 4 |

If this document is printed it becomes uncontrolled. Check with the web for the latest revision.



**Стандарт  
Электрон  
Связь**

Мы молодая и активно развивающаяся компания в области поставок электронных компонентов. Мы поставляем электронные компоненты отечественного и импортного производства напрямую от производителей и с крупнейших складов мира.

Благодаря сотрудничеству с мировыми поставщиками мы осуществляем комплексные и плановые поставки широчайшего спектра электронных компонентов.

Собственная эффективная логистика и склад в обеспечивает надежную поставку продукции в точно указанные сроки по всей России.

Мы осуществляем техническую поддержку нашим клиентам и предпродажную проверку качества продукции. На все поставляемые продукты мы предоставляем гарантию .

Осуществляем поставки продукции под контролем ВП МО РФ на предприятия военно-промышленного комплекса России , а также работаем в рамках 275 ФЗ с открытием отдельных счетов в уполномоченном банке. Система менеджмента качества компании соответствует требованиям ГОСТ ISO 9001.

Минимальные сроки поставки, гибкие цены, неограниченный ассортимент и индивидуальный подход к клиентам являются основой для выстраивания долгосрочного и эффективного сотрудничества с предприятиями радиоэлектронной промышленности, предприятиями ВПК и научно-исследовательскими институтами России.

С нами вы становитесь еще успешнее!

**Наши контакты:**

**Телефон:** +7 812 627 14 35

**Электронная почта:** [sales@st-electron.ru](mailto:sales@st-electron.ru)

**Адрес:** 198099, Санкт-Петербург,  
Промышленная ул, дом № 19, литера Н,  
помещение 100-Н Офис 331